



PO Box 2551  
2257 West Broadway  
South Portland, ME 04106

1.800.370.3473  
fax 207.879.0540

www.norrisinc.com

Please fax this information to the Administrative Sales Assistant at the So. Portland Office at (207)-879-0540.

## Building Owner Information Form

|                        |            |
|------------------------|------------|
| Job Name:              | Project #: |
| Electrical Contractor: |            |

## NFPA requires this information for proper documentation

***\*The contractor MUST provide all of the information with an  
asterisk below before ANY equipment can be released.***

*If building owner contact is unknown provide contact name/tel. of GC and check box*

|                                     |                         |
|-------------------------------------|-------------------------|
| Electrical Contractor Contact Name: |                         |
| Estimated Date Equip. Needed:       | *Estimated Finals Date: |

|                  |
|------------------|
| *Building Owner: |
|------------------|

|                    |
|--------------------|
| *Job Site Address: |
|--------------------|

|        |        |      |
|--------|--------|------|
| *City: | State: | Zip: |
|--------|--------|------|

|                |                  |
|----------------|------------------|
| *Contact Name: | Check here if GC |
| State          |                  |

|           |        |
|-----------|--------|
| *Phone #: | Fax #: |
|-----------|--------|



PO Box 2551  
2257 West Broadway  
South Portland, ME 04106

1.800.370.3473  
fax 207.879.0540

[www.norrisinc.com](http://www.norrisinc.com)

**Thank you for your cooperation.**

**Please advise the building owners that if this system is equipped with a digital communicator, then they MUST also make monitoring arrangements prior to a certificate of occupancy. Norris Inc. will attempt to contact the building owners**

---

# **STOP!**

**THIS COPY IS FOR YOUR ELECTRICIAN  
ON THE JOB-SITE**

**PLEASE BE SURE THIS COPY IS FORWARDED**

- 1) A riser diagram is enclosed. DO NOT USE THE ENGINEER'S RISER SHOWN ON THE PLANS. If there is any information that you question, call us immediately.**
  - 2) YOU MUST CALL AT LEAST FIVE DAYS IN ADVANCE TO SCHEDULE FINAL CONNECTION ASSISTANCE.**
  - 3) All of your wires must be labeled and clear of any grounds, shorts or opens and must maintain polarity throughout. Meter out all circuits before calling for final connection assistance. If applicable verify End of Line resistors are in place.**
  - 4) If using shielded cable, the drain wires must be connected and fully insulated (wrapped with tape) so that neither the shield or the drain wire touches the backbox.**
  - 5) Unless special arrangements are made, we will make one final job-site visit. If a special visit is required for an elevator inspection or partial occupancy, then additional charges may apply if special arrangements were not made ahead. Call your customer service representative.**
  - 6) If you have any defective or left-over parts DO NOT WRITE ON THEM OR THE BOXES. Save the original box, all mounting hardware and instructions. Returns that do not conform to this practice will not be accepted for credit.**
  - 7) If the system is being monitored through a digital communicator, then please turn to page 2.**
-



PO Box 2551  
2257 West Broadway  
South Portland, ME 04106

1.800.370.3473  
fax 207.879.0540

[www.norrisinc.com](http://www.norrisinc.com)

## **IMPORTANT INFORMATION FOR THE BUILDING OWNERS SPECIAL NOTE REGARDING ALARM MONITORING SERVICES**

**Included within your alarm system package is a digital communicator, which sends a coded message to a private 24-hour central station if your alarm system is activated. This is a code requirement for most fire alarm systems. As a service to our customer, we offer central station monitoring services from our local UL Listed central station at extremely competitive rates.**

**If the central station monitoring contract is purchased through Norris Inc. prior to our scheduled start-up; we will connect, program, and test the communicator at no additional charge.**

**Should the building owners decide to obtain monitoring services from another company, then the cost for programming and testing the communicator will be the sole responsibility of the firm they have contracted with. Furthermore, if programming changes are made to the system by persons other than Norris Inc. technicians, then the company performing the changes shall be solely liable for any personal injury or loss of life or damage to or loss of property arising out of the use of or inability to use the system and it shall result in a waiver of any system warranties.**

**We appreciate that you understand the delicate nature of this life safety and/or security system and realize that serious problems may arise when modifications to the system are made including very simple programming changes.**

**Call Norris Inc. at 1-800-370-FIRE (3473) to make  
arrangements for central station monitoring services.**





PO Box 2551  
2257 West Broadway  
South Portland, ME 04106

1.800.370.3473  
fax 207.879.0540

[www.norrisinc.com](http://www.norrisinc.com)

# ***SUBMITTAL PACKAGE***

**Project:** Ethan Allen – 145 Commercial St.

**System:** Fire Alarm System

**Submitted  
By:** Norris Inc.  
2257 West Broadway  
South Portland, Maine 04106  
Telephone: (800) 370-3473

**Electrical  
Contractor:** Deblois Electric Inc.  
PO Box 7899  
Lewiston, ME 04240

**Date:** October 1, 2013

## Company Profile

*"We are extremely proud to represent the highest quality manufacturers integrating life safety, alarm and communication systems throughout northern New England."*

**-- Bradford Norris, President --**

## Mission Statement


Provide quality engineered systems, exceptional service.

## Goal

Learn...Continually Improve...Exceed Expectations

Founded in 1979 Norris Inc. has grown to become Northern New England's leading integrated system contracting and supply company. Norris Inc. is an innovated proactive organization with extensive experience in integration interdisciplinary building management systems. Our local and national affiliations assure that your project will be done properly regardless of size representing leading manufacturers our comprehensive products provide outstanding quality reliability and performance... surpassing customer application requirements and exceeding the stringent requirements of Underwriters Laboratories, National Fire Protection Association and other codes. We maintain an exceptional level of quality and provide the highest levels of customer service. Our knowledgeable technical support will insure the great service you deserve. Whether your needs involve industrial, commercial, institutional, or educational applications, you can trust that Norris Inc. has the complete resources it takes to provide the right solution right away.

---



## **OUR CONTINUOUS COMMITMENT TO OUR ENVIRONMENT**

At Norris, Inc. we are proudly committed to continuous environmental improvement for a sustainable future and to develop strong partnerships within our community.

Our mission while running our operations is to do everything within our power to improve the environmental quality of our world and to work together to create a clean and safe place to live in and work in for future generations.

We will incorporate and promote green practices within our operations with policies to support it, a system of rewarding those that fully embrace it and then will regularly review our practices for continuous improvement.

We will establish policies, make investments in technologies and set the example in our own operations to include our ongoing commitment to go paperless and making it a requirement to Reuse, Reduce & Recycle, to turn off unneeded lights, to not allow our vehicles to idle, to encourage carpooling and to utilize practical energy efficient transportation.

We will always be 100% compliant with all applicable environmental laws and regulations and will report any violations.

We will remain committed to working locally and whenever possible to sell and use locally manufactured products.

We will insist that every purchase we make will include a review of its environmental impact with a very high priority to selecting the greenest products and services available.

We will remain committed to selling low energy products. This includes promoting wireless technologies, using existing wire infrastructures in our installations, promoting solar powered devices, using our Remote Services in lieu of on-site service calls and performing calculations to minimize power supply and battery needs.

We will educate our employees and customers to illustrate that green practices and purchases are almost always less costly in the long run.

We will support and give priority to organizations that show the strongest commitment to the environment.

We will actively encourage and promote the same responsible green practices that we utilize in the work place to our employees for use in their everyday personal lives.



PO Box 2551  
2257 West Broadway  
South Portland, ME 04106

1.800.370.3473  
fax 207.879.0540

[www.norrisinc.com](http://www.norrisinc.com)

## **LIMITED WARRANTY**

Norris, Inc. warrants that the products of its manufacturers shall be free from defects in materials or workmanship as warranted by the manufacturer which is typically for a one (1) year period from the completed installation date, but not always. The completed installation date will be the date when the end-user was able to begin using or started using the product(s) or the system, whether partially or in its entirety. For projects that have a specification or bid instructions to follow which contains specific warranty requirements, Norris Inc. will always honor the warranty terms exactly as specified in the project's specifications or bid documents, which may be more or less in coverage and duration than the manufacturer's warranty. In performing hundreds of projects per year with thousands of different products it is impossible for Norris, Inc. to track the terms and details of specified or individual product warranties. Therefore Norris, Inc. will request that the owner's representative provide these special warranty details when the warranty work is requested; otherwise a standard one year warranty on the equipment will be honored. The manufacturer's warranty is for equipment only and does not include any labor and/or shipping costs. All warranties provided by Norris, Inc. are limited with the same limitations included with the manufacturer's warranty which is included in the manuals of the products being provided.

The warranty will apply only if such goods have been properly installed, are subject to normal proper use and have not been modified in any manner whatsoever. Upon return of the defective product, Norris, Inc. will, at its sole discretion, either repair or replace, at no cost, such goods determined to have a defect in materials or workmanship. In cases of a warranty repair, Norris, Inc. will use its sole discretion to determine if a suitable replacement part can be provided on loan while the repairs are being performed.

All warranty work is performed during regular business hours. If emergency warranty work is required, the customer will pay the difference between the emergency service bill and our normal hourly charges.

Norris, Inc.'s limited warranty does not apply to those products that are damaged due to misuse, abuse, negligence, exposure to adverse environmental conditions, acts of God or have been modified in any manner whatsoever.


Norris, Inc.'s Standard terms and conditions are provided with our invoices. Those Terms and Conditions shall be provided upon request.

NORRIS, INC. SHALL NOT UNDER ANY CIRCUMSTANCES BE LIABLE FOR ANY INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING FROM LOSS OF LIFE &/OR PROPERTY OR OTHER DAMAGE OR LOSSES OWING TO THE FAILURE OF NORRIS INC. PRODUCTS BEYOND THE COST OF REPAIR OR REPLACEMENT OF ANY DEFECTIVE PRODUCTS.

NORRIS, INC. MAKES NO WARRANTY OF FITNESS OR MERCHANTABILITY AND NO OTHER WARRANTY, ORAL OR WRITTEN, EXPRESS OR IMPLIED AS ALLOWED TO THE FULLEST EXTENT OF THE LAW.



City of Portland/Portland Police Department  
Alarm Business/Agent Permit

The seal of the Portland Police Department is centered in the background. It is a circular emblem with a shield in the center. The shield has the word "POLICE" at the top and "PORTLAND" at the bottom. The shield is flanked by two figures, possibly representing justice and mercy, and topped by a crown. The entire seal is rendered in a light, faded green color.

Issued to  
**Norris, Inc.**  
Permit Number 1304  
Expires 12/31/2014





*This is to certify that*

**NORRIS, INC.**

*is an authorized Engineered Systems Distributor for NOTIFIER*

*During the years of 2013*

*Signed for and on behalf of NOTIFIER*

*Vice President Domestic Sales*



**Norris Inc**

2257 West Broadway

South Portland, ME 04106

1-800-370-3473

**DEBLOIS ELECTRIC INC.**

PO BOX 7899

LEWISTON, ME 04240-

**315841SP****Equipment List :**

Page: 1

**DEBLOI** 207-783-6512 Fax:207-783-7428**Ethan Allen-- 145 Commercial St.****Description**

NOTIFIER-NBG-12LX, Addressable Pull Station

NOTIFIER-FSP-851, Intelligent Address Photo detector; w/FlashScan.

NOTIFIER-B210LP, Conventional Flanged Mounting Base

NOTIFIER-FCPS-24S8, 8.0 amps, 120 VAC remote charger PS.

ADI-IM-1270, 12V 7AH Battery

NOTIFIER-FCM-1, Address Cntrl Mod. with FlashScan

GENTEX-GEC3-24WR, 24VDC Horn Strobe, Select. Cd, Wall Red

GENTEX-GES3-24WR, 24VDC Strobe Select. Cd, Wall Red

# ➤ NBG-12LX

## Addressable Manual Pull Station



Intelligent/Addressable Devices

### General

The Notifier NBG-12LX is a state-of-the-art, dual-action (i.e., requires two motions to activate the station) pull station that includes an addressable interface for any Notifier intelligent control panel except FireWarden series panels, and the NSP-25 panel. Because the NBG-12LX is addressable, the control panel can display the exact location of the activated manual station. This leads fire personnel quickly to the location of the alarm.

### Features

- Maintenance personnel can open station for inspection and address setting without causing an alarm condition.
- Built-in bicolor LED, which is visible through the handle of the station, flashes in normal operation and latches steady red when in alarm.
- Handle latches in down position and the word “ACTIVATED” appears to clearly indicate the station has been operated.
- Captive screw terminals wire-ready for easy connection to SLC loop (accepts up to 12 AWG/3.25 mm<sup>2</sup> wire).
- Can be surface mounted (with SB-10 or SB-I/O) or semi-flush mounted. Semi-flush mount to a standard single-gang, double-gang, or 4" (10.16 cm) square electrical box.
- Smooth dual-action design.
- Meets ADAAG controls and operating mechanisms guidelines (Section 4.1.3[13]); meets ADA requirement for 5 lb. maximum activation force.
- Highly visible.
- Attractive shape and textured finish.
- Key reset.
- Includes Braille text on station handle.
- Optional trim ring (BG12TR).
- Meets UL 38, Standard for Manually Actuated Signaling Boxes.
- Up to 99 NBG-12LX stations per loop on CLIP protocol loops.
- Up to 159 NBG-12LX stations per loop on FlashScan® protocol loops.
- Dual-color LED blinks green to indicate normal on FlashScan® systems.

### Construction

Shell, door, and handle are molded of durable polycarbonate material with a textured finish.

### Specifications

- **Shipping Weight:** 9.6 oz. (272.15 g)
- **Normal operating voltage:** 24 VDC.
- **Maximum SLC loop voltage:** 28.0 VDC.
- **Maximum SLC loop current:** 375 µA.
- **Temperature Range:** 32°F to 120°F (0°C to 49°C)
- **Relative Humidity:** 10% to 93% (noncondensing)
- **For use indoors in a dry location**



**The NBG-12LX**  
**Addressable Manual Pull Station**

### Installation

The NBG-12LX will mount semi-flush into a single-gang, double-gang, or standard 4" (10.16 cm) square electrical outlet box, or will surface mount to the model SB-10 or SB-I/O surface backbox. If the NBG-12LX is being semi-flush mounted, then the optional trim ring (BG12TR) may be used. The BG12TR is usually needed for semi-flush mounting with 4" (10.16 cm) or double-gang boxes (not with single-gang boxes).

### Operation

Pushing in, then pulling down on the handle causes it to latch in the down/activated position. Once latched, the word “ACTIVATED” (in bright yellow) appears at the top of the handle, while a portion of the handle protrudes from the bottom of the station. To reset the station, simply unlock the station with the key and pull the door open. This action resets the handle; closing the door automatically resets the switch.

Each manual station, on command from the control panel, sends data to the panel representing the state of the manual switch. Two rotary decimal switches allow address settings (1 – 159 on FlashScan® systems, 1 – 99 on CLIP systems).

### Architectural/Engineering Specifications

Manual Fire Alarm Stations shall be non-coded, with a key-operated reset lock in order that they may be tested, and so designed that after actual Emergency Operation, they cannot be restored to normal except by use of a key. An operated station shall automatically condition itself so as to be visually detected as activated. Manual stations shall be constructed of red-colored polycarbonate material with clearly visible operating instructions provided on the cover. The word FIRE shall appear on the front of the stations in white letters, 1.00 inches (2.54 cm) or larger. Stations shall be suitable for surface mounting on matching backbox SB-10 or SB-I/O; or semi-flush mounting on a standard single-gang, double-gang, or 4"



(10.16 cm) square electrical box, and shall be installed within the limits defined by the Americans with Disabilities Act (ADA) or per national/local requirements. Manual Stations shall be Underwriters Laboratories listed.

Manual stations shall connect with two wires to one of the control panel SLC loops. The manual station shall, on command from the control panel, send data to the panel representing the state of the manual switch. Manual stations shall provide address setting by use of rotary decimal switches.

The loop poll LED shall be clearly visible through the front of the station. The LED shall flash while in the normal condition, and stay steadily illuminated when in alarm.

## Product Line Information

**NBG-12LX:** Dual-action addressable pull station. Includes key locking feature.

**SB-10:** Surface backbox; metal.

**SB-I/O:** Surface backbox; plastic.

**BG12TR:** Optional trim ring.

**17021:** Keys, set of two.

**NY-Plate:** New York City trim plate

## Agency Listings and Approvals

In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL / CUL Listed:** S692 (listed for Canadian and non-Canadian applications)
- **MEA:** 67-02-E
- **CSFM:** 7150-0028:0199
- **FDNY:** COA #6038 (NFS2-640), COA #6058 (NFS2-3030)
- **BSMI:** CI313066760047
- **U.S. Coast Guard:** 161.002/23/3 (AFP-200); 161.002/27/3 (AM-2020/AFP-1010; 161.002/42/1 (NFS-640)
- **Lloyd's Register:** 02/6007 (NFS-640); 94/60004 (E2) (AFP-200); 03/60011 (E1); 07/60007 (NFS2-3030)
- **FM Approved**

**Patented:** U.S. Patent No. D428,351; 6,380,846; 6,314,772; 6,632,108.

---


Notifier® and FlashScan® are a registered trademarks of Honeywell International Inc.

©2010 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.

---



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



Made in the U.S. A.

# ➤ FSP-851(A) Series

## Intelligent Plug-In Photoelectric Smoke Detectors with FlashScan®



Intelligent/Addressable Devices

### General

Notifier FSP-851(A) Series intelligent plug-in smoke detectors with integral communication provide features that surpass conventional detectors. Detector sensitivity can be programmed in the control panel software. Sensitivity is continuously monitored and reported to the panel. Point ID capability allows each detector's address to be set with rotary, decimal address switches, providing exact detector location for selective maintenance when chamber contamination reaches an unacceptable level. The FSP-851(A) photoelectric detector's unique optical sensing chamber is engineered to sense smoke produced by a wide range of combustion sources. Dual electronic thermistors add 135°F (57°C) fixed-temperature thermal sensing on the FSP-851T(A). The FSP-851R(A) is a remote test capable detector for use with DNR(A)/DNRW duct detector housings. FSP-851(A) series detectors are compatible with Notifier Onyx and CLIP series Fire Alarm Control Panels (FACPs).

**FlashScan®** (U.S. Patent 5,539,389) is a communication protocol developed by Notifier that greatly increases the speed of communication between analog intelligent devices. Intelligent devices communicate in a grouped fashion. If one of the devices in the group has new information, the panel's CPU stops the group poll and concentrates on single points. The net effect is response speed greater than five times that of earlier designs.

### Features

- Sleek, low-profile design.
- Addressable-analog communication.
- Stable communication technique with noise immunity.
- Low standby current.
- Two-wire SLC connection.
- Compatible with FlashScan® and CLIP protocol systems.
- Rotary, decimal addressing (1-99 on CLIP systems, 1-159 on FlashScan systems).
- Optional remote, single-gang LED accessory.
- Dual LED design provides 360° viewing angle.
- Visible bi-color LEDs blink green every time the detector is addressed, and illuminate steady red on alarm (*FlashScan systems only*).
- Remote test feature from the panel.
- Walk test with address display (an address on 121 will blink the detector LED: 12-[pause]-1 (*FlashScan systems only*)).
- Built-in functional test switch activated by external magnet.
- Built-in tamper-resistant feature.
- Sealed against back pressure.
- Constructed of off-white fire-resistant plastic, designed to commercial standards, and offers an attractive appearance.
- 94-5V plastic flammability rating.
- SEMS screws for wiring of the separate base.
- Optional relay, isolator, and sounder bases.

### Specifications

**Sensitivity:** 0.5% to 2.35% per foot obscuration

**Size:** 2.1" (5.3 cm) high; base determines diameter.

- **B210LP(A):** 6.1" (15.5 cm) diameter.
- **B501(A):** 4.1" (10.4 cm) diameter.
- **B200S(A):** 6.875" (17.46 cm) diameter.



B210-2951.jpg

FSP-851(A) in B210LP(A) Base

- **B200SR(A):** 6.875" (17.46 cm) diameter.
- **B224RB(A):** 6.2" (15.748 cm) diameter.
- **B224BI(A):** 6.2" (15.748 cm) diameter.

**Shipping Weight:** 5.2oz. (147g).

**Operating Temperature range:** FSP-851(A), 0°C to 49°C (32°F to 120°F). FSP-851T(A), 0°C to 38°C (32°F to 100°F). Low temperature signal for FSP-851T(A) at 45°F +/- 10°F (7.22°C +/- 5.54°C). FSP-851R(A) installed in a DNR(A)/DNRW, -20°C to 70°C (-4°F to 158°F).

**UL/ULC Listed Velocity Range:** 0-4000 ft/min. (1219.2 m/min.), suitable for installation in ducts.

**Relative Humidity:** 10%-93% noncondensing.

**Thermal Ratings:** Fixed-temperature setpoint 135°F (57°C).

### DETECTOR SPACING AND APPLICATIONS

Notifier recommends spacing detectors in compliance with NFPA 72. In low airflow applications with smooth ceiling, space detectors 30 feet (9.144m) for ceiling heights 10 feet (3.148m) and higher. For specific information regarding detector spacing, placement, and special applications refer to NFPA 72. *System Smoke Detector Application Guide*, document A05-1003, is available at [systemsensor.com](http://systemsensor.com)

### ELECTRICAL SPECIFICATIONS

**Voltage Range:** 15-32 volts DC peak.

**Standby Current (max. avg.):** 300µA @ 24VDC (one communication every five seconds with LED enabled).

**LED Current (max.):** 6.5mA @ 24 VDC ("ON").

### Installation

FSP-851(A) plug-in detectors use a separate base to simplify installation, service, and maintenance. A special tool allows maintenance personnel to plug in and remove detectors without using a ladder.

Mount base (all base types) on an electrical backbox which is at least 1.5" (3.81 cm) deep. For a chart of compatible junction boxes, see DN-60054.

**NOTE:** 1) Because of inherent supervision provided by the SLC loop, end-of-line resistors are not required. Wiring "T-taps" or branches are permitted for Style 4 (Class "B") wiring. 2) When using relay or sounder bases, consult the ISO-X(A) installation

sheet 156-1380 for device limitations between isolator modules and isolator bases.

## Agency Listings and Approvals

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. *Consult factory for latest listing status.*

- **UL Listed:** S1115.
- **ULC Listed:** S1115 (FSP-851A, FSP-851RA, FSP-851TA).
- **MEA Listed:** 225-02-E .
- **FM Approved.**
- **CSFM:** 7272-0028:0206 .
- **Maryland State Fire Marshal:** Permit # 2122 .
- **BSMI:** CI313066760036.
- **CCCF:** Certif. # 2004081801000017 (FSP-851T)  
Certif. # 2004081801000016 (FSP-851).
- **U.S. Coast Guard:** 161.002/42/1 (NFS-640); 161.002/50/0 (NFS2-640/NFS-320/NFS-320C, excluding B210LP(A)).
- **Lloyd's Register:** 11/600013 (NFS2-640/NFS-320/NFS-320C, excluding B210LP(A)).

## Product Line Information

**NOTE:** "A" suffix indicates ULC Listed model.

➤ **FSP-851:** Low-profile intelligent photoelectric sensor. Must be mounted to one of the bases listed below.

**FSP-851A:** Same as FSP-851 but with ULC listing.

**FSP-851T:** Same as FSP-851 but includes a built-in 135°F (57°C) fixed-temperature thermal device.

**FSP-851TA:** Same as FSP-851T but with ULC listing.

**FSP-851R:** Low-profile intelligent photoelectric sensor, remote test capable. For use with DNRA/DNRW.

**FSP-851RA:** Same as FSP-851R but with ULC listing. For use with DNRA.

## INTELLIGENT BASES

**NOTE:** "A" suffix indicates ULC Listed model.

**NOTE:** For details on intelligent bases, see DN-60054.

**B210LP(A):** Standard U.S. flanged low-profile mounting base.

**B210LPBP:** Bulk pack of B210LP; package contains 10.

**B501(A):** Standard European flangeless mounting base.

**B501BP:** Bulk pack of B501; package contains 10.

**B200S(A):** Intelligent, programmable sounder base capable of producing sound output in high or low volume with ANSI Temporal 3, ANSI Temporal 4, continuous tone, marching tone, and custom tone.

**B200SR(A):** Intelligent sounder base capable of producing sound output with ANSI Temporal 3 or continuous tone. Replaces B501BH series bases in retrofit applications.

**B224RB(A):** Plug-in System Sensor **relay** base. Screw terminals: up to 14 AWG (2.0 mm²). Relay type: Form-C. Rating: 2.0 A @ 30 VDC resistive; 0.3 A @ 110 VDC inductive; 1.0 A @ 30 VDC inductive.

**B224BI(A):** Plug-in System Sensor **isolator** detector base. Maximum 25 devices between isolator bases .

## ACCESSORIES

**F110:** Retrofit flange to convert B210LP(A) to match the B710LP(A) profile, or to convert older high-profile bases to low-profile.

**F110BP:** Bulk pack of F110; package contains 15.

**F210:** Replacement flange for B210LP(A) base.

**RA100Z(A):** Remote LED annunciator. 3 – 32 VDC. Mounts to a U.S. single-gang electrical box. For use with B501(A) and B210LP(A) bases only.

**SMB600:** Surface mounting kit

**M02-04-00:** Test magnet.

**M02-09-00:** Test magnet with telescoping handle.

**XR2B:** Detector removal tool. Allows installation and/or removal of detector heads from bases in high ceiling applications.

**XP-4:** Extension pole for XR2B. Comes in three 5-foot (1.524 m) sections.

**T55-127-010:** Detector removal tool without pole.

**BCK-200B:** Black detector covers for use with FSP-851(A) only; box of 10.

**WCK-200B:** White detector covers for use with FSP-851(A) only; box of 10.

-Notifier® and FlashScan® are registered trademarks of Honeywell International Inc.

©2011 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



# Intelligent Bases

**B501(A), B200S(A), B200SR(A),  
B210LP(A), B2241BI(A), B224RB(A),  
Mounting Kits, and Accessories**



**Addressable Devices**

## General

Intelligent FlashScan® and CLIP mounting bases and kits provide a variety of ways to install NOTIFIER detectors in any application. Intelligent detectors can be mounted in either flanged or flangeless bases depending on junction box selection (see *Junction Box Selection Guide*). Across this product line, detectors plug in easily to the base with SEMS screws; and models employ various 12 to 24 AWG wire ranges.

**Relay, isolator, and sounder bases** can be used to meet local code requirements. Relay bases provide one Form-C contact relay for control of auxiliary functions such as door closure and elevator recall. Isolator bases allow loops to continue to operate under fault conditions and automatically restore when the fault is removed. Sounder bases are available in temporal and non-temporal pattern versions depending on whether the signal is to be used for evacuation purposes.

## Specifications

### Diameter:

- B501: 4.1" (104 mm).
- B224BI, B224RB, B210LP: 6.1" (155 mm).
- B200S/SR: 6.875" (17.46 cm).

### Wire gauge:

- B224BI, B224RB: 14 to 24 AWG.
- B210LP, B501, B200S/SR: 12 to 24 AWG.

### Temperature range:

- B224BI, B224RB, B200S/SR: 32°F to 120°F (0°C to 49°C).
- B210LP, B501: -4°F to 150°F (-20°C to 66°C).

**Humidity range:** 10% to 93% RH, non-condensing.

**System temperature and humidity ranges:** This system meets NFPA requirements for operation at 0°C to 49°C (32°F to 120°F); and at a relative humidity (noncondensing) of 85% at 30°C (86°F) per NFPA, and 93% ± 2% at 32°C ± 2°C (89.6°F ± 1.1°F) per ULC. However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and all peripherals be installed in an environment with a nominal room temperature of 15°C to 27°C (60°F to 80°F).

## Electrical Ratings

### FOR B200S/SR:

**External supply voltage:** 16 to 33 VDC (VFWR)

**Standby current:** 500 µA maximum.

### Alarm current:

- B200S: 25 mA maximum at high-volume setting; 15 mA maximum at low-volume setting.
- B200SR: 35 mA maximum.

**SLC operating voltage:** 15 to 32 VDC.

**SLC standby current:** 300 µA.



**Flangeless Mounting Base  
B501(A)**



**Flanged Mounting Base  
B210LP(A)**



**Sounder Base  
B200S(A), B200SR(A)**



**Relay Base  
B224RB(A)**

**Sound output:** measured in a UL reverberant room at 10 feet, 24 Volts (continuous tone).

- B200S, high-volume: Greater than 85 dBA minimum.
- B200S, low-volume: Greater than 75 dBA minimum.
- B200SR: Greater than 85 dBA minimum.

### FOR B224RB, B224BI:

**Operating voltage:** 15 to 32 VDC (powered by SLC).

**Standby ratings:** <500 µA maximum @ 24 VDC.

**Set time (B224RB only):** short delay 55 to 90 msec; long delay 6 to 9 seconds.

**Reset time (B224RB only):** 20 msec maximum.

**Relay characteristics (B224RB only):** two-coil latching relay; one Form-C contact; ratings (UL/CSA): 0.9 A @ 125 VAC, 0.9 A @ 110 VDC, and 3.0 A @ 30 VDC.

## Product Line Information

### INTELLIGENT BASES

**B501:** Flangeless mounting base.

**B501A:** Flangeless mounting base, ULC Listed.

**B501BP:** Bulk pack of B501 (10).

**B210LP:** Flanged mounting base.

**B210LPA:** Flanged mounting base, ULC listed

**B210LPBP:** Bulk pack of B210LP (10).

**B200S:** Intelligent addressable sounder base capable of producing sound output in high or low volume with ANSI Temporal 3, ANSI Temporal 4, continuous tone, marching tone, and custom tone.

**B200SA:** Same as B200S with ULC-listing.

**B200SR:** Intelligent sounder base capable of producing sound output with ANSI Temporal 3 or continuous tone.

**B200SRA:** Same as B200SR with ULC-listing.



**B224RB:** Relay base.

**B224RBA:** Relay base, ULC Listed.

**B224BI:** Isolator base.

**B224BIA:** Isolator base, ULC Listed.

### **MOUNTING KITS AND ACCESSORIES**

**SMB600:** Surface mounting kit, flanged.

**F110:** Retrofit flange for converting high-profile bases to low-profile.

**F110BP:** Bulk pack of F110 (10).

**F210:** Accessory flange ring for B210LP(A) base (new design). 6-inch diameter.

**F210BP:** Bulk pack of F210 (10).

**RA100Z:** Remote LED annunciator.

**RA100ZA:** Remote LED annunciator, ULC Listed.

**M02-04-00:** Detector test magnet.

**M02-09-00:** Test magnet with telescoping handle.

**XR2B:** Detector removal tool for current heads (*T55-127-010 included*).

**XR2:** Detector Remove Tool for use with low profile detector heads, and FSL-751.

**XP-4:** Extension pole for XR2/B (*5 to 15 ft/1.524 to 4.572 m*).

**T55-127-010:** Detector removal head.

**BCK-200B:** Black detector kit, package of 10 (for use with photo and ion detectors).

**WCK-200B:** White detector kit, package of 10 (for use with photo and ion detectors).

### **Agency Listings and Approvals**

The listings and approvals below apply to intelligent bases as noted. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL Listed:** S911
- **ULC Listed:** S911
- **FM Approved**
- **MEA:** 22-95-E, 205-94-E Vol. 2; 257-06-E
- **CSFM:** 7300-1653:0126, 7135-1653:0213, 7300-0028:0173, 7300-1653:0109

### **Junction Box Selection Guide**

| Base Models   | Single Gang | 3.5" Oct. | 4.0" Oct. | 4.0" Sq. | 4.0" Sq. with 3.0" mud ring | 50 mm | 60 mm | 70 mm | 75 mm |
|---------------|-------------|-----------|-----------|----------|-----------------------------|-------|-------|-------|-------|
| B200S, B200SR | Yes         | Yes       | Yes       | Yes      | Yes                         | No    | No    | No    | No    |
| B501          | No          | Yes       | No        | No       | Yes                         | Yes   | Yes   | Yes   | No    |
| B210LP        | Yes         | Yes       | Yes       | Yes      | Yes                         | No    | No    | No    | No    |
| B224RB        | No          | Yes       | Yes       | Yes      | No                          | No    | Yes   | Yes   | Yes   |
| B224BI        | No          | Yes       | Yes       | Yes      | No                          | No    | No    | Yes   | Yes   |

**NOTE:** Box depth contingent on base and wire size.  
Refer to National Electric Code or applicable local codes for appropriate recommendations.

FlashScan®, NOTIFIER® and System Sensor® are registered trademarks of Honeywell International Inc.  
©2011 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



## ➤ FCPS-24S6(C/E) & FCPS-24S8(C/E)

### 6- & 8-Amp 24-Volt Remote Power Supplies



Power Supplies


#### General

The FCPS-24S6E (6-amp) and FCPS-24S8E (8-amp) are remote power supplies with battery charger. The FCPS-24S6/-24S8 may be connected to any 12 or 24 volt fire alarm control panel (FACP) or may be used as stand-alone supplies. Primary applications include notification appliance (bell) circuit (NAC) expansion (to support ADA requirements and NAC synchronization) or auxiliary power to support 24 volt system accessories. The FCPS-24S6/-24S8 provides regulated and filtered 24 VDC power to four notification appliance circuits configured as either four Class B (Style Y) or Class A (Style Z, with ZNAC-4 option module). Alternately, the four outputs may be configured as all non-resettable, all resettable or two non-resettable and two resettable. The FCPS-24S6/-24S8 also contains a battery charger capable of charging up to 18 AH batteries. FCPS-24S6C & FCPS-24S8C are ULC-listed.

**NOTE:** Unless otherwise specified, the terms FCPS-24S6 and FCPS-24S8 used in this document refers to the standard FCPS-24S6 and FCPS-24S8, FCPS-24S6C and FCPS-24S8C, the FCPS-24S6E and FCPS-24S8E

#### Features

- UL-Listed NAC synchronization using System Sensor, Wheelock, or Gentex "Commander<sup>2</sup>" appliances.
- Operates as a "sync-follower" or as a "sync-generator" (default). See note on page 2.
- Contains two fully-isolated input/control circuits - triggered from FACP NAC (NAC expander mode) or jumped permanently "ON" (stand-alone mode).
- Four Class B (Style Y) or four Class A (Style Z, with ZNAC-4 module) NACs.
- 6-amp (FCPS-24S6) or 8-amp (FCPS-24S8) full load output, with 3 amps maximum/circuit, in NAC expander mode (UL 864).
- 4-amp (FCPS-24S6) or 6-amp (FCPS-24S8) continuous output in stand-alone mode (UL 1481).
- Compatible with coded inputs; signals passed through.
- Optional power-supervision relay (EOLR-1).
- In stand-alone mode, output power circuits may be configured as: resettable, (reset line from FACP required), non-resettable, or a mix of two and two.
- Fully regulated and filtered power output - optimal for powering four-wire smoke detectors, annunciators, and other system peripherals requiring regulated/filtered power.
- Power-limiting technology meets UL power-limiting requirements.
- Form-C normally-closed trouble relay.
- Fully supervised power supply, battery, and NACs.
- Selectable earth fault detection.
- AC trouble report selectable for immediate 2-hour delay.
- Works with virtually any UL 864 fire alarm control which utilizes an industry-standard reverse-polarity notification circuit (including unfiltered and unregulated bell power).
- Requires input trigger voltage of 9 - 32 VDC.
- Self-contained in compact, locking cabinet - 15"H x 14.5"W x 2.75"D (cm: 38.1H x 36.83W x 6.985D).



6927ph01.jpg

- Includes integral battery charger capable of charging up to 18 AH batteries. Cabinet capable of housing 7.0 AH batteries.
- Battery charger may be disabled via DIP switch for applications requiring larger batteries.
- Fixed, clamp-type terminal blocks accommodate up to 12 AWG (3.1mm<sup>2</sup>) wire.

#### Specifications

##### Primary (AC) Power:

- FCPS-24S6C/-24S8C: 120 VAC, 60 Hz, 3.2A maximum.
- FCPS-24S6E/-24S8E: 240 VAC, 50 Hz, 1.6A maximum.
- Wire Size: minimum #14 AWG (2.0mm<sup>2</sup>) with 600 V insulation.

##### Control Input Circuit:

- **Trigger Input Voltage:** 9 to 32 VDC.
- **Trigger Current:** 2.0 mA (16 - 32 V); Per Input: 1.0 mA (9 - 16 V).

##### Trouble Contact Rating: 5 A at 24 VDC.

**Auxiliary Power Output:** Specific application power 500 mA maximum.

##### Output Circuits:

- +24 VDC filtered, regulated.
- 3.0 A maximum for any one circuit.
- Total continuous current for all outputs (stand-alone mode):
  - FCPS-24S6: 4.0 A maximum.
  - FCPS-24S8: 6.0 A maximum.
- Total short-term current for all outputs (NAC expander mode):
  - FCPS-24S6: 6.0 A maximum.
  - FCPS-24S8: 8.0 A maximum.

##### Secondary Power (Battery) Charging Circuit:

- Supports lead-acid batteries only.
- Float-charge voltage: 27.6 VDC.

- Maximum current charge: 1.5 A.
- Maximum battery capacity: 18 AH.

## Applications

**Example 1:** Expand notification appliance power an additional 6.0 A (FCPS-24S6) or 8.0 A (FCPS-24S8). Use up to four Class B (Style Y) outputs or four Class A (Style Z) outputs (using ZNAC-4). For example, the FACP notification appliance circuits will activate the FCPS when reverse-polarity activation occurs. Trouble conditions on the FCPS are sensed by the FACP through the notification appliance circuit.

**Example 2:** Use the FCPS to expand auxiliary regulated 24-volt system power up to 4.0 A (FCPS-24S6) or up to 6.0 A (FCPS-24S8). Both resettable and non-resettable power options are available. Resettable outputs are created by connecting the resettable output from the FACP to one or both of the FCPS inputs.

**Example 3:** Use addressable control modules to activate the FCPS instead of activating it through the FACP notification appliance circuits. This typically allows for mounting the FCPS at greater distances\* away from the FACP while expanding system architecture in various applications.

For example, an addressable control module is used to activate the FCPS, and an addressable monitor module is used to sense FCPS trouble conditions. Local auxiliary power output from the FCPS provides power to the addressable control module.

*\*NOTE: Addressable FACP's are capable of locating control and monitor modules at distances of up to 12,500 feet (3,810 meters).*

## Sync Follower/Generator Note

In some installations, it is necessary to synchronize the flash timing of all strobes in the system for ADA compliance. Strokes accomplish this by monitoring very short timing pulses on the NAC power which are created by the FACP. When installed at the end of a NAC wire run, the FCPS-24S6/-24S8 can track (i.e. "follow") the strobe synchronization timing pulses on the existing NAC wire run. This maintains the overall system flash timing of the additional strobes attaches to the FCPS.

When the FCPS-24S6/-24S8 is configured (via DIP switch settings) as a "sync follower," the FCPS's NAC outputs track the strobe synchronization pulses present at the FCPS's sync input terminal. The pulses originate from an upstream FACP or other power supply.

When the FCPS-24S6/-24S8 are configured (via DIP switch settings) as a "sync generator," the FCPS's sync input terminals are not used. Rather, the FCPS is the originator of the strobe synchronization pulses on the FCPS's NAC outputs. In "sync generator" mode, the sync type (System Sensor, Wheelock, or Gentex) is selectable via DIP switch settings.

## Standards and Codes

The FCPS-24S6 and FCPS-24S8 comply with the following standards:

- **NFPA 72** National Fire Alarm Code.
- **UL 864** Standard for Control Units for Fire Alarm Systems (NAC expander mode).
- **UL 1481** Power Supplies for Fire Alarm Systems.

## Agency Listings and Approvals

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL Listed:** S635, S674
- **ULC Listed:** S635 (FCPS-24S6C & FCPS-24S8C)
- **CSFM Approved:** 7315-0028:225
- **MEA:** 299-02-E
- **FM Approved**

## Ordering Information

**FCPS-24S6:** 6.0 A, 120 VAC remote charger power supply. Includes main printed circuit board, transformers, enclosure (15"H x 14.5"W x 2.75"D [cm: 38.1H x 36.83W x 6.985D]), and installation instructions.

**FCPS-24S6C:** Same as above, ULC-listed.

**FCPS-24S6R:** Same as FCPS-24S6 with red enclosure.

**FCPS-24S6E:** 6.0 A, 240 VAC remote charger power supply. Includes main printed circuit board, transformers, enclosure (15"H x 14.5"W x 2.75"D [cm: 38.1H x 36.83W x 6.985D]), and installation instructions.

**FCPS-24S8:** 8.0 A, 120 VAC remote charger power supply. Includes main printed circuit board, transformers, enclosure (15"H x 14.5"W x 2.75"D [cm: 38.1H x 36.83W x 6.985D]), and installation instructions.

**FCPS-24S8C** Same as above, ULC-listed.

**FCPS-24S8R:** Same as FCPS-24S8 with red enclosure.

**FCPS-24S8E:** 8.0 A, 240 VAC remote charger power supply. Includes main printed circuit board, transformers, enclosure (15"H x 14.5"W x 2.75"D [cm: 38.1H x 36.83W x 6.985D]), and installation instructions.

**ZNAC-4:** Class A (Style Y) NAC option module.

**EOLR-1:** 12/24 VDC end-of-line relay for monitoring four-wire smoke detector power.

**BAT-1270:** Battery, 12-volt, 7.0 AH (two required, see BAT Series data sheet DN-6933).

**PS-1270:** Battery, 12-volt, 7.0 AH (two required, see PS Series data sheet DN-1109)

System Sensor® and NOTIFIER® are registered trademarks of Honeywell International Inc.

©2009 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



# ➤ BAT Series Batteries

## Sealed Lead-Acid or Gell Cell


**Power Supplies**

### General

**BAT Series Batteries** feature a new part-numbering/listing system — providing an improved method of delivery for NOTIFIER-approved sealed lead-acid batteries for all your fire alarm system needs. Multiple brands of batteries are now offered under generic part numbers, reducing backorder situations and permitting us to deliver these products in a more timely fashion. NOTIFIER has approved the multiple brands listed below as possible product shipped for a given part number. Please note that any incoming orders for “PS Series” batteries will be converted to the equivalent BAT Series part numbers.



6933cov.jpg

### Features

- Provide secondary power for control panels.
- Sealed and maintenance-free.
- Overcharge protected.
- Easy handling with leakproof construction.
- Ruggedly constructed, high-impact case (ABS, polystyrene, or polypropylene, depending on models).
- Long service life.
- Compact design.

### Agency Listings and Approvals

The listings and approvals below apply to BAT Series Batteries. In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL Recognized Components:** files MH19884 (*B & B Battery*), MH20567 (*UPG, previously Jolt*), MH20845 (*Power-Sonic*).

### Part Number Reference




| CURRENT Part Number | BATTERY DESCRIPTION      | ALTERNATES APPROVED: manufacturers and P/Ns shipped under BAT P/Ns                               |
|---------------------|--------------------------|--|
| BAT-1250            | 12 V, 5 AH, sealed.      | BP5-12 (B&B Battery); PS-1250 (Power-Sonic); SA1250 (Jolt) to be replaced with UB1250 (UPG).     |
| BAT-1250            | 12 V, 5 AH, sealed.      | BP5-12 (B&B Battery); PS-1250 (Power-Sonic); SA1250 (Jolt) to be replaced with UB1250 (UPG).     |
| ➤ BAT-1270          | 12 V, 7 AH, sealed.      | BP7-12 (B&B Battery); PS-1270 (Power-Sonic); SA1272 (Jolt) to be replaced with UB1270 (UPG).     |
| BAT-12120           | 12 V, 12 AH, sealed.     | BP12-12 (B&B Battery); PS-12120 (Power-Sonic); SA12120 (Jolt) to be replaced with UB12120 (UPG). |
| BAT-12180           | 12 V, 18 AH, sealed.     | PS-12180 (Power-Sonic); SA12180 (Jolt) to be replaced with UB12180 (UPG).                        |
| BAT-12180           | 12 V, 18 AH, sealed.     | PS-12180 (Power-Sonic); SA12180 (Jolt) to be replaced with UB12180 (UPG).                        |
| BAT-12260           | 12 V, 26 AH, sealed.     | BP26-12 (B&B Battery); PS-12260 (Power-Sonic); SA12260 (Jolt) to be replaced with UB12260 (UPG). |
| BAT-12550           | 12 V, 55 AH, sealed.     | PS-12550 (Power-Sonic); XSA12550 (Jolt) to be replaced with UB12550 (UPG).                       |
| BAT-12550           | 12 V, 55 AH, sealed.     | PS-12550 (Power-Sonic); XSA12550 (Jolt) to be replaced with UB12550 (UPG).                       |
| BAT-121000          | 12 V, 100 AH, gell cell. | PS-121000 (Power-Sonic); XSA121000A (Jolt) to be replaced with UB121000 (UPG).                   |




POWER-SONIC
Part Number Reference

1109t1.tbl

| MODEL     | Nominal Voltage V | Nominal Capacity @ 20 hr. rate A.H. | Discharge Current @20 hr. rate mA | DIMENSIONS |     |       |     |        |     |                      |     |        |      |
|-----------|-------------------|-------------------------------------|-----------------------------------|------------|-----|-------|-----|--------|-----|----------------------|-----|--------|------|
|           |                   |                                     |                                   | Width      |     | Depth |     | Height |     | Height over terminal |     | Weight |      |
|           |                   |                                     |                                   | in.        | mm  | in.   | mm  | in.    | mm  | in.                  | mm  | lb.    | kg.  |
| PS-1250   | 12                | 5                                   | 250                               | 3.54       | 90  | 2.76  | 70  | 4.02   | 102 | 4.21                 | 107 | 4.1    | 1.9  |
| PS-1270   | 12                | 7                                   | 325                               | 5.94       | 151 | 2.56  | 65  | 3.7    | 94  | 3.86                 | 98  | 5.7    | 2.6  |
| PS-12120  | 12                | 12                                  | 600                               | 5.94       | 151 | 3.86  | 98  | 3.7    | 94  | 3.86                 | 98  | 8.8    | 4    |
| PS-12180  | 12                | 18                                  | 875                               | 7.13       | 181 | 2.99  | 76  | 6.57   | 167 | 6.57                 | 167 | 12.8   | 5.8  |
| PS-12250  | 12                | 25                                  | 1300                              | 6.89       | 175 | 6.54  | 166 | 4.92   | 125 | 4.92                 | 125 | 18.7   | 8.5  |
| PS-12550  | 12                | 55                                  | 3000                              | 10.25      | 260 | 6.6   | 168 | 8.2    | 208 | 9.45                 | 240 | 39.7   | 18   |
| PS-121000 | 12                | 100                                 | 5000                              | 12         | 305 | 6.6   | 168 | 8.2    | 208 | 9.45                 | 240 | 65.7   | 29.8 |



at left:  
PS-121000  
Shelf-Life  
and Storage



at left:  
PS-1210000  
Discharge  
Characteristics

## B & B BATTERY

| Model   | V  | Nominal Capacity (AH) |       |       |       | Weight |       | Terminal |      |          |      | Dimensions |      |     |      |     |      |     |      |
|---------|----|-----------------------|-------|-------|-------|--------|-------|----------|------|----------|------|------------|------|-----|------|-----|------|-----|------|
|         |    |                       |       |       |       |        |       | Standard |      | Optional |      | L          |      | W   |      | H   |      | TH  |      |
|         |    | 20 hr                 | 10 hr | 5 hr  | 1 hr  | kg     | lbs   | Type     | Pos. | Type     | Pos. | mm         | in   | mm  | in   | mm  | in   | mm  | in   |
| BP5-12  | 12 | 5.00                  | 4.75  | 4.25  | 3.00  | 1.86   | 4.10  | T1       | 3    | T2       |      | 90         | 3.54 | 70  | 2.76 | 102 | 4.02 | 106 | 4.17 |
| BP7-12  | 12 | 7.00                  | 6.65  | 5.95  | 4.20  | 2.60   | 5.73  | T2       | 5    | T1       |      | 151        | 5.94 | 65  | 2.56 | 93  | 3.66 | 98  | 3.86 |
| BP12-12 | 12 | 12.00                 | 11.40 | 10.20 | 7.20  | 4.03   | 8.89  | B1       | 5    | T1       |      | 151        | 5.94 | 98  | 3.86 | 94  | 3.70 | 98  | 3.86 |
| BP26-12 | 12 | 26.00                 | 24.70 | 22.10 | 15.60 | 9.40   | 20.73 | B1       | 7    | T2.11    | 9    | 175        | 6.89 | 166 | 6.54 | 125 | 4.92 | 125 | 4.92 |

### Charging Procedure

| Application              | Charging method   | Charging voltage at 20°C (V/cell) | Temperature compensation coefficient of charging voltage (mV/°C/cell) | Maximum charging current (CA) | Charging time 0.1 CA, 20°C (h) |               | Temp (°C)                |
|--------------------------|---|-----------------------------------|---|-------------------------------|--------------------------------|---------------|--------------------------|
|                          |   |                                   |   |                               | 100% discharge                 | 50% discharge |                          |
| For standby power source | Constant voltage and constant current charging (with current restriction) | 2.25 ~ 2.30                       | - 3   | 0.3                           | 24                             | 20            | 0 ~ 40°C<br>(32 ~ 104°F) |
| For cycle service        |   | 2.40 ~ 2.50                       | - 4   | 0.3                           | 16                             | 10            |                          |

Temperature compensation of charging voltage is not needed when using the batteries within 5°C to 35°C range.

| Final Voltage | Discharge Time: for Model BP5-12           |        |        |        |       |       |       |       |       |
|---------------|--|--------|--------|--------|-------|-------|-------|-------|-------|
|               | 5 min                                      | 10 min | 15 min | 30 min | 1 hr  | 3 hr  | 5 hr  | 10 hr | 20 hr |
|               | Battery Output Power (W): for Model BP5-12 |        |        |        |       |       |       |       |       |
| 10.80 V       | 180.8                                      | 133.1  | 106.6  | 63.5   | 36.39 | 14.57 | 10.05 | 5.62  | 2.94  |
| 10.50 V       | 209.2                                      | 144.2  | 111.5  | 65.9   | 37.48 | 14.87 | 10.20 | 5.70  | 3.00  |
| 10.20 V       | 222.3                                      | 149.4  | 115.0  | 67.4   | 38.16 | 15.00 | 10.26 | 5.73  | 3.01  |
| 9.90 V        | 232.3                                      | 152.9  | 117.6  | 68.3   | 38.61 | 15.10 | 10.29 | 5.75  | 3.02  |
| 9.60 V        | 240.0                                      | 156.0  | 120.0  | 69.0   | 39.0  | 15.20 | 10.32 | 5.75  | 3.02  |

**Constant Power Discharge Characteristics at 25°C/77°F for BP5-12**

| Final Voltage | Discharge Time: for Model BP7-12           |        |        |        |       |       |       |       |       |
|---------------|--|--------|--------|--------|-------|-------|-------|-------|-------|
|               | 5 min                                      | 10 min | 15 min | 30 min | 1 hr  | 3 hr  | 5 hr  | 10 hr | 20 hr |
|               | Battery Output Power (W): for Model BP7-12 |        |        |        |       |       |       |       |       |
| 10.80 V       | 253.1                                      | 186.3  | 149.3  | 88.8   | 50.95 | 20.40 | 14.07 | 7.86  | 4.11  |
| 10.50 V       | 292.9                                      | 201.8  | 156.2  | 92.2   | 52.47 | 20.81 | 14.28 | 7.98  | 4.20  |
| 10.20 V       | 311.2                                      | 209.1  | 161.0  | 94.3   | 53.42 | 21.00 | 14.36 | 8.02  | 4.22  |
| 9.90 V        | 325.2                                      | 214.1  | 164.7  | 95.6   | 54.06 | 21.15 | 14.41 | 8.04  | 4.23  |
| 9.60 V        | 336.0                                      | 218.4  | 168.0  | 96.6   | 54.60 | 21.27 | 14.45 | 8.04  | 4.23  |

**Constant Power Discharge Characteristics at 25°C/77°F for BP7-12**

| Final Voltage | Discharge Time: for Model BP12-12           |        |        |        |       |       |       |       |       |
|---------------|---|--------|--------|--------|-------|-------|-------|-------|-------|
|               | 5 min                                       | 10 min | 15 min | 30 min | 1 hr  | 3 hr  | 5 hr  | 10 hr | 20 hr |
|               | Battery Output Power (W): for Model BP12-12 |        |        |        |       |       |       |       |       |
| 10.80 V       | 433.9                                       | 319.4  | 256.0  | 152.3  | 87.34 | 34.98 | 24.12 | 13.48 | 7.05  |
| 10.50 V       | 502.2                                       | 346.0  | 267.7  | 158.1  | 89.96 | 35.68 | 24.48 | 13.68 | 7.20  |
| 10.20 V       | 533.6                                       | 358.5  | 276.0  | 161.7  | 91.57 | 36.00 | 24.61 | 13.75 | 7.23  |
| 9.90 V        | 557.5                                       | 367.1  | 282.4  | 164.0  | 92.67 | 36.25 | 24.70 | 13.79 | 7.25  |
| 9.60 V        | 576.0                                       | 374.4  | 288.0  | 165.6  | 93.60 | 36.47 | 24.77 | 13.79 | 7.25  |


**Constant Power Discharge Characteristics at 25°C/77°F for BP12-12**

| Final Voltage | Discharge Time: for Model BP26-12           |        |        |        |        |       |       |       |       |
|---------------|---|--------|--------|--------|--------|-------|-------|-------|-------|
|               | 5 min                                       | 10 min | 15 min | 30 min | 1 hr   | 3 hr  | 5 hr  | 10 hr | 20 hr |
|               | Battery Output Power (W): for Model BP26-12 |        |        |        |        |       |       |       |       |
| 10.80 V       | 940.0                                       | 692.0  | 554.6  | 330.0  | 189.23 | 75.79 | 52.25 | 29.20 | 15.26 |
| 10.50 V       | 1088.0                                      | 749.7  | 580.0  | 342.5  | 194.91 | 77.30 | 53.04 | 29.64 | 15.60 |
| 10.20 V       | 1156.0                                      | 776.7  | 598.0  | 350.3  | 198.41 | 78.00 | 53.33 | 29.79 | 15.67 |
| 9.90 V        | 1208.0                                      | 795.3  | 611.8  | 355.2  | 200.79 | 78.54 | 53.52 | 29.88 | 15.71 |
| 9.60 V        | 1248.0                                      | 811.2  | 624.0  | 358.8  | 202.80 | 79.01 | 53.68 | 29.88 | 15.71 |


**Constant Power Discharge Characteristics at 25°C/77°F for BP26-12**

# B & B BATTERY


**BP5-12 Battery Discharge Characteristics (25°C/77°F)**




**BP12-12 Battery Discharge Characteristics (25°C/77°F)**



**BP7-12 Battery Discharge Characteristics (25°C/77°F)**



**BP26-12 Battery Discharge Characteristics (25°C/77°F)**



**BP05-12**



**BP12-12**



**BP26-12**




# UPG BATTERY


UB1250 has the same specifications as previous Jolt SA1250;  
SA1272 to be replaced with UB1270 (specs/diagrams pending).

## UB1250 (previously SA1250) Diagrams

UB1250/SA1250 discharge current vs. time



UB1250/SA1250 discharge characteristics (25°C/77°F)




## UB1250, SA1250 Specifications


- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 5.0 AH.
- Dimensions: total height 107 mm (4.21"); container height 101 mm (3.98"); length 90 mm (3.54"); width 70 mm (2.76").
- Weight: approximately 1.83 kg (4.03 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 32 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 0.25 A: 5.0 AH.
  - 5 hr @ 0.8 A: 4.0 AH.
  - 1 hr @ 3.0 A: 3.0 AH.
  - 1 C @ 5.0 A: 2.5 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 60 A (5 sec).
- Maximum charging current: 1.5 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.

## SA1272 Diagrams

SA1272 discharge current vs. time



SA1272 discharge characteristics (25°C/77°F)



## SA1272 Specifications

- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 7.2 AH.
- Dimensions: total height 100 mm (3.94"); container height 94 mm (3.70"); length 151 mm (5.95"); width 65 mm (2.56").
- Weight: approximately 2.66 kg (5.85 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 22 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 0.36 A: 7.2 AH.
  - 5 hr @ 1.15 A: 5.76 AH.
  - 1 hr @ 4.32 A: 4.32 AH.
  - 1 C @ 7.2 A: 3.6 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 90 A (5 sec).
- Maximum charging current: 2.16 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.




# UPG BATTERY

Same specifications as previous Jolt models;  
packaging and part numbers are the only changes.


## UB12120 (was SA12120) Diagrams

UB12120/SA12120 discharge current vs. time



6933up05.tif

UB12120/SA12120 discharge characteristics (25°C/77°F)




6933up06.tif

## UB12120, SA12120 Specifications

- Nominal voltage: 12 V.
  - Nominal capacity (20 hr): 12.0 AH.
  - Dimensions: total height 100 mm (3.94"); container height 94 mm (3.70"); length 151 mm (5.95"); width 98 mm (3.86").
  - Weight: approximately 4.10 kg (9.04 lbs).
  - Container material: UL94HB ABS, UL94V-0 ABS.
  - Internal resistance (25°C, 77°F): ~ 14 m.
  - Discharge capacity under different temperatures:
    - 40°C: ~ 102%
    - 25°C: ~ 100%
    - 0°C: ~ 85%
  - Capacity 25°C/77°F:
    - 20 hr @ 0.6 A: 12.0 AH.
    - 5 hr @ 1.92 A: 9.6 AH.
    - 1 hr @ 7.2 A: 7.2 AH.
    - 1 C @ 12.0 A: 6.0 AH.
  - Charging voltage (25°C, 77°F):
    - Standby use: 13.65 V ± 0.15 V.
    - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 120 A (5 sec).  
Maximum charging current: 3.6 A.  
Self-discharge residual capacity (25°C, 77°F):  
After 3 months: ~ 90%.  
After 6 months: ~ 82%.  
After 12 months: ~ 70%.


## UB12180 (was SA12180) Diagrams

UB12180/SA12180 discharge current vs. time



6933up07.tif

UB12180/SA12180 discharge characteristics (25°C/77°F)



6933up08.tif

## UB12180, SA12180 Specifications


- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 18.0 AH.
- Dimensions: total height 167 mm (6.58"); container height 167 mm (6.58"); length 181 mm (7.13"); width 76 mm (2.99").
- Weight: approximately 6.06 kg (13.36 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 13 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 0.9 A: 18.0 AH.
  - 5 hr @ 2.88 A: 14.4 AH.
  - 1 hr @ 10.8 A: 10.8 AH.
  - 1 C @ 18.0 A: 9.0 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 300 A (5 sec).
- Maximum charging current: 5.4 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.

# UPG BATTERY

Same specifications as previous Jolt models;  
packaging and part numbers are the only changes.


## UB12260 (was SA12260) Diagrams

UB12260/SA12260 discharge current vs. time



6933up09.tif

UB12260/SA12260 discharge characteristics (25°C/77°F)




6933up10.tif

## UB12260, SA12260 Specifications

- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 26.0 AH.
- Dimensions: total height 125 mm (4.92"); container height 125 mm (4.92"); length 166 mm (6.54"); width 175 mm (6.89").
- Weight: approximately 8.80 kg (19.40 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 10 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 1.3 A: 26.0 AH.
  - 5 hr @ 4.16 A: 20.8 AH.
  - 1 hr @ 15.6 A: 15.6 AH.
  - 1 C @ 26.0 A: 13.0 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 300 A (5 sec).
- Maximum charging current: 7.8 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.


## UB12550 (was SA12550) Diagrams

UB12550/SA12550 discharge current vs. time



6933up11.tif

UB12550/SA12550 discharge characteristics (25°C/77°F)



6933up12.tif

## UB12550, SA12550 Specifications


- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 55.0 AH.
- Dimensions: total height 234.5 mm (9.23"); container height 216.5 mm (8.52"); length 229 mm (9.02"); width 138 mm (5.43").
- Weight: approximately 19.0 kg (41.8 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 8 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 2.75 A: 55.0 AH.
  - 5 hr @ 8.8 A: 44.0 AH.
  - 1 hr @ 33.0 A: 33.0 AH.
  - 1 C @ 55.0 A: 27.5 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 600 A (5 sec).
- Maximum charging current: 16.5 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.

# UPG BATTERY

Same specifications as previous Jolt models;  
packaging and part numbers are the only changes.


## UB121000 (XSA121000A) Diagrams

UB121000/XSA121000A discharge current vs. time



6933up13.tif

UB121000/XSA121000A discharge characteristics (25°C/77°F)




6933up14.tif

## UB121000 (XSA121000A) Diagrams

- Nominal voltage: 12 V.
- Nominal capacity (20 hr): 100.0 AH.
- Dimensions: total height 221 mm (8.70"); container height 214 mm (8.43"); length 329 mm (12.95"); width 172 mm (6.77").
- Weight: approximately 34.00 kg (74.8 lbs).
- Container material: UL94HB ABS, UL94V-0 ABS.
- Internal resistance (25°C, 77°F): ~ 6.5 m.
- Discharge capacity under different temperatures:
  - 40°C: ~ 102%
  - 25°C: ~ 100%
  - 0°C: ~ 85%
- Capacity 25°C/77°F:
  - 20 hr @ 5.0 A: 100.0 AH.
  - 5 hr @ 16.0 A: 80.0 AH.
  - 1 hr @ 60.0 A: 60.0 AH.
  - 1 C @ 100.0 A: 50.0 AH.
- Charging voltage (25°C, 77°F):
  - Standby use: 13.65 V ± 0.15 V.
  - Cycle use: 14.7 V ± 0.3 V.
- Maximum discharge current: 600 A (5 sec).
- Maximum charging current: 30 A.
- Self-discharge residual capacity (25°C, 77°F):
  - After 3 months: ~ 90%.
  - After 6 months: ~ 82%.
  - After 12 months: ~ 70%.


## UPG Summary Diagrams

Summary discharge characteristics



6933up15.wmf

Summary discharge current vs. time curve (25°C/77°F)



6933up16.wmf



6933ub1280.jpg



6933ub12260.jpg

## UPG BATTERY

Same specifications as previous Jolt models;  
packaging and part numbers are the only changes.

### Charging Procedure: UPG Battery

| Application              | Charging method   | Charging voltage at 25°C (V/cell) | Temperature compensation coefficient of charging voltage (mV/°C/cell) | Maximum charging current (CA) | Charging time 0.1 CA, 25°C (h) |                   | Temp (°C)                |
|--------------------------|---|-----------------------------------|---|-------------------------------|--------------------------------|-------------------|--------------------------|
|                          |   |                                   |   |                               | 100% discharge                 | 50% discharge     |                          |
| For standby power source | Constant voltage and constant current charging (with current restriction) | 2.25 ~ 2.30                       | - 3.3<br>(-1.8 mV/°F/cell)  | 0.3                           | T <sup>3</sup> 24              | T <sup>3</sup> 20 | 0 – 40°C<br>(32 – 104°F) |
| For cycle service        |   | 2.40 ~ 2.50                       | - 5<br>(-2.8 mV/°F/cell)  | 0.3                           | 16 < T < 24                    | 10 < T < 24       |                          |

Temperature compensation of charging voltage is not needed when using the batteries within 5°C to 35°C range.



---

**NOTIFIER®** is a registered trademark of Honeywell International Inc.  
Batteries display trademarks of the manufacturer.  
©2009 by Honeywell International Inc. All rights reserved. Unauthorized use  
of this document is strictly prohibited.

---



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.

# FCM-1(A) & FRM-1(A) Series

## Control and Relay Modules



Intelligent / Addressable Devices

### General

**FCM-1(A) Control Module:** The FCM-1(A) Addressable Control Module provides Notifier intelligent fire alarm control panels a circuit for Notification Appliances (horns, strobes, speakers, etc.) Addressability allows the FCM-1(A) to be activated, either manually or through panel programming, on a select (zone or area of coverage) basis.

**FRM-1(A) Relay Module:** The FRM-1(A) Addressable Relay Module provides the system with a dry-contact output for activating a variety of auxiliary devices, such as fans, dampers, control equipment, etc. Addressability allows the dry contact to be activated, either manually or through panel programming, on a select basis.

FlashScan® (U.S. Patent 5,539,389) is a communication protocol developed by NOTIFIER Engineering that greatly enhances the speed of communication between analog intelligent devices. Intelligent devices communicate in a grouped fashion. If one of the devices within the group has new information, the panel CPU stops the group poll and concentrates on single points. The net effect is response speed greater than five times that of other designs.



FCM-1(A)

### Features

- Built-in type identification automatically identifies these devices to the control panel.
- Internal circuitry and relay powered directly by two-wire SLC loop. The FCM-1(A) module requires power (for horns, strobes, etc.), or audio (for speakers).
- Integral LED “blinks” green each time a communication is received from the control panel and turns on in steady red when activated.
- LED blink may be deselected globally (affects all devices).
- High noise immunity (EMF/RFI).
- The FCM-1(A) may be used to switch 24-volt NAC power, audio (up to 70.7 Vrms).
- Wide viewing angle of LED.
- SEMS screws with clamping plates for wiring ease.
- Direct-dial entry of address 01– 159 for FlashScan loops, 01 – 99 for CLIP mode loops.
- Speaker, and audible/visual applications may be wired for Class B or A (Style Y or Z).

### Applications

The FCM-1(A) is used to switch 24 VDC audible/visual power, high-level audio (speakers), or control telephone devices. The FRM-1(A) may be programmed to operate dry contacts for applications such as door holders or Air Handling Unit shut-down, and to reset four-wire smoke detector power.

**NOTE:** Refer to the SLC Manual (PN 51253) for details regarding releasing applications with the FCM-1(A). Refer to the FCM-1-REL datasheet (DN-60390) for new FlashScan® releasing applications.

### Construction

- The face plate is made of off-white heat-resistant plastic.
- Controls include two rotary switches for direct-dial entry of address (01-159).

- The FCM-1(A) is configured for a single Class B (Style Y) or Class A (Style Z) Notification Appliance Circuit.
- The FRM-1(A) provides two Form-C dry contacts that switch together.

### Operation

Each FCM-1(A) or FRM-1(A) uses one of 159 possible module addresses on a SLC loop (99 on CLIP loops). It responds to regular polls from the control panel and reports its type and status, including the open/normal/short status of its Notification Appliance Circuit (NAC). The LED blinks with each poll received. On command, it activates its internal relay. The FCM-1(A) supervises Class B (Style Y) or Class A (Style Z) notification or control circuits.

Upon code command from the panel, the FCM-1(A) will disconnect the supervision and connect the external power supply in the proper polarity across the load device. The disconnection of the supervision provides a positive indication to the panel that the control relay actually turned ON. The external power supply is always relay isolated from the communication loop so that a trouble condition on the external power supply will never interfere with the rest of the system.

Rotary switches set a unique address for each module. The address may be set before or after mounting. The built-in TYPE CODE (not settable) will identify the module to the control panel, so as to differentiate between a module and a sensor address.

### Specifications for FCM-1(A)

**Normal operating voltage:** 15 to 32 VDC.

**Maximum current draw:** 6.5 mA (LED on).

**Average operating current:** 350  $\mu$ A direct poll, 375  $\mu$ A group poll with LED flashing, 485  $\mu$ A Max. (LED flashing, NAC shorted.)

**Maximum NAC Line Loss:** 4 VDC.

**External supply voltage (between Terminals T10 and T11):** Maximum (NAC): Regulated 24 VDC; Maximum (Speakers): 70.7 V RMS, 50W.

**Drain on external supply:** 1.7 mA maximum using 24 VDC supply; 2.2 mA Maximum using 80 VRMS supply.

**Max NAC Current Ratings:** For class B wiring system, the current rating is 3A; For class A wiring system, the current rating is 2A.

**Temperature range:** 32°F to 120°F (0°C to 49°C).

**Humidity range:** 10% to 93% non-condensing.

**Dimensions:** 4.5" (114.3 mm) high x 4" (101.6 mm) wide x 1.25" (31.75 mm) deep. Mounts to a 4" (101.6 mm) square x 2.125" (53.975 mm) deep box.

**Accessories:** SMB500 Electrical Box; CB500 Barrier

## Specifications for FRM-1(A)

**Normal operating voltage:** 15 to 32 VDC.

**Maximum current draw:** 6.5 mA (LED on).

**Average operating current:** 230  $\mu$ A direct poll; 255  $\mu$ A group poll.

**EOL resistance:** not used.

**Temperature range:** 32°F to 120°F (0°C to 49°C).

**Humidity range:** 10% to 93% non-condensing.

**Dimensions:** 4.5" (114.3 mm) high x 4" (101.6 mm) wide x 1.25" (31.75 mm) deep. Mounts to a 4" (101.6 mm) square x 2.125" (53.975 mm) deep box.

**Accessories:** SMB500 Electrical Box; CB500 Barrier

## Agency Listings and Approvals

In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL:** S635
- **ULC:** S3705 (A version only)
- **FM Approved**
- **CSFM:** 7300-0028:202, 7300-0028:219
- **MEA:** 14-00-E
- **FDNY:** COA #6038, #6026

## Contact Ratings for FRM-1(A)

| Current Rating | Maximum Voltage | Load Description    | Application |
|----------------|-----------------|---------------------|-------------|
| 3 A            | 30 VDC          | Resistive           | Non-Coded   |
| 2 A            | 30 VDC          | Resistive           | Coded       |
| .9 A           | 110 VDC         | Resistive           | Non-Coded   |
| .9 A           | 125 VDC         | Resistive           | Non-Coded   |
| .5 A           | 30 VDC          | Inductive (L/R=5ms) | Coded       |
| 1 A            | 30 VDC          | Inductive (L/R=2ms) | Coded       |
| .3 A           | 125 VAC         | Inductive (PF=0.35) | Non-Coded   |
| 1.5 A          | 25 VAC          | Inductive (PF=0.35) | Non-Coded   |
| .7 A           | 70.7 VAC        | Inductive (PF=0.35) | Non-Coded   |
| 2 A            | 25 VAC          | Inductive (PF=0.35) | Non-Coded   |

**NOTE:** Maximum (Speakers): 70.7 V RMS, 50 W

## Product Line Information

**NOTE:** "A" suffix indicates ULC Listed model.

**FCM-1(A):** Intelligent Addressable Control Module.

**FRM-1(A):** Intelligent Addressable Relay Module.

**A2143-20:** Capacitor, required for Class A (Style Z) operation of speakers.

**SMB500:** Optional Surface-Mount Backbox.

**CB500:** Control Module Barrier — required by UL for separating power-limited and non-power limited wiring in the same junction box as FCM-1(A).

**NOTE:** For installation instructions, see the following documents:

- *FCM-1(A) Installation document I56-1169.*
- *FRM-1(A) Installation document I56-3502.*
- *Notifier SLC Wiring Manual, document 51253.*

**Notifier®** and **FlashScan®** are registered trademarks of Honeywell International Inc.

©2010 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.



## Commander<sup>3</sup> Series Selectable Candela Evacuation Signals

### Applications

The Commander<sup>3</sup> Series is a low profile strobe and horn/strobe combination that offers dependable audible and visual alarms and the lowest current available.

The GE3 Series 24VDC offers tamperproof field selectable candela options of 15, 30, 60, 75, and 110 candela. The 12VDC offers tamperproof field selectable candela options of 15, 30, 60, and 75 candela.

The Commander<sup>3</sup> Series horn offers a continuous or synchable temporal three in 2400Hz and mechanical tone, a chime and whoop tone. All tones are easy for the professional to change in the field by using switches.

The GE3 Series has a minimal operation current and has a minimum flash rate of 1Hz regardless of input voltage.

The Commander<sup>3</sup> Series is shipped with the standard 4" metal mounting plate which incorporates the popular *Super-Slide™* feature that allows the installer to easily test for supervision. The product also features a locking mechanism which secures the product to the bracket without any screws showing.

The Commander<sup>3</sup> also features the *Checkmate™* - Instant Voltage Verification feature which allows the installer to check the voltage drop draw and match it to the blueprint.

The GE3 Series appliances are UL 464 and UL 1971, listed for use with fire protective systems and are warranted for three years from date of purchase.

### Standard Features

- Nominal voltage 12VDC and 24VDC
- 24VDC units have field selectable candela options of 15, 30, 60, 75, and 110 candela
- 12VDC units have field selectable candela options of 15, 30, 60, and 75 candela
- GEH horn is available in 12VDC or 24VDC
- Super-Slide™ Bracket - Ease of Supervision Testing
- Checkmate™ - Instant Voltage Verification
- **Unit Dimensions:** 5" high x 4.5" wide x 2.5" deep
- Synchronize strobe and/or horn with Gentex Series Control Module (12VDC product must use the AVSM Module)
- Prewire entire system, then install signals
- Lower installation and operating costs
- Input terminals 12 to 18 AWG
- Switch selection for high or low dBA
- Switch for chime, whoop, mechanical and 2400Hz tone
- Tamperproof re-entrant grill
- Switch for continuous or temporal 3 (not available on whoop tone)

## ➤ GEC3/GES3 12 & 24 VDC S E R I E S



### Product Listings

#### SIGNALING



- UL 464 & UL 1971 Listed
- CAN/ULC S526-M87 Listed
- ULSZ7.S3406 Listed (GEC3-24, GEH24 & GEH12)
- FM Approved
- CSFM: 7135-0569:122 (GEC3-24 & GEH-24)  
7125-0569:123 (GES3-24)  
7125-0569:129 (GES3-12)  
7135-0569:130 (GEC3-12 & GEH-12)
- BS+A/MEA: 285-91-E (GEC3-24 & GES3-24)  
580-06-E (GEC3-12 & GES3-12)
- BFP (City of Chicago)

### Product Compliance

- NFPA 72
- Americans with Disabilities Act (ADA)



- Surface mount with the GSB (Gentex Surface Mount Box)
- Silence horn while strobes remain flashing
- Wide voltage range 8-17.5VDC (12VDC units) 16-33VDC or FWR (24VDC units)
- Faceplate available in red or off-white



## GEH 12VDC or 24VDC Low Profile Evacuation Horn

| Model Number | Part Number  | Nominal Voltage | Reverberant dBA @ 10ft., per UL 464 | In Anechoic Room dBA @ 10ft. |
|--------------|--------------|-----------------|-------------------------------------|------------------------------|
| GEH12-R      | 904-1239-002 | 12VDC           | 62-82                               | 100                          |
| GEH12-W      | 904-1241-002 | 12VDC           | 62-82                               | 100                          |
| GEH24-R      | 904-1205-002 | 24VDC           | 62-82                               | 100                          |
| GEH24-W      | 904-1207-002 | 24VDC           | 62-82                               | 100                          |

## GES3 12VDC or 24VDC Selectable Candela Low Profile Evacuation Strobe

| Model Number | Part Number  | Nominal Voltage | Candela (UL 1971)   |
|--------------|--------------|-----------------|---------------------|
| GES3-12WR    | 904-1235-002 | 12 VDC          | 15, 30, 60, 75      |
| GES3-12WW    | 904-1237-002 | 12 VDC          | 15, 30, 60, 75      |
| GES3-12PWR   | 904-1236-002 | 12 VDC          | 15, 30, 60, 75      |
| GES3-12PWW   | 904-1238-002 | 12 VDC          | 15, 30, 60, 75      |
| GES3-24WR    | 904-1321-002 | 24 VDC          | 15, 30, 60, 75, 110 |
| GES3-24WW    | 904-1319-002 | 24 VDC          | 15, 30, 60, 75, 110 |
| GES3-24PWR   | 904-1322-002 | 24 VDC          | 15, 30, 60, 75, 110 |
| GES3-24PWW   | 904-1320-002 | 24 VDC          | 15, 30, 60, 75, 110 |

### Model Designations:

W = Wall mount  
R = Red faceplate  
W = Off-white faceplate  
P = Plain (no lettering)

All units are available in plain (no lettering).  
When ordering add a "P" to the end of the model number. **Plain units are non-returnable.**

ALERT bezel available  
AGENT bezel available.

## GEC3 12VDC or 24VDC Selectable Candela Low Profile Evacuation Horn/Strobe

| Model Number | Part Number  | Nominal Voltage | Candela (UL 1971)   | Reverberant dBA @ 10ft., per UL 464 | In Anechoic Room dBA @ 10ft. |
|--------------|--------------|-----------------|---------------------|-------------------------------------|------------------------------|
| GEC3-12WR    | 904-1231-002 | 12 VDC          | 15, 30, 60, 75      | 62-82                               | 100                          |
| GEC3-12WW    | 904-1233-002 | 12 VDC          | 15, 30, 60, 75      | 62-82                               | 100                          |
| GEC3-12PWR   | 904-1232-002 | 12 VDC          | 15, 30, 60, 75      | 62-82                               | 100                          |
| GEC3-12PWW   | 904-1234-002 | 12 VDC          | 15, 30, 60, 75      | 62-82                               | 100                          |
| GEC3-24WR    | 904-1317-002 | 24 VDC          | 15, 30, 60, 75, 110 | 62-82                               | 100                          |
| GEC3-24WW    | 904-1315-002 | 24 VDC          | 15, 30, 60, 75, 110 | 62-82                               | 100                          |
| GEC3-24PWR   | 904-1318-002 | 24 VDC          | 15, 30, 60, 75, 110 | 62-82                               | 100                          |
| GEC3-24PWW   | 904-1316-002 | 24 VDC          | 15, 30, 60, 75, 110 | 62-82                               | 100                          |

### GE3-12 Product Strobe Current Ratings

| Candela             | 15cd  | 30cd  | 60cd  | 75cd  |
|---------------------|-------|-------|-------|-------|
| 12VDC               | 106mA | 131mA | 186mA | 237mA |
| UL Max <sup>1</sup> | 163mA | 212mA | 331mA | 436mA |

### GE3-24 Product Strobe Current Ratings

| Candela             | 15cd | 30cd | 60cd  | 75cd  | 110cd |
|---------------------|------|------|-------|-------|-------|
| 24VDC               | 55mA | 63mA | 88mA  | 112mA | 136mA |
| UL Max <sup>1</sup> | 78mA | 96mA | 137mA | 180mA | 224mA |

### GE3-12 Product Horn Current Ratings

| Horn Mode             | Minimum dBA @ 10ft., per UL 464 (HIGH) | Minimum dBA @ 10ft., per UL 464 (LOW) | Regulated 12VDC Max. Operating @ High Setting (mA) |
|-----------------------|--|---------------------------------------|--|
| Temp 3 2400Hz         | 76                                     | 69*                                   | 29   |
| Temp 3 Mechanical     | 75                                     | 68*                                   | 26   |
| Temp 3 Chime          | 62*                                    | 60*                                   | 13   |
| Continuous 2400Hz     | 79                                     | 74*                                   | 29   |
| Continuous Mechanical | 78                                     | 72*                                   | 26   |
| Continuous Chime      | 63*                                    | 61*                                   | 13   |
| Whoop                 | 78                                     | 71*                                   | 55   |

### GE3-24 Product Horn Current Ratings

| Horn Mode             | Minimum dBA @ 10ft., per UL 464 (HIGH) | Minimum dBA @ 10ft., per UL 464 (LOW) | Regulated 24VDC Max. Operating @ High Setting (mA) |
|-----------------------|--|---------------------------------------|--|
| Temp 3 2400Hz         | 78                                     | 71*                                   | 28   |
| Temp 3 Mechanical     | 76                                     | 70*                                   | 25   |
| Temp 3 Chime          | 70*                                    | 66*                                   | 15   |
| Continuous 2400Hz     | 81                                     | 74*                                   | 28   |
| Continuous Mechanical | 80                                     | 72*                                   | 25   |
| Continuous Chime      | 70*                                    | 66*                                   | 15   |
| Whoop                 | 82                                     | 69*                                   | 56   |


### NOTES:

- To obtain the horn/strobe current draw, add the strobe current draw and the horn current draw.
- Operating temperature: 32° to 120°F (0° to 49° C). The GE3 Series is not listed for outdoor use.
- The sound output for the temporal 3 tone is rated lower since the time the horn is off is averaged into the sound output rating. While the horn is producing a tone in the temporal 3 mode its sound pressure is the same as the continuous mode.
- For nominal and peak current across UL regulated voltage range for filtered DC power and unfiltered (FWR [Full Wave Rectified]) power, see installation manual. 12VDC models are DC only.
- Gentex does not recommend using a coded or pulsing signaling circuit with any of our strobe products (see Technical Bulletin 014).


\*Operating the horn in this mode at this voltage will result in not meeting the minimum UL reverberant sound level required for public mode fire protection service. These settings are acceptable only for private mode fire alarm use. Use the high dBA setting for public mode application (not applicable when using the chime tone. The chime tone is always private mode).

<sup>1</sup> RMS current ratings are per UL average RMS method. UL max current rating is the maximum RMS current within the listed voltage range (16-33VDC for 24VDC units) (8-17VDC for 12VDC units). For strobes the UL max current is usually at the minimum listed voltage (16VDC for 24VDC units) (8VDC for 12VDC units). For audibles the max current is usually at the maximum listed voltage. For unfiltered FWR ratings, see installation manual.


## Mounting Super-Slide™




## Checkmate™ - Instant Voltage Verification




## Switch Locations



## Candela Selection




## Conventional GES3/GEC3 Series Wiring Diagrams



# GEC3/GES3 12 & 24 VDC S E R I E S

## Wiring Diagram GE3 Series with Gentex Synchronization Module



**Note:** See Technical Bulletin 015 for proper synchronization module for application.

**Note:** When synchronizing the GE3 12VDC Series, the AVSM synchronization module **MUST** be used.

## Architect & Engineering Specifications

The audible and/or visible signal shall be Gentex GE3 Series or approved equal and shall be listed by Underwriters Laboratories, Inc. per UL 1971 and/or UL 464. The notification appliance shall also be listed with Factory Mutual Listing Service (FM), the California State Fire Marshal (CSFM) and the Bureau of Standards and Appeals (NYC).

The notification appliance (combination audible/visible) shall produce a peak sound output of 100dBA or greater at 12VDC or 24VDC as measured in an anechoic chamber. The signaling appliance shall also have the capability to silence the audible signal while leaving the visible signal energized with the use of a single pair of power wires. Additionally, the user shall be able to select either continuous or temporal tone output with the temporal signal having the ability to be synchronized.

Unit shall be capable of being installed so that any unauthorized attempt to change the candela setting will result in a trouble signal at the fire alarm control panel.

The audible/visible and visible signaling appliance shall also maintain a minimum flash rate of 1Hz or up to 2Hz regardless of power input voltage. The appliance shall have an operating current of 55mA or less at 24VDC for the 15Cd strobe circuit and 106mA or less at 12VDC for the 15Cd strobe circuit.

The appliance shall be polarized to allow for electrical supervision of the system wiring. The unit shall be provided with a mounting bracket with terminals and barriers for input/output wiring and be able to mount to a single gang or double gang box or double workbox without the use of an adapter plate. The unit shall have an input voltage range of 16-33 volts with either direct current or full wave rectified power for 24VDC models or a voltage range of 8-17.5 volts for 12VDC models.

The appliance shall be capable of testing supervision without disconnecting wires. Also the appliance shall be capable of mounting to a surface back box. The unit shall also be able to verify voltage at the unit without removing unit.

24 units per carton  
28 pounds per carton

**GENTEX**  
CORPORATION

Fire Protection Products Group

### Important Notice:

These materials have been prepared by Gentex Corporation ("Gentex") for informational purposes only, are necessarily summary, and are not purported to serve as legal advice and should not be used as such. Gentex makes no representations and warranties, express or implied, that these materials are complete and accurate, up-to-date, or in compliance with all relevant local, state and federal laws, regulations and rules. The materials do not address all legal considerations as there is inevitable uncertainty regarding interpretation of laws, regulations and rules and the application of such laws, regulations and rules to particular fact patterns. Each person's activities can differently affect the obligations that exist under applicable laws, regulations or rules. Therefore, these materials should be used only for informational purposes and should not be used as a substitute for seeking professional legal advice. Gentex will not be responsible for any action or failure to act in reliance upon the information contained in this material.

551-0050-03