GENERAL NOTES

1. THESE DRAWINGS DEPICT GENERAL LOCATIONS OF LIFE SAFETY EQUIPMENT & FIELD DEVICES. EXACT ROUTING OF CONDUITS TO BE DETERMINED IN THE FIELD BY THE INSTALLING CONTRACTOR TO SUIT CONDITIONS. ALL CHANGES SHALL BE CLEARLY INDICATED ON THE RECORD DRAWINGS.
2. SHOULD ANY CONDITIONS EXIST THAT DIFFER FROM WHAT IS INDICATED ON THESE DRAWINGS WHICH CAUSE MAJOR DEVIATIONS IN THE WORK SHOWN, THE CONTRACTOR SHALL CONTACT SIMPLEXGRINNELL IN A TIMELY MANNER SO AS NOT TO IMPAIR THE CONSTRUCTION SCHEDULE.
3. CONTRACTOR IS RESPONSIBLE FOR MAKING AND OBTAINING APPROVAL FOR ALL NECESSARY ADJUSTMENTS IN CIRCUITING AS REQUIRED TO ACCOMMODATE THE RELOCATION OF EQUIPMENT AND/OR DEVICES WHICH ARE AFFECTED BY ANY AUTHORIZED CHANGE. ALL CHANGES SHALL BE CLEARLY INDICATED ON THE RECORD DRAWINGS.
4. A STAMPED SET OF APPROVED FIRE ALARM DRAWINGS SHALL BE AT THE JOB SITE AND SHALL BE USED FOR INSTALLATION.
5. THE POWER CIRCUIT TO THE FACP AND TO THE FIRE ALARM POWER SUPPLIES SHALL BE ON A DEDICATED 120V, 20A BRANCH CIRCUIT BREAKER, AND SHALL HAVE A RED MARKING, LOCK-ON PROVISION AND SHALL BE IDENTIFIED AS "FIRE ALARM CIRCUIT CONTROL." THE LOCATION OF THE CIRCUIT DISCONNECT MEANS (CIRCUIT BREAKER) SHALL BE PERMANENTLY IDENTIFIED AT THE FIRE ALARM CONTROL UNIT.
6. UPDATE THE AS-BUILT DRAWING SET DAILY WITH JOB PROGRESS. RETURN THE AS-BUILT DRAWING SET TO SIMPLEXGRINNELL NO LATER THAN 7 DAYS AFTER FINAL TEST.
7. THE CONTRACTOR WILL MAINTAIN ALL AREAS OF THE BUILDING IN A NEAT AND WORKMAN LIKE MANNER.
8. DO NOT APPLY POWER EXCEPT IN THE PRESENCE OF A FACTORY TRAINED SIMPLEXGRINNELL TECHNICAL REPRESENTATIVE.
9. ANY SMOKE DETECTOR HEAD INSTALLED BEFORE THE BUILDING IS CLEANED AND ACCEPTED SHALL BE COVERED TO PROTECT FROM DUST. ANY FALSE ALARMS DUE TO DIRT CONTAMINATED HEADS SHALL BE THE RESPONSIBILITY OF THE FIRE ALARM INSTALLER.
10. THE FIRE ALARM INSTALLER WILL MAINTAIN THE FIRE RESISTANCE INTEGRITY OF ALL WALL, CEILING, AND ROOF ASSEMBLIES ANY TIME THAT WORK IS NOT ACTIVELY BEING PERFORMED.
11. INSTALLATION OF DEVICES SHALL BE IN ACCORDANCE WITH MANUFACTURER'S INSTRUCTIONS. POWER LIMITED AND NON-POWER LIMITED FIELD WIRING MUST BE INSTALLED WITHIN THE FACP ENCLOSURE IN ACCORDANCE WITH MANUFACTURER'S INSTRUCTIONS AND NEC.
12. ALL WIRING SHALL BE INSTALLED ACCORDING TO NFPA 70 (NEC).
13. FIRE ALARM CIRCUITS SHALL BE IDENTIFIED IN ACCORDANCE WITH APPROPRIATE SECTION OF NEC 760. MARK ALL FIRE ALARM WIRES IN ACCORDANCE WITH NEC 760 SECTIONS FOR POWER LIMITED AND NON-POWER LIMITED WIRE.
14 FIRE ALARM CABLE INSTALLED IN DUCTS, PLENUM, AND OTHER SPACES USED FOR ENVIRONMENTAL AIR SHALL BE TYPE FPLP.
15. FIRE ALARM CABLE INSTALLED IN THE VERTICAL RUNS AND PENETRATE MORE THAN ONE FLOOR OR CABLES INSTALLED IN VERTICAL RUNS IN SHAFTS SHALL BE TYPE FPLR.
16. FIRE ALARM CABLE INSTALLED IN UNDERGROUND CONDUIT OR OTHER WET LOCATIONS SHALL BE UL LISTED FOR WET LOCATIONS.
17. FIRE ALARM CIRCUITS EXTENDING BEYOND ONE BUILDING AND RUN OUTDOOR SHALL BE INSTALLED IN ACCORDANCE WITH NFPA 70 ARTICLES 760, 770, 725 AND 800 WHERE APPLICABLE.
18. ALL WIRING, INCLUDING SHIELDS MUST BE DRY AND FREE OF SHORTS AND GROUNDS.
19. ALL SHIELDED WIRE MUST HAVE SHIELD CONTINUITY AT FULL LENGTH OF THE WIRE.
20. ONLY SYSTEM WIRING CAN BE RUN IN THE SAME CONDUIT.
21. 120VAC IS NOT PERMITTED IN THE SAME CONDUIT WITH LOW VOLTAGE WIRING.
22. MAINTAIN 40 PERCENT CONDUIT FILL RATIO AS PER NEC REQUIREMENTS.
23. EXISTING CONDUITS MAY BE USED BY THE INSTALLATION CONTRACTOR AS DEEMED NECESSARY, HOWEVER, ANY EXISTING CONDUIT WILL BE USED ONLY IF CONDUITS MEET CURRENT STANDARDS AND CODES. SIMPLEXGRINNELL MAKES NO STATEMENTS WRITTEN OR VERBAL AS TO THE CONDITION OF EXISTING CONDUITS.

SYSTEM DESCRIPTION / SCOPE OF WORK

OCCUPANCY TYPE: R-1 RESIDENTIAL GROUP

SPRINKLER PROTECTION: UNKNOWN

PROVIDE AND INSTALL A NEW AUTOMATIC AND MANUAL FIRE ALARM SYSTEM AS SHOWN ON DRAWINGS.

ALL WIRING TO BE CLASS B. WIRING IS STYLE Y FOR NOTIFICATION APPLIANCE CIRCUITS, STYLE B FOR INITIATING DEVICE CIRCUITS, AND STYLE 4 FOR SIGNALING LINE CIRCUITS.

AUTOMATIC FIRE ALARM SYSTEM SHALL TRANSMIT THE ALARM, SUPERVISORY AND TROUBLE SIGNALS TO AN APPROVED SUPERVISING STATION. THE SUPERVISING STATION SHALL BE LISTED AS EITHER UUFX OR UUJS UNDERWRITERS LABORATORY OR SHALL MEET THE REQUIREMENTS OF FACTORY MUTUAL RESEARCH APPROVAL STANDARD 3011. SUPERVISION OF SYSTEM AND LEASED TELEPHONE LINES SHALL BE ARRANGED BY THE OWNER.

FIRE ALARM APPLICABLE CODES & STANDARDS

NFPA 72-2010 EDITION

LIFE SAFETY CODE (NFPA 101), 1997 EDITION

NATIONAL ELECTRIC CODE (NFPA 70), 2002 EDITION

ELEVATOR CODE ASHE A.17.1, 2000 ADDENDA A17.1A, 2002 EDITION

JURISDICTIONS WITHIN THE STATE MAY HAVE AMENDMENTS TO THE STATE ADOPTED CODE.
CHECK WITH THE LOCAL JURISDICTION AUTHORITY FOR MORE DETAILS.

SYMBOL KEY

FIRE ALARM SYMBOLS LEGEND

SYMBOL	DESCRIPTION	MODEL#	BACKBOX
F	MANUAL PULL STATION	SIMPLEX 4099-9003	SINGLE GANG BOX 2 1/2" DEEP
	HEAT SENSOR / BASE	SIMPLEX 4098-9733 SIMPLEX 4098-9792 BASE	4" OCTAGONAL BOX 1 1/2" DEEP
CO SB	SMOKE SENSOR, WITH CO SENSOR BASE SB = INTEGRAL SOUNDER	SIMPLEX 4098-9714 SIMPLEX 4098-9771 BASE	4" OCTAGONAL BOX 1 1/2" DEEP
R	DUCT SMOKE SENSOR	SIMPLEX 4098-9756	MOUNT TO DUCTWORK
AM	INDIVIDUAL ADDRESSABLE MODULE	SIMPLEX 4090-9001	SINGLE GANG BOX 2 1/2" DEEP WITH COVER
ACM	RELAY IAM	SIMPLEX 4090-9002	4" SQUARE BOX 2 1/8" DEEP W/TWO GANG COVER
#	WALL MOUNT MULTI-CANDELA HORN/STROBE, WHITE # = CANDELA RATING	SIMPLEX 49AV-WWF	4" SQUARE BOX 1 1/2" DEEP W/4905-9940 ADAPTER SKIRT WHEN SURFACE MOUNTED
#	WALL MOUNT MULTI-CANDELA STROBE ONLY, WHITE # = CANDELA RATING	SIMPLEX 49V0-WWF	4" SQUARE BOX 1 1/2" DEEP W/4905-9940 ADAPTER SKIRT WHEN SURFACE MOUNTED
75 WP	WALL MOUNT MULTI-CANDELA WEATHERPROOF STROBE ONLY, WHITE 75 CANDELA RATING	SIMPLEX 49V0-WWFO	49WPBB-AVVOWW BACK BOX SUPPLIED BY SIMPLEXGRINNELL
6.8K	END-OF-LINE RESISTOR 3.3K (EOL) END-OF-LINE RESISTOR 4.7K (EOL) END-OF-LINE RESISTOR 6.8K (EOL) END-OF-LINE RESISTOR 10K (EOL)	SIMPLEX 4081-9002 SIMPLEX 4081-9003 SIMPLEX 4081-9004 SIMPLEX 4081-9008	SUPPLIED BY OTHERS
	REMOTE TEST STATION W/ LED AND KEY SWITCH	SIMPLEX 2098-9806	SINGLE GANG BOX 2 1/2" DEEP
FACP	FIRE ALARM CONTROL PANEL	SIMPLEX 4100-9111	
FAA	SERIAL LCD ANNUNCIATOR	SIMPLEX 4603-9101	6 GANG BOX 3 1/2" DEEP
T4M	TEMPORAL CODE 4 MODULE	SIMPLEX 4905-9835	4" SQUARE BACK BOX, 2 1/8" DEEP
	DOOR HOLDER	SUPPLIED BY OTHERS	SUPPLIED BY OTHERS
TAC#	FIRE ALARM TERMINAL CABINET	4905-9950	SUPPLIED BY OTHERS
	SMOKE SENSOR / BASE L = LED BASE R = RELAY BASE ISO = ISOLATOR BASE	SIMPLEX 4098-9714 SIMPLEX 4098-9792 BASE SIMPLEX 4098-9789 BASE SIMPLEX 4098-9791 BASE SIMPLEX 4098-9793 BASE	 4" OCTAGONAL BOX 1 1/2" DEEP 4" OCTAGONAL BOX 1 1/2" DEEP 4" OCTAGONAL BOX 1 1/2" DEEP W/ 1 1/2" EXT RING 4" OCTAGONAL BOX 1 1/2" DEEP
	ENCAPSULATED RELAY	SIMPLEX 4098-9843	SINGLE GANG BOX 2 1/8" DEEP W/COVER
	AREA RESCUE - MASTER STATION PANEL	NC150R	SUPPLIED BY OTHERS
	AREA RESCUE - ASSISTANCE REMOTE STATION	IR150SS	SUPPLIED BY OTHERS
WP 75	WALL MOUNT MULTI-CANDELA WEATHERPROOF HORN/STROBE, WHITE 75 CANDELA RATING	SIMPLEX 49AV-WWFO-BA	49WPBB-AVVOWW BACK BOX SUPPLIED BY SIMPLEXGRINNELL

WIRE SCHEDULE

FIRE ALARM WIRE LIST

	CIRCUIT DESCRIPTION	RISER RATED: FPLR	SINGLE CONDUCTOR(THHN,TFFN)	PLENUM RATED: FPLP
A	ADDRESSABLE NOTIFICATION CIRCUIT 14 AWG SOLID UNSHIELDED TWISTED PAIR	SG ANIX./PAIGE 454718ARE AREA=0.0380 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-1N-03-BX		SG ANIX./PAIGE 454719ARE AREA=0.0333 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-2N-03
B	RUI/N2 COMMUNICATION 1 PAIR 18 AWG TWISTED OVERALL SHIELD	SG ANIX./PAIGE 740215 AREA=0.0196 SQ. INCH ANIXTER PART NUMBER T740215		SG ANIX./PAIGE 740214L AREA=0.0196 SQ. INCH ANIXTER PART NUMBER FAMC-1802C-1-2S-03B5
C	CITY CONNECT CIRCUIT 2 CONDUCTOR 18 AWG SOLID	SG ANIX./PAIGE 454703ARE AREA=0.0204 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-1N-03-BX		SG ANIX./PAIGE 740132R AREA=0.0141 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-2N-03
G	GROUND WIRE (BOND WIRE) - 1 CONDUCTOR 12 AWG SOLID (GREEN)		SG ANIX./PAIGE 741223 AREA=0.0115 SQ. INCH	
K	REMOTE TEST SWITCH/ LED CIRCUIT - (2) 2 CONDUCTOR 18 AWG SOLID	SG ANIX./PAIGE 454703ARE AREA=0.0204 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-1N-03-BX	(4) #18 AWG AREA=0.0055 SQ. INCH (EACH)	SG ANIX./PAIGE 740132R AREA=0.0141 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-2N-03
L	REMOTE LED CIRCUIT 2 CONDUCTOR 18 AWG SOLID	SG ANIX./PAIGE 454703ARE AREA=0.0204 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-1N-03-BX	(2) #18 AWG AREA=0.0055 SQ. INCH (EACH)	SG ANIX./PAIGE 740132R AREA=0.0141 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-2N-03
M	IDNET CIRCUIT - 1 PAIR 18 AWG UNSHIELDED TWISTED (SUBSCRIPT "u" IF MIXED w/SHIELDED)	SG ANIX./PAIGE 454703ARE AREA=0.0204 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-1N-03-BX		SG ANIX./PAIGE 740132R AREA=0.0141 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-2N-03
P	POWER CIRCUIT 2 CONDUCTOR 14 AWG SOLID (SUBSCRIPT "r" IF RESETTABLE)	SG ANIX./PAIGE 454718ARE AREA=0.0380 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-1N-03-BX	(2) #14 AWG AREA=0.0097 SQ. INCH (EACH)	SG ANIX./PAIGE 454719ARE AREA=0.0333 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-2N-03
R	RELAY CIRCUIT 2 CONDUCTOR 14 AWG SOLID	SG ANIX./PAIGE 454718ARE AREA=0.0380 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-1N-03-BX	(2) #14 AWG AREA=0.0097 SQ. INCH (EACH)	SG ANIX./PAIGE 454719ARE AREA=0.0333 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-2N-03
V	VISUAL/SIGNAL CIRCUIT 2 CONDUCTOR 14 AWG SOLID	SG ANIX./PAIGE 454718ARE AREA=0.0380 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-1N-03-BX	(2) #14 AWG AREA=0.0097 SQ. INCH (EACH)	SG ANIX./PAIGE 454719ARE AREA=0.0333 SQ. INCH ANIXTER PART NUMBER FA-1402C-1-2N-03
Z	ZONE CIRCUIT 2 CONDUCTOR 18 AWG SOLID	SG ANIX./PAIGE 454703ARE AREA=0.0204 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-1N-03-BX	(2) #18 AWG AREA=0.0055 SQ. INCH (EACH)	SG ANIX./PAIGE 740132R AREA=0.0141 SQ. INCH ANIXTER PART NUMBER FA-1802C-1-2N-03

CONDUIT SIZE	CONDUCTOR AREA	CONDUIT SIZE	CONDUCTOR AREA
1/2"	0.12 SQ INCH *	1-1/4"	0.60 SQ INCH *
3/4"	0.21 SQ INCH *	1-1/2"	0.82 SQ INCH *
1"	0.34 SQ INCH *	2"	1.34 SQ INCH *

* 40% FILL PER N.E.C.

THE CABLES SPECIFIED HERE ARE FOR REFERENCE OF REQUIRED ELECTRICAL CHARACTERISTICS AS WELL AS CODE REQUIREMENTS. ALTERNATE SUPPLIERS MAY BE SUBSTITUTED PROVIDING EQUIVALENT CHARACTERISTICS ARE MAINTAINED. ITEMS SUCH AS CAPACITANCE BETWEEN CONDUCTORS AND WIRE GAUGE CAN BE CRUCIAL TO THE CIRCUIT DESIGN OF THIS SYSTEM INSTALLATION.

REFERENCE https://www.anixter.com/customer/tycofs FOR SG ANIXTER CABLE DATA

ABBREVIATIONS LEGEND

AC = ABOVE CEILING
C = CEILING MOUNTED
E = EXISTING TO REMAIN
RC = EXISTING TO REMOVE AND COVER
RD = EXISTING DEVICE TO BE RELOCATED
RL = RELOCATED DEVICE
RR = REMOVE EXISTING AND REPLACE W/NEW

WP = WEATHERPROOF
XP = EXPLOSION PROOF
H = HIGH HUMIDITY
AFF = ABOVE FINISHED FLOOR
AHJ = AUTHORITY HAVING JURISDICTION
ALM = ALARM
ANN = ANNUNCIATOR
BMS = BUILDING MANAGEMENT SYSTEM
CBC = CALIFORNIA BUILDING CODE
CD = (eg. 15CD) CANDELA
CSFM = CALIFORNIA STATE FIRE MARSHALL
DET = DETECTOR
DGP = DATA GATHERING PANEL
EOL = END OF LINE
EPO = EMERGENCY POWER OFF
FACP = FIRE ALARM CONTROL PANEL
FATC = FIRE ALARM TERMINAL CABINET
FBO = FURNISHED BY OTHERS
FCC = FIRE COMMAND CENTER
FAA = FIRE ALARM ANNUNCIATOR
FTR = FIRE ALARM TRANSPONDER
FSD = FIRE SMOKE DAMPER

HT = HEIGHT
HVAC = HEATING, VENTILATION, & AIR CONDITIONING
IMS = INFORMATION MANAGEMENT SYSTEM
MAX = MAXIMUM
MIN = MINIMUM
N/A = NOT APPLICABLE
NAC = NOTIFICATION APPLIANCE CIRCUIT EXTENDER
NDU = NETWORK DISPLAY UNIT
NEC = NATIONAL ELECTRICAL CODE
NFPA = NATIONAL FIRE PROTECTION ASSOCIATION
NIC = NOT IN CONTRACT
NPU = NETWORK PROCESSING UNIT
NTS = NOT TO SCALE
PAP = PRE-ACTION PANEL
SCC = STATUS COMMAND CENTER
SLC = SIGNALING LINE CIRCUIT
SMK = SMOKE
SUPV = SUPERVISORY
TAC = TRUEALERT ADDRESSABLE CONTROLLER
TRBL = TROUBLE
TS = TAMPER SWITCH
TYP = TYPICAL
UON = UNLESS OTHERWISE NOTED
VCC = VOICE COMMAND CENTER
VT = VALVE TAMPER
WF = WATER FLOW
W = (eg. 1/2W) WATT
W/ = WITH
W/O = WITH OUT

DEVICE ADDRESSING LEGEND

ADDRESSABLE CARD (IDNET OR MAPNET) — DEVICE ADDRESS

M2-1

ADDRESSABLE DEVICES NUMBERING

CHANNEL DESIGNATOR — DEVICE DESIGNATOR
ADDRESSABLE POWER SUPPLY (EPS, TPS) — BRANCH/REPEATER DESIGNATOR (OPT.)

A1:2-1(1) — (#) BRANCH, (E#:#) REPEATER:BRANCH

ADDRESSABLE NOTIFICATION DEVICE

CIRCUIT DESIGNATOR — DEVICE DESIGNATOR

NAC2-1

VISUAL, AUDIBLE OR A/V DEVICE

SEQUENCE OF OPERATION

SYSTEM OUTPUTS

CONTROL UNIT ANNUNCIATION: A ACTUATE COMMON ALARM SIGNAL INDICATOR; B ACTUATE COMMON ALARM SIGNAL; C ACTUATE COMMON SUPERVISORY SIGNAL INDICATOR; D ACTUATE AUDIBLE SUPERVISORY SIGNAL; E ACTUATE COMMON TROUBLE SIGNAL INDICATOR; F ACTUATE AUDIBLE TROUBLE SIGNAL; G ACTUATE APPROPRIATE LOCATION INDICATOR; H ACTUATE ALL AUDIBLE EVACUATION SIGNALS; I ACTUATE ALL VISIBLE EVACUATION SIGNALS; J DISPLAY CHANGE OF STATUS

NOTIFICATION: K TRANSMIT ALARM SIGNAL TO SUPERVISING STATION; L TRANSMIT SUPV. SIGNAL TO SUPERVISING STATION; M TRANSMIT TROUBLE SIGNAL TO SUPERVISING STATION

FIRE SAFETY CONTROL: N RELEASE ELEVATOR FIRE DOORS; O ELEVATOR SHUNT TRIP; P MAIN FLOOR ELEVATOR RECALL; Q ALTERNATE FLOOR ELEVATOR RECALL; R ELEVATOR HAT FLASH; S FAN SHUT DOWN; T DAMPER SHUT DOWN; U PRESSURIZE STAIRWELLS; V REMOTE DISPLAY ACTIVE STATUS; W

SYSTEM INPUTS	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z	AA	AB	AC	AD	AE	AF	AG	AH	AI	AJ	REMARKS
1 SMOKE SENSOR/DETECTOR	•	•					•	•	•		•	•																					•	•	•	•	1
2 SMOKE/HEAT SENSOR W/ SOUNDER BASE			•	•			•				•		•																								2
3 MANUAL PULL STATION	•	•					•	•	•		•	•																							•		3
4 HEAT SENSOR/DETECTOR	•	•					•	•	•		•	•																							•		4
5 DUCT SENSOR/DETECTOR			•	•			•						•																				•	•	•	•	5
6 MAIN FLR. ELEV. LOBBY SMOKE DETECTOR	•	•					•	•	•		•	•						•			•												•	•	•	•	6
7 ELEVATOR LOBBY SMOKE DETECTORS (EXC. MAIN FLR.)	•	•					•	•	•		•	•						•		•													•	•	•	•	7
8 ELEVATOR MECH. ROOM HEAT DETECTOR	•	•					•	•	•		•	•							•																•	•	8
9 ELEVATOR MECH. ROOM SMOKE DETECTOR	•	•					•	•	•		•	•								•		•											•	•	•	•	9
10 ELEVATOR SHAFT HEAT DETECTOR	•	•					•	•	•		•	•							•																•	•	10
11 ELEVATOR SHAFT SMOKE DETECTOR	•	•					•	•	•		•	•								•		•											•	•	•	•	11
12 ELEVATOR POWER MONITOR							•				•		•																						•		12
13 WATERFLOW SWITCH	•	•					•	•	•		•	•																							•	•	13
14 TAMPER SWITCH			•	•			•				•		•																						•		14
15 POST INDICATOR VALVE SWITCH			•	•			•				•		•																						•		15
16 FIRE ALARM AC POWER FAILURE					•	•					•			•				•																	•		16
17 FIRE ALARM SYSTEM LOW BATTERY					•	•					•			•																					•		17
18 OPEN CIRCUIT OR GROUND FAULT					•	•					•			•																					•		18
19 CLASS B NOTIFICATION CIRCUIT (NAC) - SHORT					•	•					•			•																					•		19
20																																					20
21																																					21
22																																					22
23																																					23
24																																					24
25																																					25
26																																					26
27																																					27
28																																					28
29																																					29
30																																					30
31																																					31
32																																					32
	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z	AA	AB	AC	AD	AE	AF	AG	AH	AI	AJ	

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 04/03/15

tyco Simplex
Safer. Smarter. Tyco.™
DISTRICT - 147
20 THOMAS DRIVE
WESTBROOK, ME 04092
SERVICE: 207-842-6440
PHONE: 20
FAX:

PRESS HOTEL
119 EXCHANGE ST
PORTLAND, ME

ISSUE LOG:				
MARK	DATE	CAD	CHK	DESCRIPTION
1	5-8-14	JD	KG	REVISED PER ENGINEERS COMMENTS & ADDED AOR SYSTEM

Revisions shown with 1 cloud

DRAWN BY:	JD
CHECKED BY:	KG
ISSUE DATE:	4/24/14
JOB #:	977465501
PROJECT #:	147-PRE-BOOKED

SIMPLEXGRINNELL © 2013

SYSTEM: FIRE ALARM SYSTEM

SHEET: GENERAL INFORMATION

FA-002

IMPORTANT NOTICE TO USER: By accepting or using this drawing and/or the information contained herein, the user agrees to the following terms and conditions: The attached information in this drawing may be subject to copyright or confidential ownership. Any use, reuse, copying, modification or alteration of the information contained herein shall be at the sole risk of the user. This information may not be sold or transferred to any third party, used for other projects or additions to this project for which it was prepared, or used for completion of this project by any third party. SimplexGrinnell disclaims all liability for the use or any third party and such use will be a user's sole risk. User shall, to the fullest extent permitted by law, defend, indemnify, and hold SimplexGrinnell harmless from any and all claims for loss, damage or injury arising directly or indirectly therefrom.

LAST SAVED BY: JUDELACRUZ
LAST PRINTED: 5/29/2014 3:07:25 PM
24" x 36" - Arch D Size