

DAA-75 Series

Digital Audio Amplifiers



Voice Control Systems

GENERAL

The DAA-75 Series Amplifiers provide more 75 watts of audio for applications that are too large for the DAA-50 series amplifiers. Up to 32 DAA series amplifiers, can be connected to the DAL (digital audio loop) on one DVC Digital Voice Command unit. DAA-75 series amplifiers can be mixed with DAA-50 series amplifiers on the same DAL.

Each DAA-75 is capable of accessing and processing one of up to eight audio channels on the DVC audio loop, amplifying the signal, and distributing it via four Class B or two Class A outputs at 75 watts. DAA-75 amplifiers can store backup alarm and trouble messages, and provide an adjustable background music input. An optional Firefighter's telephone riser on the DAA-75 supports FFT communications with the controlling DVC. Each DAA incorporates a powerful digital signal processor, a 75 watt amplifier, built-in audio NAC outputs, and a chassis which mounts in a single row of either CAB-4 or EQ Series cabinets.

The DAA-75 does not charge batteries; therefore a separate listed charging power supply must be used in conjunction with the backup batteries.

FEATURES

- Listed to UL Standard 864, 9th edition.
- 75 W total output power at 25 VRMS
- Multiple versions provide connection options for twisted-pair wire, single-mode fiber, and multi-mode fiber media
- Two Class A high-level audio outputs; or alternately, four Class B outputs supported. Outputs dynamically share the 75 W - the total power can be dedicated to a single output if required.
- Audio output activation via network control-by-event equations resident within the DVC
- Two digital audio ports support Style 4 or 7 configurations.
- Auxiliary input for 12 Vp-p analog low-level audio.
- Auxiliary input for 1 VRMS, to be used for background music input, an interface with a telephone paging source, or other compatible audio sources. Audio levels can be adjusted by end user. Continuous supervision for active DAA output circuits.
- Programmable through **VeriFire® Tools**.
- Up to two minutes of standard quality backup digital message storage (from a **VeriFire Tools** message library, or created by the installer) for use in the event of communication loss.
- Multiple DAA-75 can share batteries supported by a single charging power supply
- Isolated alarm bus input, to be used for backup activation of alarm messages when normal digital communication is lost
- Relay contacts that will activate on a trouble condition provide an option for redundant annunciation to a local panel

INSTALLATION

The DAA-75 arrives from the factory already installed on its chassis. The DAA-75 mounts in one tier of any CAB-4 Series cabinet; the DAA tier can be covered using a DP-1B dress panel, ordered separately. The DAA-75 may also be installed



daa75photo1.jpg

in one tier of an EQ series cabinet. No dress plate is used for EQ cabinet installations. DAA-75 series amplifiers (wire versions) may be installed in adjacent rows of a CAB-4 series cabinet for non-continuous duty applications (background music is a continuous-duty application). The EQ series cabinets supports DAA-75 series amplifiers (wire or fiber) installed in adjacent rows for continuous as well as non continuous duty applications.

SPECIFICATIONS

DAA-PS POWER SUPPLY BOARD

- AC power (TB1): 115 - 120 VAC, 60 Hz input, 4.5 A maximum; or for "E" versions, 220 - 240 VAC, 50/60 Hz input, 2.3 A maximum. Recommended wiring: 12 to 14 AWG (1.6 mm O.D.) with 600 VAC insulation
- Battery connections (TB3): Supplied cable connections to batteries.

DAA-7525 BOARDS

- Digital audio ports, wire media, A and B (TB2, TB3): Maximum distance per segment is 1900 feet (579.12 m) on Belden 5320UJ (18 AWG, TP) FPL cable; 18 AWG (0.821 mm²) twisted-pair, unshielded, power-limited. See wiring documentation, P/N 52916ADD: C Addendum to DVC and DAA Manuals. Electrically isolated ports support Style 4 or 7 wiring.
- Digital audio ports, "F" versions: Digital audio loop connectors A and B support multi-mode fiber. Maximum attenuation is 4.2 dB for multi-mode with 50/125 micrometer cable @ 850 nm; 8.0 dB for multi-mode with 62.5/125 micrometer cable @ 850 nm.
- Digital audio ports, "SF" versions: Digital audio loop connectors A and B support single-mode fiber. Maximum attenuation is 5.0 dB for single-mode with 9/125 micrometer cable @ 1300 nm.
- Alarm bus (TB4): Power-limited by source. Recommended wiring: 14 to 22 AWG (2.08 to 0.326 mm²) twisted-pair
- Trouble bus (TB5): Dry contact. Recommended wiring: 14 to 22 AWG (2.08 to 0.326 mm²) twisted-pair
- FFT riser (TB13): Power-limited output. Class A (Style Z) or Class B (Style Y) operation. Style Y two-wire connections require a 3.9K ohm, 1/2 watt resistor (P/N R-3.9K). Maximum wiring resistance (including individual telephone zone to last handset) permitted is 50 ohms, 10,000 feet (3048 m)

maximum wiring distance at 12 AWG (3.31 mm²) to last handset.

- Auxiliary input A (AUX A, TB9): Signal strength from low-level analog audio input: 1 VRMS maximum. Optional supervision (selected through programming). Recommended wiring: 18 to 22 AWG (0.821 to 0.326 mm²) twisted-pair. Auxiliary input must be in the same room as the DAA.
- Auxiliary input B (AUX B, TB8): Signal strength from low-level analog audio input: 12 Vp-p nominal, 15 Vp-p maximum. Optional supervision (selected through programming). Recommended wiring: 14 to 22 AWG (2.08 to 0.326 mm²) twisted-pair.
- Speaker circuits (TB10, TB11, TB12, and TB13): Power limited outputs. 75 watts dynamically shared among the four outputs. Supervision determined by programming. Recommended wiring: 14 to 22 AWG (2.08 to 0.326 mm²) twisted shielded pair.
- End-of-line resistors: For Class A: 10K ohm, 1/2 watt, P/N R-10K. For Class B: 20K ohm, 1/2 watt, P/N R-20K.

STANDARDS AND CODES

The DAA-75 Series Digital Audio Amplifiers comply with the following standards:

- NFPA 72 2002 National Fire Alarm Code.
- Underwriters Laboratories Standard UL 864, 9th Edition.
- Underwriters Laboratories of Canada (ULC) ULC-S527-99 Standard of Control Units for Fire Alarm Systems.
- Part 15 Class A of the conducted and radiated emissions as required by FCC.

LISTINGS AND APPROVALS

These listings and approvals apply to the basic DAA-75 Series Digital Audio Amplifiers. In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- UL Listed: file S635.
- ULC Listed: file S635.
- FM Approved

PRODUCT LINE INFORMATION

DAA-7525: Digital Audio Amplifier (75 W, 25 VRMS), assembly with DAA-PS power supply board, shipped mounted to its chassis.

DAA-7525F: Digital Audio Amplifier (75 W, 25 VRMS), multi-mode fiber, assembly with DAA-PS power supply board, shipped mounted to its chassis.

DAA-7525SF: Digital Audio Amplifier (75 W, 25 VRMS), single-mode fiber, assembly with DAA-PS power supply board, shipped mounted to its chassis.

220-240 VAC MODELS

DAA-7525E: Digital Audio Amplifier (75 W, 25 VRMS, 240 VAC), assembly with DAA-PS power supply board, shipped mounted to its chassis.

DAA-7525FE: Digital Audio Amplifier (75 W, 25 VRMS), multi-mode fiber, 240 VAC, assembly with DAA-PS power supply board, shipped mounted to its chassis.

DAA-7525SFE: Digital Audio Amplifier (75 W, 25 VRMS), single-mode fiber, 240 VAC, assembly with DAA-PS power supply board, shipped mounted to its chassis.

ACCESSORIES

DP-1B: Dress panel; covers one tier of CAB-4 Series cabinet.

ONYX®, NOTIFIER®, and VeriFire® are registered trademarks of Honeywell International Inc.

©2008 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.



Made in the U.S.A.

For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.
www.notifier.com