P200
Battery & Voltage Drop Calculations

Project Name:		**Standby Hours:**	24
		Alarm Mins:	5
Installed By:		**Batt Efficiency:**	80%
Designed By:		**SLC Type:**	Cla
Date:		**NAC Source Voltage:**	20.4

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

Model #: P200
Panel ID:
Location:

Max Panel Current (amps): 5

User assumes all responsibility to ensure the quantities and current draw values in this worksheet are accurate prior to submittal.

Qty	FACP Part #	Description	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
1	P200	Analog Addressable FACP	0.130	0.130	0.220	0.220
			Panel Standby:	**0.130**	**Panel Alarm:**	**0.220**

	P-LINK (RS-485)		Standby		Alarm	
1	UD-1000	DACT	0.016	0.016	0.023	0.023
	RA-6075	LCD Annunciator	0.020		0.025	
1	RA-6500	LCD Annunciator	0.020	0.020	0.050	0.050
	LED-16	LED Annunciator	0.025		0.025	
	LED-16	LED Annunciator LED Power*	0.015		0.210	
	CA-6075	Class A Module	0.012		0.044	
	PSN-1000(E)	Power Expander	0.015		0.015	
	RLY-5	Relay Expander	0.025		0.035	
	RLY-5	Relay Expander Power*	0.010		0.135	
	DRV-50	LED Driver Module	0.025		0.025	
	DRV-50	LED Driver Module LED Power*	0.010		0.215	
	FCB-1000	Fire Communications Bridge	0.025		0.025	
	FIB-1000	Fiber Interface Board	0.030		0.030	
	SPG-1000	Serial Parallel Gateway	0.040		0.040	
		(Maximum current draw on P-Link limited to 1 Amp)	**P-LINK Standby:**	**0.036**	**P-LINK Alarm:**	**0.073**

Only enter quantity if PLINK power is being used to power device

	SLC Devices		Standby		Alarm	
1	PSA	Analog Photo Smoke	0.000325	0.000325	0.000325	0.000325
	PSHA	Analog Photo Smoke/Heat	0.000325		0.000325	
	RHA	Analog Rate of Rise Heat	0.000325		0.000325	
	FHA	Analog Fixed Temp Heat	0.000325		0.000325	
2	APS-SA/APS-DA	Addressable Pull Station Single/Dual Action	0.000325	0.000650	0.000325	0.000650
	MCM	Mini Contact Input Module	0.000325		0.000325	
	SCM-4	Single Contact Input Module	0.000325		0.001000	
3	DCM-4	Dual Contact Input Module	0.000325	0.000975	0.001000	0.003000
	TRM-4	Twin Relay Output Module	0.000325		0.001000	
	CIZM-4 *	Conventional Zone Input Mod	0.000325		0.001000	
	MOM-4 *	Monitored Output Module	0.000325		0.001000	
	ARB *	Detector Base w/Relay	0.000325		0.000325	
	ASB *	Detector Base w/Sounder	0.000325		0.000325	
	SCI **	Short Circuit Isolator (Class A)	0.000325		0.002340	
	AIB **	Detector Base w/Isolator (Class A)	0.000325		0.002340	
	SCI/AIB Class B **	Current Draw from Install Manual				
1		SLC Loop Alarm LED Current	0.000000	0.000000	0.027000	0.027000
*	Requires Aux Power (Configure Below)		**SLC Standby:**	**0.001950**	**SLC Alarm:**	**0.030975**

** See the installation manual for special considerations when installing AIB, SCI devices on Class B loops.

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

NAC Circuits (See NAC Configuration below)			Standby (amps)		A
Ckt	Use	Description	Total		
1			0.00000		
2			0.00000		
		NAC Standby:	**0.00000**	NAC Alarm:	

I/O Circuits (See I/O Configuration below)			Standby (amps)		Alarm (amps)
Ckt	Use	Description	Total		Total
1			0.00000		0.00000
2			0.00000		0.00000
		I/O Standby:	**0.00000**	I/O Alarm:	**0.00000**

Battery Calculation Summary

	Standby (amps)		Alarm (amps)
Panel Current:	0.13000		0.22000
P-Link Current:	0.03600		0.07300
SLC Device Current:	0.00195		0.03098
NAC Circuit Current:	0.00000		5.00000
I/O Circuit Current:	0.00000		0.00000
Total Standby:	**0.167950**	Total Alarm:	**5.32398**
Standby Hours:	24	Alarm Mins:	5
AH Required:	**4.04**	AH Required:	**0.45**

SLC Loop Type: Class B
Point Capacity Needed: 9
Point Capacity Actual: 75

Total Combined Standby & Alarm AmpHours Required: 4.49
Efficiency Factor: 80%

Required Battery AmpHours: **5.61**

Battery AmpHours Provided:

Note: The cabinet will house two 8 AH or 18 AH batteries. The charging circuit is rated for up to two 55 AH batteries.

POTTER
The Symbol of Protection

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

NAC Circuit Configuration & Voltage Drop

NAC 1

MAX Circuit Current (amps): 3 **Source Voltage Used (VDC): 20.4**

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	3.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
1	1	to these bottom 5 rows			3.000000	3.000000
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**3.00000**

NAC 2

MAX Circuit Current (amps): 3 **Source Voltage Used (VDC): 20.4**

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	2.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
1		to these bottom 5 rows			2.000000	2.000000
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**2.00000**

POTTER
The Symbol of Protection

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

I/O Circuit Configuration & Voltage Drop

I/O 1

MAX Circuit Current (amps): 1 **Source Voltage Used (VDC): 20.4**

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	0.000	20.40	16

		Circuit Devices	Standby (amps)		Alarm (amps)	
Qty	Lookup Type	Desc	Each	Total	Each	Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**0.00000**

I/O 2

MAX Circuit Current (amps): 1 **Source Voltage Used (VDC): 20.4**

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	0.000	20.40	16

		Circuit Devices	Standby (amps)		Alarm (amps)	
Qty	Lookup Type	Desc	Each	Total	Each	Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**0.00000**

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

User Defined Parts		
Description	**Standby**	**Alarm**
User Defined 1		
User Defined 2		
User Defined 3		
User Defined 4		
User Defined 5		
User Defined 6		
User Defined 7		
User Defined 8		
User Defined 9		
User Defined 10		
User Defined 11		
User Defined 12		
User Defined 13		
User Defined 14		
User Defined 15		
User Defined 16		
User Defined 17		
User Defined 18		
User Defined 19		
User Defined 20		
User Defined 21		
User Defined 22		
User Defined 23		
User Defined 24		
User Defined 25		
User Defined 26		
User Defined 27		
User Defined 28		
User Defined 29		
User Defined 30		
User Defined 31		
User Defined 32		
User Defined 33		
User Defined 34		
User Defined 35		
User Defined 36		
User Defined 37		
User Defined 38		
User Defined 39		
User Defined 40		
User Defined 41		
User Defined 42		
User Defined 43		
User Defined 44		
User Defined 45		
User Defined 46		
User Defined 47		
User Defined 48		
User Defined 49		
User Defined 50		
User Defined 51		
User Defined 52		
User Defined 53		
User Defined 54		
User Defined 55		

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 12/07/16

User Defined 56		
User Defined 57		
User Defined 58		
User Defined 59		
User Defined 60		
User Defined 61		
User Defined 62		
User Defined 63		
User Defined 64		
User Defined 65		
User Defined 66		
User Defined 67		
User Defined 68		
User Defined 69		
User Defined 70		
User Defined 71		
User Defined 72		
User Defined 73		
User Defined 74		
User Defined 75		
User Defined 76		
User Defined 77		
User Defined 78		
User Defined 79		
User Defined 80		
User Defined 81		
User Defined 82		
User Defined 83		
User Defined 84		
User Defined 85		
User Defined 86		
User Defined 87		
User Defined 88		
User Defined 89		
User Defined 90		
User Defined 91		
User Defined 92		
User Defined 93		
User Defined 94		
User Defined 95		
User Defined 96		
User Defined 97		
User Defined 98		
User Defined 99		
User Defined 100		