TELECOMMUNICATIONS LEGEND

- TELEPHONE OUTLET LOCATION. PROVIDE 3/4" CONDUIT TO NEAREST ACCESSIBLE CEILING.
  "W" = INDICATES WALL PHONE
- COMBINATION TELEPHONE/DATA OUTLET LOCATION. PROVIDE 3/4" CONDUIT TO NEAREST ACCESSIBLE CEILING.
- DATA OUTLET LOCATION. PROVIDE 3/4" CONDUIT TO NEAREST ACCESSIBLE CEILING.
- WA — WIRELESS ACCESS POINT LOCATION. PROVIDE BACK BOX AS REQUIRED BY EQUIPMENT.
- CAMERA OUTLET LOCATION. PROVIDE BACK BOX AS REQUIRED BY EQUIPMENT.

MOTOR & CONTROLS LEGEND

- 30AS — DISCONNECT SWITCH RATED 30AMP, 3–POLE, IN NEMA TYPE 1 ENCLOSURE, UNLESS OTHERWISE NOTED
  "3R" – INDICATES NEMA TYPE 3R ENCLOSURE
  "2P" – INDICATES 2 POLE SINGLE PHASE DISCONNECT
  "60AS" – INDICATES 60A SWITCH
- 60AS 200F — FUSED DISCONNECT SWITCH, 3–POLE, IN NEMA TYPE 1 ENCLOSURE, UNLESS OTHERWISE NOTED.
  "3R" – INDICATES NEMA TYPE 3R ENCLOSURE
  "60AS" – INDICATES 60AMP SWITCH
  "50AF" – INDICATES 50AMP FUSES
- 100NF 90AT CB — ENCLOSED CIRCUIT BREAKER IN NEMA TYPE 1 ENCLOSURE, UNLESS OTHERWISE NOTED
  "100AF" – INDICATES 100AMP, 3–POLE FRAME CIRCUIT BREAKER
  "90AT" – INDICATES 90AMP TRIP

DEMOLITION LEGEND

XM	EXISTING EQUIPMENT TO REMAIN
X	EXISTING EQUIPMENT TO BE REMOVED
XR	EXISTING EQUIPMENT TO BE RELOCATED
XN	NEW LOCATION OF EXISTING RELOCATED EQUIPMENT
NR	EXISTING EQUIPMENT TO BE REMOVED AND NEW EQUIPMENT TO BE INSTALLED ON EXISTING BRANCH/FEEDER
	EXISTING EQUIPMENT FOR INFORMATION ONLY– INDICATED BY SYMBOL WITH LIGHT AND OUT OF FUNCTION LINE TYPE
	EXISTING EQUIPMENT TO BE REWORKED– INDICATED BY SYMBOL WITH DASHED AND IN FUNCTION LINE TYPE

FIRE ALARM LEGEND

REFER TO DRAWING E–400 FOR FIRE ALARM LEGEND AND GENERAL NOTES

SECURITY LEGEND

- KP — WALL MOUNTED KEY PAD. PROVIDE BACK BOX AND 3/4" CONDUIT TO ABOVE NEAREST ACCESSIBLE CEILING.

WIRING DEVICE LEGEND

- S — DUPLEX RECEPTACLE, GROUNDING TYPE, RATED 20A, 125V
  "S" = INDICATES CIRCUIT NUMBER
  "IG" = INDICATES ISOLATED GROUND TYPE
  "WP" = INDICATES WEATHERPROOF
  "C" = INDICATES COUNTER HEIGHT
  "U" = DUPLEX RECEPTACLE WITH USB CONNECTIONS
- 20A, 125V SINGLE RECEPTACLE – FLUSH WALL MOUNTED
- 20A, 125V QUADRUPLEX RECEPTACLE – FLUSH WALL MOUNTED
- 20A, 125V DUPLEX RECEPTACLE FLUSH WALL MOUNTED – GFI TYPE.
- 20A, 125V QUADRUPLEX RECEPTACLE FLUSH WALL MOUNTED – GFI TYPE.
- J — JUNCTION BOX
- J — JUNCTION BOX WITH FINAL EQUIPMENT CONNECTION
- J AD — CONNECTION TO AUTOMATIC DOOR
- J EWC — CONNECTION TO ELECTRIC WATER COOLER
- J HD — CONNECTION TO HAND DRYER
- 509 — EQUIPMENT TAG – REFER TO EQUIPMENT SCHEDULE

BRANCH CIRCUIT & FEEDER LEGEND

- BRANCH CIRCUIT OR FEEDER CONCEALED IN FINISHED AREAS
- BRANCH CIRCUIT OR FEEDER, CONCEALED IN OR UNDER FLOOR SLAB
- BRANCH CIRCUIT OR FEEDER TURNING UP TOWARDS OBSERVER
- BRANCH CIRCUIT OR FEEDER TURNING DOWN AWAY FROM OBSERVER
- CONDUIT STUBBED ABOVE CEILING
- PANEL–1,3,5 — HOMERUN–NUMERAL WHERE USED INDICATES CIRCUIT NUMBER FOR REFERENCE ONLY.
  2#12+1#12G–3/4"C FOR ONE CKT. HOMERUN, U.O.N.
  4#12+1#12G–3/4"C FOR TWO CKT. HOMERUN, U.O.N.
  6#12+1#12G–3/4"C FOR THREE CKT. HOMERUN, U.O.N.
- FLEXIBLE CONNECTION TO EQUIPMENT. RACEWAY AND CONDUCTOR RATING TO MATCH ASSOCIATED BRANCH CIRCUIT OR FEEDER

POWER DISTRIBUTION

- SURFACE MOUNTED PANELBOARD
- RECESSED MOUNTED PANELBOARD
- GROUND BAR
- T3 — DRY TYPE TRANSFORMER
  "T3" – INDICATES KVA RATING OF TRANSFORMER
- KT3 — DRY TYPE TRANSFORMER K–RATED
  "KT3" – INDICATES KVA RATING OF TRANSFORMER

LIGHTING FIXTURE LEGEND

- FR2 — LIGHTING FIXTURE (SEE LIGHTING FIXTURE SCHEDULE)
  "FR2" – INDICATES LIGHTING FIXTURE TYPE
  "2" – INDICATES CIRCUIT NUMBER
  "a" – INDICATES SWITCH CONTROL
  "NL"– INDICATES NIGHT LIGHT (UNSWITCHED) CIRCUIT
- AR1 — RECESSED DOWNLIGHT FIXTURE (SEE LIGHTING FIXTURE SCHEDULE)
- EXIT SIGN LIGHTING FIXTURE, CEILING, PENDANT MOUNTED, ARROWS AND EXIT FACE (SHADED) AS INDICATED
- EXIT SIGN LIGHTING FIXTURE, WALL MOUNTED, ARROWS AND EXIT FACE AS (SHADED) AS INDICATED.
- P1 — TRACK LIGHTING, WITH TYPE AS5 HEADS
- EMERGENCY LIGHTING BATTERY UNIT WITH DOUBLE LAMP HEADS
- EMERGENCY LIGHTING BATTERY UNIT REMOTE HEAD

SWITCH LEGEND

- Sa — SINGLE POLE SWITCH, RATED 20A, 120/277V
  "a" LOWER CASE LETTER INDICATES FIXTURE SWITCH CONTROL
- S2a — TWO POLE SINGLE THROW SWITCH, RATED 20A, 120/277V
- S3a — THREE WAY SWITCH, RATED 20A, 120/277V
- S4a — FOUR WAY SWITCH, RATED 20A, 120/277V
- SP — SINGLE POLE SWITCH RATED 20A, 120/277V, WITH PILOT LIGHT
- S3P — THREE WAY SWITCH RATED 20A, 120/277V, WITH PILOT LIGHT
- SK — SINGLE POLE SWITCH, RATED 20A, 120/277V, KEY OPERATED
- SLV — LOW VOLTAGE SWITCH
- ST — TIMER SWITCH
- H OS — OCCUPANCY SENSOR, SURFACE WALL MOUNTED

ELECTRICAL DEMOLITION NOTES

1. THE CONTRACTOR SHALL INCLUDE IN HIS BID ALL COSTS ASSOCIATED WITH REMOVALS AND RELOCATIONS OF ELECTRICAL WORK AS DESCRIBED IN THE SPECIFICATIONS WITH ALLOWANCES FOR EXPECTED OR UNFORESEEN DIFFICULTIES WHEN CONCEALED WORK HAS BEEN OPENED. NO CLAIMS FOR ADDITIONAL WORK ASSOCIATED WITH DEMOLITION WILL BE ACCEPTED, EXCEPT IN CERTAIN CASES CONSIDERED JUSTIFIABLE BY THE ARCHITECT.
2. THE CONTRACTOR SHALL REMOVE AND/OR RELOCATE ALL EXISTING ELECTRICAL WORK WHICH INTERFERES WITH THE NEW ARCHITECTURAL AND ELECTRICAL LAYOUTS IN FULL COORDINATION WITH THE ARCHITECT'S DEMOLITION PLANS. ALL SYSTEMS WHICH ARE NO LONGER REQUIRED TO FUNCTION SHALL BE DE–ENERGIZED AND DISCONNECTED AT THE SOURCE OF POWER SUPPLY.
3. THE CONTRACTOR SHALL PERFORM DEMOLITION AND REMOVAL WORK WITH MINIMUM INTERFERENCE WITH FUNCTIONING ELECTRICAL SYSTEMS. ALL AFFECTED SYSTEMS SHALL BE RECONNECTED AND RESTORED.
4. DEMOLITION AND REMOVAL WORK SHALL BE PERFORMED IN A NEAT AND WORKMANLIKE MANNER. THE CONTRACTOR SHALL PATCH, REPAIR OR OTHERWISE RESTORE ANY DAMAGED INTERIOR OR EXTERIOR BUILDING SURFACE TO ITS ORIGINAL CONDITION.
5. THE CONTRACTOR SHALL REMOVE ALL ELECTRICAL OUTLETS, SWITCHES AND OTHER DEVICES, COMPLETE WITH ASSOCIATED WIRING, CONDUITS, ETC., FROM PARTITIONS THAT ARE TO BE REMOVED. WHERE THE REMOVAL OF THESE ITEMS DISRUPTS EXISTING WIRING THAT IS TO REMAIN, THE CONTRACTOR SHALL INSTALL JUNCTION BOXES AND OTHER DEVICES AND PROVIDE BYPASS CONNECTIONS NECESSARY TO MAKE CIRCUITS AFFECTED CONTINUOUS AND READY FOR OPERATION. OTHERWISE, WIRING SHALL BE REMOVED BACK TO THE NEAREST ELECTRICAL JUNCTION BOX THAT IS TO REMAIN OR TO PANELBOARD.
6. ALL RACEWAYS WHICH BECOME EXPOSED DURING THE ALTERATION WORK SHALL BE REMOVED AND REROUTED CONCEALED BEHIND FINISHED SURFACES.
7. ALL UNUSED OUTLET BOXES OR CAPPED FLOOR OUTLETS SHALL BE PROVIDED WITH MATCHING BLANK COVERS.
8. EXISTING PANEL DIRECTORIES AFFECTED BY THE ALTERATION WORK SHALL BE MODIFIED TO REFLECT THE BRANCH CIRCUIT WIRING CHANGES.
9. PORTIONS OF FEEDER RUNS TO BE REMOVED OR ABANDONED AS A RESULT OF DEMOLITION WORK, BUT WHICH ARE REQUIRED TO REMAIN ENERGIZED, SHALL BE CUT AT CONVENIENT LOCATIONS, REROUTED AND RECONNECTED. NEW FEEDER EXTENSIONS SHALL MATCH EXISTING ONES IN ALL RESPECTS, CABLE TYPE, CONDUCTOR AMPACITY, CONDUIT SIZES, ETC.
10. THE CONTRACTOR SHALL NOTIFY THE OWNER AT THE APPROPRIATE TIME OF THE PROJECTED DEMOLITION AND PHASING SCHEDULE SO THAT REMOVAL OR RELOCATION OF AFFECTED UTILITIES MAY BE CARRIED OUT IN COORDINATION WITH THE PROJECT REQUIREMENTS. THE CONTRACTOR SHALL FOLLOW CLOSELY THE ARCHITECT'S DEMOLITION AND PHASING SCHEDULE AND PROCEED IN THE SPECIFIED SEQUENCE.
11. ALL EXISTING MATERIAL AND EQUIPMENT IN USABLE CONDITION, WHICH IS TO BE REMOVED UNDER THIS CONTRACT, SHALL REMAIN THE PROPERTY OF THE OWNER OR SHALL BE DISPOSED OF BY THE ELECTRICAL CONTRACTOR, AS DIRECTED BY THE OWNER.
12. ARRANGE TO WORK CONTINUOUSLY, INCLUDING OVER TIME, IF REQUIRED, TO ASSURE THAT SYSTEMS WILL BE SHUT DOWN ONLY DURING THE TIME ACTUALLY REQUIRED TO MAKE THE NECESSARY CONNECTIONS TO THE EXISTING SYSTEMS.
13. THE SHUTDOWN OF EXISTING BUILDING ELECTRICAL SERVICES SHALL BE COORDINATED WITH THE OWNER. MAKE ARRANGEMENTS AT LEAST 5 BUSINESS DAYS PRIOR TO A SHUTDOWN.

ABBREVIATIONS

A/AMP	AMPERE	KWH	KILOWATT HOURS
AC	ALTERNATION CURRENT	LTG	LIGHTING
ADA	AMERICAN WITH DISABILITIES ACT	MCB	MAIN CIRCUIT BREAKER
AF	AMPERE FRAME	MEC	MASSACHUSETTS ELECTRICAL CODE
AFF	ABOVE FINISHED FLOOR	M/G	MOTOR/GENERATOR SET
AFG	ABOVE FINISHED GRADE	MH	MANHOLE
AIC	AMPERE INTERRUPTING CAPACITY	MLO	MAIN LUGS ONLY
AL	ALUMINUM	MTD	MOUNTED
AT	AMPERE TRIP	MTG	MOUNTING
ATS	AUTOMATIC TRANSFER SWITCH	NC	NORMALLY CLOSED CONTACT
AWG	AMERICAN WIRE GAUGE	NEC	NATIONAL ELECTRICAL CODE
B	BURIED	NO	NORMALLY OPEN CONTACT
C	CONDUIT	NTS	NOT TO SCALE
CA	CABLE	#	NUMBER
CATV	CABLE TELEVISION	OPD	OVER CURRENT PROTECTION DEVICE
CCTV	CLOSED CIRCUIT TELEVISION SYSTEM	POS	PROVIDED UNDER OTHER SECTIONS
CB	CIRCUIT BREAKER	PVC	POLYVINYL CHLORIDE
CKT	CIRCUITS	PWR	POWER
CPU	CENTRAL PROCESSING UNIT	RGS	RIGID GALVANIZED STEEL
℄	CENTERLINE	RMS	ROOT MEAN SQUARE VALUE
dB	DECIBEL	RPM	REVOLUTIONS PER MINUTE
DC	DIRECT CURRENT	SN	SOLID NEUTRAL
DWG	DRAWING	SWBD	SWITCHBOARD
EC	ELECTRICAL CONTRACTOR	TB	TERMINAL BLOCK
EMT	ELECTRIC METALLIC TUBING	TEL	TELEPHONE
FDR	FEEDER	TERMN	TERMINAL
FLMT	FLEXIBLE LIQUID TIGHT METALLIC TUBING	TSP	TWISTED SHIELDED–PAIR
FREQ	FREQUENCY	TVSS	TRANSIENT VOLTAGE SURGE SUPPRESSER
GEC	GROUNDING ELECTRODE CONDUCTOR	TYP	TYPICAL
GFI	GROUND FAULT INTERRUPTING	UG	UNDERGROUND
GND	GROUND	UNO	UNLESS NOTED OTHERWISE
HH	HANDHOLE	UPS	UNINTERRUPTIBLE POWER SUPPLY
HP	HORSEPOWER	UTP	UNSHIELDED TWISTED–PAIR
HVAC	HEATING, VENTILATING AND AIR CONDITIONING	V	VOLTS
HZ	HERTZ	VA	VOLT–AMPERE
IG	ISOLATED GROUND	VSD	VARIABLE SPEED DRIVE
JB	JUNCTION BOX	W	WATTS
KVA	KILOVOLT–AMPERE	WP	WEATHERPROOF
KW	KILOWATT		

ELECTRICAL GENERAL NOTES

1. GENERAL NOTES, SYMBOL LIST AND DETAILS ARE APPLICABLE TO ALL ELECTRICAL DRAWINGS.
2. ALL WORK IS NEW UNLESS OTHERWISE NOTED.
3. DRAWINGS ARE DIAGRAMMATIC AND INDICATE GENERAL ARRANGEMENT OF SYSTEMS AND WORK. FOLLOW DRAWINGS IN LAYING OUT WORK AND CHECK DRAWINGS OF OTHER TRADES TO VERIFY SPACE CONDITIONS. MAINTAIN HEADROOM AND SPACE CONDITIONS.
4. SECURE ALL SUPPORTS TO BUILDING STRUCTURE UTILIZING TOGGLE BOLTS (HOLLOW MASONRY), EXPANSION SHIELDS OR INSERTS (CONCRETE AND BRICK), MACHINE SCREWS (METAL), BEAM CLAMPS (FRAMEWORK), WOOD SCREWS (WOOD) OR PAN THRU STRAPS (METAL DECK). NAILS, RAWL PLUGS AND WOOD PLUGS ARE NOT PERMITTED. WHERE REQUIRED BY STRUCTURE, PROVIDE THRU BOLTS AND FISH PLATES. SUPPORT HORIZONTAL RUNS OF METALLIC RACEWAYS NOT MORE THAN 10 FT APART. SUPPORT RACEWAY RISERS AT EACH FLOOR LEVEL. RUN EXPOSED RACEWAYS PARALLEL WITH OR AT RIGHT ANGLES TO WALLS.
5. PASS RACEWAYS OVER WATER, STEAM OR OTHER PIPING WHEN PULL BOXES ARE NOT REQUIRED. NO RACEWAY WITHIN 3 INCHES OF STEAM OR HOT WATER PIPES OR APPLIANCES (EXCEPT PIPE CROSSINGS WHERE RACEWAY SHALL BE AT LEAST 1 INCH FROM PIPE COVERS).
6. CUT CONDUIT ENDS SQUARE. REAM SMOOTH. PAINT MALE THREAD OF FIELD THREADED RACEWAYS WITH GRAPHITE BASE PIPE COMPOUND. DRAW UP TIGHT WITH RACEWAY COUPLING.
7. HORIZONTAL OR CROSS RUNS IN PARTITIONS AND WALLS ARE NOT PERMITTED. DO NOT RUN CONDUIT IN PRECAST ROOF SLABS, IN 2 INCH SLABS OR IN TERRAZZO FLOOR FINISH.
8. LEAVE WIRES WITH SUFFICIENT SLACK TO PERMIT MAKING FINAL CONNECTIONS. RACEWAYS OVER 10 FT LONG IN WHICH WIRING IS NOT INSTALLED: FURNISH FISH WIRE.
9. SET BOXES SQUARE AND TRUE WITH BUILDING FINISH. ERECT WALL AND SWITCH OUTLETS IN ADVANCE OF FURRING AND FIREPROOFING. SECURE TO BUILDING STRUCTURE BY ADJUSTABLE STRAP IRONS.
10. VERIFY LOCATIONS OF OUTLETS AND SWITCHES IN FINISHED ROOMS WITH ARCHITECTURAL DRAWINGS OF INTERIOR DETAILS AND FINISH. IN CENTERING OUTLETS AND LOCATING BOXES AND OUTLETS, ALLOW FOR OVERHEAD PIPES, DUCTS AND MECHANICAL EQUIPMENT, VARIATIONS IN FIREPROOFING AND PLASTERING, WINDOW AND DOOR TRIM, PANELING, HUNG CEILINGS AND THE LIKE. CORRECT ANY INACCURACY RESULTING FROM FAILURE TO DO SO WITHOUT EXPENSE TO OWNER.
11. LOCATIONS INDICATED FOR LOCAL WALL SWITCHES ARE SUBJECT TO MODIFICATIONS AT OR NEAR DOORS. COORDINATE WITH ARCHITECT AND INSTALL SWITCH ON SIDE OPPOSITE HINGE. VERIFY FINAL HINGE LOCATIONS IN FIELD PRIOR TO SWITCH OUTLET INSTALLATION.
12. COVERS OF JUNCTION AND PULLBOXES SHALL BE READILY ACCESSIBLE.
13. PROVIDE PULLBOXES WHERE INDICATED, WHERE REQUIRED BY CODE AND WHEREVER NECESSARY TO FACILITATE PULLING OF WIRE. COORDINATE PULLBOX LOCATIONS WITH OTHER TRADES.
14. EMPTY RACEWAY RUNS: PROVIDE PULLBOXES EVERY 100 FT AND AS INDICATED. COORDINATE LOCATIONS WITH OTHER TRADES.
15. JUNCTION AND PULLBOXES: LOCATE GENERALLY NOT EXPOSED IN FINISHED SPACES. WHERE NECESSARY, REROUTE RACEWAYS OR MAKE OTHER ARRANGEMENTS FOR CONCEALMENT.
16. SUPPORT PANEL, JUNCTION AND PULLBOXES INDEPENDENTLY TO BUILDING STRUCTURE WITH NO WEIGHT BEARING ON RACEWAYS.
17. ALL ACCESS DOOR LOCATIONS SHALL BE REVIEWED BY ARCHITECT PRIOR TO INSTALLATION.
18. CONNECT CONDUIT TO MOTOR CONDUIT TERMINAL BOXES WITH FLEXIBLE CONDUIT (MINIMUM 18 IN. LENGTH AND 50% SLACK). DO NOT TERMINATE IN OR FASTEN RACEWAYS TO MOTOR FOUNDATION.
19. PROVIDE SEPARATE RACEWAYS FOR CONDUCTORS OF NORMAL AND EMERGENCY CIRCUITS. COMMON BOXES: PROVIDE BARRIERS BETWEEN EMERGENCY AND NORMAL WIRING.
20. HEIGHTS OF OUTLETS FROM FINISHED FLOOR TO CENTERLINE OF OUTLET:

RECEPTACLES AND TELEPHONES:	
GENERALLY	1'–6"
OVER WORK BENCHES	3'–6"
WALL SWITCHES	4'–0"
WALL FIXTURES	7'–0"
MOTOR CONTROLLERS	5'–0"
GONGS AND HORNS	7'–6"
FIRE ALARM STATIONS	4'–0"
CLOCKS	7'–6"
STROBE LIGHTS	6'–8" TO BOTTOM (OR 6" BELOW CEILING, WHICHEVER IS LOWER)

EXCEPTIONS: AT JUNCTION OF DIFFERENT WALL FINISH MATERIALS, ON MOLDING OR BREAK IN WALL SURFACE, IN VIOLATION OF CODE REQUIREMENTS, AS NOTED OR DIRECTED.

CONTRACTOR SHALL BE RESPONSIBLE FOR COORDINATING AND CONFIRMING ALL MOUNTING HEIGHTS WITH ARCHITECT AND ARCHITECTURAL DRAWINGS.

21. WIRE COLOR CODING: AS PER CODE. WHERE COLOR–CODED CABLE IS NOT AVAILABLE, CERTIFY IN WRITING AND REQUEST PERMISSION FOR OVERLAP COLOR TAPING OF CONDUCTORS (MINIMUM LENGTH 6") IN ACCESSIBLE LOCATIONS. COLOR CODING, ONCE SELECTED, MUST BE USED CONSISTENTLY FOR THE ENTIRE PROJECT.
22. INSTALL NEW WORK AND CONNECT TO EXISTING WORK WITH MINIMUM INTERFERENCE TO EXISTING FACILITIES. TEMPORARY SHUTDOWNS: ONLY WITH WRITTEN CONSENT OF OWNER. MAINTAIN CONTINUOUS OPERATION OF EXISTING FACILITIES. ALARM AND EMERGENCY SYSTEMS ARE NOT TO BE INTERRUPTED.
23. FIRESTOPPING SHALL BE INSTALLED WHENEVER WIRING OR RACEWAYS CROSS FIRE RATED CONSTRUCTION.
24. LIGHTING FIXTURE SCHEDULE STANDARD NOTE: LIGHTING FIXTURE SCHEDULE SHOWN ON ENGINEER'S DRAWINGS ARE FOR INFORMATION PURPOSES ONLY. LIGHTING FIXTURES SHOWN ARE THOSE SELECTED BY ARCHITECT. ENGINEER SHALL NOT BE RESPONSIBLE FOR INFORMATION SHOWN RELATED TO FIXTURE SELECTION AND OVERALL LIGHTING DESIGN. REFER TO ARCHITECTURAL DRAWINGS FOR FURTHER INFORMATION.

HARRIMAN
AUBURN PORTLAND MANCHESTER

WHOLE FOODS MARKET

PUB DEVELOPMENT AND DEPARTMENT RELOCATIONS
2 SOMERSET ST
PORTLAND, ME

Harriman Project No. 15103
Key Plan Proj North

AMPEG
PROFESSIONAL ELECTRICAL CONTRACTORS OF CT, INC.
100 Accress Road
Norwood, MA 02062
phone 781-769-7767
fax 781-769-7913
145 Robert Jackson Way
Plainville, CT 06062

e3i Engineers Inc.
4 South Market Street,
Suite S5026
Boston, MA 02109
Tel 781 799 9351

Issues and Revisions

Mark	Date	Description
–	09-28-15	ISSUED FOR PERMITTING

STATE OF MAINE — DAVID J. COUNTERMACHE No. 10536 — LICENSED PROFESSIONAL ENGINEER

Drawing Scales
N.T.S.

0 4" 8" 12"

PA / PE: •••
Drawn By: •••

© 2015 Harriman Associates

ELECTRICAL LEGEND AND GENRAL NOTES

E00.1