



Reviewed for Code Compliance  
Inspections Division  
Approved with Conditions



# 7788F/7744F Series

## Wireless Fire Alarm Communicators for IntelliNet



Model 7788F



### Features:

- UL Listed Date: 07/22/15
- Meets NFPA 72 requirements
- Direct reporting to AES receiver across IntelliNet mesh radio network
- Each Subscriber acts as transmitter/receiver/repeater
- Simple and fast activation on network
- On board status LEDs for easy set up
- 8 programmable zone inputs – 7788F
- 4 programmable zone inputs and 4 reverse polarity inputs – 7744F
- Easy programming via AES handheld programmer or PC
- Rugged metal housing ideal for any commercial fire alarm application
- Narrowband compliant

### Models 7788F/7744F-ULP with IntelliPro Fire also includes

- IntelliPro Fire transmits full alarm data from virtually any fire alarm panel digital communicator
- Alarm format support for Contact ID, Pulse, as well as Bosch Modem IIe and Modem IIIa
- Easy installation in AES subscriber
- Operates in applications with or without a phone line



Wireless mesh networking is an innovative technology adopted by many industries with applications that need to communicate data over a large geographic area with a high level of reliability at a low total cost of ownership.

The advanced design and 2-way communications capability provides easy installation, expansion, and management when compared to alternative communication methods, both wired and wireless.

### Advanced Wireless Alarm Monitoring

As expensive dedicated landlines, required for UL864 compliance disappear, and the future of GSM for alarm transmission becomes increasingly uncertain, the AES IntelliNet mesh radio network continues to offer unmatched reliability and speed in delivering wireless alarm signals to a central station without any third-party fees or reliance on networks operated by companies outside the alarm industry. The 7788F/7744F Series Subscribers provide the wireless communications link between the fire alarm panel and the central station receiver. Ideal for most commercial fire alarm applications, each 7788F/7744F Series Subscriber is housed in a full-sized, red, locked steel cabinet and supports a range of alarm panel inputs, including EOL fire, EOL supervised, and direct voltage from the panel (non-fire applications).

### Supervised Operation

AES Subscribers offer fully-supervised operation that includes monitoring of operating power (both primary AC and battery back-up) and the connection to the mesh radio network. Each subscriber “checks-in” with the AES central station receiver at least once every 24 hours. The supervision check-in time can be set to as often as needed for the application, as appropriate for the network. Because the central station operates the wireless network, there is no additional cost for air time to transmit supervisory signals.

### Full Data Reporting from Alarm Panel Digital Dialer

Models 7788F-ULP and 7744F-ULP come equipped with an IntelliPro-Fire Full Data Module (AES-7794) which enables reporting of full alarm data captured from the alarm panel’s digital communicator. IntelliPro-Fire supports most alarm communication formats including Contact ID, Pulse, as well as Bosch Modem IIe and Modem IIIa2 (when converted to Contact ID format).

# 7744F/7788F Series



Reviewed for Code Compliance  
Inspections Division  
Approved with Conditions

Date: 07/22/15

## Technical Specifications

### 7788F/7744F Series Subscriber

#### Dimensions

- 13.25"H x 8.5"W x 4.3"D  
(34cm H x 21.5cm W x 11cm D)

#### Weight

- Approx. 7 pounds (3.2 kilograms),  
excludes battery.

#### Radio Frequency

- Standard Frequency Range:  
450-470MHz  
(others available in 400-512MHz range)
- Output Power – 2 Watts

#### Antenna

- Included 2.5 db tamper resistant antenna  
mounts on enclosure
- Multiple remote antenna options available

#### Power Input

- 16.5VAC, 40VA transformer (not included)  
(AES 1640, ELK TRG1640, MG Electronics  
MGT1640 – UL Listed for use)

#### Backup Battery

- Will charge 12V battery up to 7.5 AH. Requires  
12VDC 7.5 AH battery for UL 864.

#### Alarm Signal Inputs (subscriber)

- 7788F – 8 individually programmable zones
- 7744F – 4 individually programmable zones  
and 4 reverse polarity inputs

#### UL Standards

- UL 864 Edition 9 – Standard for Control Units  
and Accessories for Fire Alarm Systems
- UL 365 – Standard for Police Station  
Connected Burglar Alarm Units and Systems
- UL 1681 – Standard for Central Station Burglar  
Alarm Units

#### Antenna Cut / Communication

##### Trouble Output

- Form C relay; fail secure;  
rated for 24 VDC 1A resistive

##### Reset Button

- Located on main circuit board.

##### Operating Temperature

- 0° to 50° C (32° to 122°F)

##### Storage Temperature

- -10° to 60° C (14° to 140°F)

##### Relative Humidity

- 0 to 85% RHC, Non Condensing

### AES-7794 IntelliPro Fire

#### Packaged with 7744F-ULP and 7788F-ULP

##### Input / Output Connections

- RJ11 connection to AES subscriber for module  
data and power
- RJ11 connector for Handheld Programmer/PC  
programming
- RJ31X Telco connections - T and R both in  
and out via terminal strip and RJ45
- Alarm Panel digital communicator T and R  
both in and out via terminal strip and RJ45
- Trouble output: Form C relay detects if  
Subscriber is off the network

##### Alarm Formats

- Support for Contact ID and Pulse formats as  
well as Modem IIe and Modem IIIa2 converted  
to CID

##### Size

- 2.8 x 5.0 inches (7.1cm x 12.7cm)

##### Power Requirements

- 12 VDC nominal - primary and backup power  
provided by the AES 7788F/7744F or other  
Subscriber

## How to Order

Model	Description
7744F	4 Zone Fire Alarm Subscriber with 4 reverse polarity inputs
7744F-ULP	7744F Fire Alarm Subscriber with IntelliPro Fire full data module
7788F	8 Zone Fire Alarm Subscriber
7788F-ULP	7788F Fire Alarm Subscriber with IntelliPro Fire full data module

## Optional Accessories

7041E	Subscriber Handheld Programmer
7794	IntelliPro Fire Full Data Module
1640	Plug-in Transformer: 16.5VAC, 40VA

AES-IntelliNet™ is the industry leader in delivering high-quality mesh radio networks to the fire and security industry in commercial, corporate, government, and educational applications with its broad line of products and advanced network management tools. Users of AES-IntelliNet networks have gained significant revenue, communications, and cost advantages while meeting the high standards of reliability required for the fire and security industry. AES-IntelliNet alarm monitoring systems are deployed at hundreds of thousands of locations in over 130 countries.



For more information  
Call 800-AES-NETS (800-237-6387)

AES Corporation | 285 Newbury Street | Peabody, MA 01960 USA  
Tel. +1 978-535-7310 | Fax +1 978-535-7313  
Email info@aes-intellinet.com | Web www.aes-intellinet.com



Copyright 2012 AES Corporation  
AES-IntelliNet is a registered trademark of  
AES Corporation

7788-7744F/1/12/R4