



P200
Battery & Voltage Drop
Calculations

Project Name:	Quality Inn	Standby Hours:	24
Installed By:		Alarm Mins:	5
Designed By:		Batt Efficiency:	80%
Date:		SLC Type:	Class B
		NAC Source Voltage:	20.4

Model #: P200

Panel ID:

Location:

Max Panel Current (amps): 5

User assumes all responsibility to ensure the quantities and current draw values in this worksheet are accurate prior to submittal.

Qty	FACP Part #	Description	Standby (amps)		Alarm (amps)	
			Each	Total	Each	Total
1	P200	Analog Addressable FACP	0.130	0.130	0.220	0.220
			Panel Standby:	0.130	Panel Alarm:	0.220

P-LINK (RS-485)			Standby		Alarm	
	UD-1000	DACT	0.016		0.023	
	RA-6075	LCD Annunciator	0.020		0.025	
1	RA-6500	LCD Annunciator	0.020	0.020	0.050	0.050
	LED-16	LED Annunciator	0.025		0.025	
	LED-16	LED Annunciator LED Power*	0.015		0.210	
	CA-6075	Class A Module	0.012		0.044	
	PSN-1000(E)	Power Expander	0.015		0.015	
	RLY-5	Relay Expander	0.025		0.035	
	RLY-5	Relay Expander Power*	0.010		0.135	
	DRV-50	LED Driver Module	0.025		0.025	
	DRV-50	LED Driver Module LED Power*	0.010		0.215	
	FCB-1000	Fire Communications Bridge	0.025		0.025	
	FIB-1000	Fiber Interface Board	0.030		0.030	
	SPG-1000	Serial Parallel Gateway	0.040		0.040	
			P-LINK Standby:	0.020	P-LINK Alarm:	0.050

(Maximum current draw on P-Link limited to 1 Amp)

***Only enter quantity if PLINK power is being used to power device**

SLC Devices			Standby		Alarm	
	PSA	Analog Photo Smoke	0.000325		0.000325	
6	PSHA	Analog Photo Smoke/Heat	0.000325	0.001950	0.000325	0.001950
26	RHA	Analog Rate of Rise Heat	0.000325	0.008450	0.000325	0.008450
	FHA	Analog Fixed Temp Heat	0.000325		0.000325	
4	APS-SA/APS-DA	Addressable Pull Station Single/Dual Action	0.000325	0.001300	0.000325	0.001300
2	MCM	Mini Contact Input Module	0.000325	0.000650	0.000325	0.000650
	SCM-4	Single Contact Input Module	0.000325		0.001000	
	DCM-4	Dual Contact Input Module	0.000325		0.001000	
	TRM-4	Twin Relay Output Module	0.000325		0.001000	
	CIZM-4 *	Conventional Zone Input Mod	0.000325		0.001000	
	MOM-4 *	Monitored Output Module	0.000325		0.001000	
	ARB *	Detector Base w/Relay	0.000325		0.000325	
	ASB *	Detector Base w/Sounder	0.000325		0.000325	
	SCI **	Short Circuit Isolator (Class A)	0.000325		0.002340	
	AIB **	Detector Base w/Isolator (Class A)	0.000325		0.002340	
	SCI/AIB Class B **	Current Draw from Install Manual	<input type="text"/>		<input type="text"/>	
1		SLC Loop Alarm LED Current	0.000000	0.000000	0.027000	0.027000
			SLC Standby:	0.012350	SLC Alarm:	0.039350

* Requires Aux Power (Configure Below)

** See the installation manual for special considerations when installing AIB, SCI devices on Class B loops.

NAC Circuits (See NAC Configuration below)			Standby (amps)	Alarm (amps)
Ckt	Use	Description	Total	Total
1			0.00000	3.00000
2			0.00000	2.00000
NAC Standby:			0.00000	NAC Alarm: 5.00000

I/O Circuits (See I/O Configuration below)			Standby (amps)	Alarm (amps)
Ckt	Use	Description	Total	Total
1			0.00000	0.00000
2			0.00000	0.00000
I/O Standby:			0.00000	I/O Alarm: 0.00000

Battery Calculation Summary		Standby (amps)	Alarm (amps)
	Panel Current:	0.13000	0.22000
	P-Link Current:	0.02000	0.05000
	SLC Device Current:	0.01235	0.03935
	NAC Circuit Current:	0.00000	5.00000
	I/O Circuit Current:	0.00000	0.00000
	Total Standby:	0.162350	Total Alarm: 5.30935
	Standby Hours:	24	Alarm Mins: 5
	AH Required:	3.90	AH Required: 0.45
	Total Combined Standby & Alarm AmpHours Required:		4.35
		Efficiency Factor:	80%
	Required Battery AmpHours:		5.44
	Battery AmpHours Provided:		<input type="text" value=""/>

Note: The cabinet will house two 8 AH or 18 AH batteries. The charging circuit is rated for up to two 55 AH batteries.

NAC 1 MAX Circuit Current (amps): 3 Source Voltage Used (VDC): 20.4

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amp)	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	3.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps)		Alarm (amps)	
			Each	Total	Each	Total
		User can add devices on the fly to these bottom 5 rows (No lookup function)				
1		Total			3.000000	3.000000
Total Standby:			0.00000		Total Alarm:	3.00000

NAC 2 MAX Circuit Current (amps): 3 Source Voltage Used (VDC): 20.4

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amp)	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	2.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps)		Alarm (amps)	
			Each	Total	Each	Total
		User can add devices on the fly to these bottom 5 rows (No lookup function)				
1		Total			2.000000	2.000000
Total Standby:			0.00000		Total Alarm:	2.00000

I/O 1 MAX Circuit Current (amps): 1 Source Voltage Used (VDC): 20.4

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amp)	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	0.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps)		Alarm (amps)	
			Each	Total	Each	Total
		User can add devices on the fly to these bottom 5 rows (No lookup function)				
			Total Standby:	0.00000	Total Alarm:	0.00000

I/O 2 MAX Circuit Current (amps): 1 Source Voltage Used (VDC): 20.4

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amp)	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	0.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps)		Alarm (amps)	
			Each	Total	Each	Total
		User can add devices on the fly to these bottom 5 rows (No lookup function)				
			Total Standby:	0.00000	Total Alarm:	0.00000