



### FACP Battery Calculation

9/13/2017

PROJECT NAME: 30-32 STATE STREET  
 Required Standby Time: 24 Hours  
 Required Alarm Time: 5 Minutes

Regulated Load in Standby				
Device Type	Number of Devices	Current (Amps)		Total Current (Amps)
FACP - MS-9200UDLS MAIN CIRCUIT BOARD	1	X 0.14500	=	0.14500
LCD-80 REMOTE ANNUNCIATOR	2	X 0.02500	=	0.05000
SD355 SMOKE DETECTOR	11	X 0.00030	=	0.00330
H355/H355R HEAT DETECTOR	54	X 0.00030	=	0.01620
MMF-301 MINI MONITOR MODULE	21	X 0.00038	=	0.00798
<b>TOTAL STANDBY LOAD</b>				<b>0.22238</b>
Regulated Load in ALARM				
Device Type	Number of Devices	Current (Amps)		Total Current (Amps)
FACP - MS-9200UDLS MAIN CIRCUIT BOARD	1	X 0.27500	=	0.27500
LCD-80 REMOTE ANNUNCIATOR	2	X 0.06400	=	0.12800
MAX ALARM DRAW - ALL ADDRESS DEVICES	1	X 0.40000	=	0.40000
NAC-1 (See Voltage Drop Calculations)	1	X 0.41100	=	0.41100
NAC-2 (See Voltage Drop Calculations)	1	X 0.60200	=	0.60200
NAC-3 (See Voltage Drop Calculations)	1	X 0.31800	=	0.31800
NAC-4 (See Voltage Drop Calculations)	1	X 0.28400	=	0.28400
<b>TOTAL ALARM LOAD</b>				<b>2.41800</b>
Battery Requirements				
Standby Load		Required Standby Time in Hours		
Current (Amps)	0.22238	X 24.00000	=	5.33700
Alarm Load		Required Alarm Time in Hours		
Current (Amps)	2.41800	X 0.08333	=	0.20150
Total Ampere Hours (before derating factor)				5.53850
Derating Factor			X	1.2
<b>TOTAL AMPERE HOURS REQUIRED</b>				<b>6.64620</b>
<b>BATTERIES TO BE PROVIDED (2 - 12v)</b>				<b>7 AH</b>

#### Point to Point NAC Voltage Drop Calculation

9/13/2017

Project Name: 30-32 STATE STREET  
 Circuit Number: NAC-1

Nominal System Voltage	20.4 volts	Wire Gauge	16	Resistance Per 1000	4.89
Minimum Device Voltage	16.0 volts		16		4.89
Distance from source to 1st device	30 feet		16		4.89
Wire Gauge for balance of circuit			16		4.89
Max Output Current	1.50 amps				
Total Circuit Current	0.411 amps				
End of Line Voltage	19.96 volts				

**Circuit is within limits**

Device	Current	Distance previous device	Voltage at Device	Drop from source	Percent Drop
Device 1	0.054	30	20.28	0.121	0.59%
Device 2	0.074	20	20.21	0.190	0.93%
Device 3	0.121	40	20.10	0.301	1.48%
Device 4	0.162	90	19.96	0.444	2.18%
Totals	0.411	180			

Notes:  
 Wire resistance is doubled in the calculations for two wires (Positive and Negative).  
 The voltage calculated to the last device must not be lower than the manufactures listed minimum operating voltage (IE: rated operating voltage 16-33 VDC (24 VDC nominal)).

#### Point to Point NAC Voltage Drop Calculation

9/13/2017

Project Name: 30-32 STATE STREET  
 Circuit Number: NAC-3

Nominal System Voltage	20.4 volts	Wire Gauge	16	Resistance Per 1000	4.89
Minimum Device Voltage	16.0 volts		16		4.89
Distance from source to 1st device	70 feet		16		4.89
Wire Gauge for balance of circuit			16		4.89
Max Output Current	1.50 amps				
Total Circuit Current	0.318 amps				
End of Line Voltage	19.79 volts				

**Circuit is within limits**

Device	Current	Distance previous device	Voltage at Device	Drop from source	Percent Drop
Device 1	0.054	70	20.18	0.218	1.07%
Device 2	0.017	25	20.12	0.282	1.38%
Device 3	0.017	25	20.06	0.345	1.68%
Device 4	0.017	30	19.99	0.410	2.01%
Device 5	0.054	35	19.92	0.483	2.37%
Device 6	0.054	20	19.89	0.514	2.52%
Device 7	0.017	35	19.85	0.550	2.70%
Device 8	0.017	30	19.82	0.576	2.82%
Device 9	0.017	25	19.81	0.593	2.91%
Device 10	0.054	25	19.79	0.606	2.97%
Totals	0.318	320			

Notes:  
 Wire resistance is doubled in the calculations for two wires (Positive and Negative).  
 The voltage calculated to the last device must not be lower than the manufactures listed minimum operating voltage (IE: rated operating voltage 16-33 VDC (24 VDC nominal)).

#### Point to Point NAC Voltage Drop Calculation

9/13/2017

Project Name: 30-32 STATE STREET  
 Circuit Number: NAC-2

Nominal System Voltage	20.4 volts	Wire Gauge	16	Resistance Per 1000	4.89
Minimum Device Voltage	16.0 volts		16		4.89
Distance from source to 1st device	50 feet		16		4.89
Wire Gauge for balance of circuit			16		4.89
Max Output Current	1.50 amps				
Total Circuit Current	0.602 amps				
End of Line Voltage	18.81 volts				

**Circuit is within limits**

Device	Current	Distance previous device	Voltage at Device	Drop from source	Percent Drop
Device 1	0.054	50	20.11	0.294	1.44%
Device 2	0.017	25	19.97	0.428	2.10%
Device 3	0.017	35	19.79	0.610	2.99%
Device 4	0.054	15	19.71	0.686	3.36%
Device 5	0.054	25	19.60	0.798	3.91%
Device 6	0.017	15	19.54	0.858	4.20%
Device 7	0.017	35	19.41	0.991	4.86%
Device 8	0.054	25	19.32	1.082	5.30%
Device 9	0.054	40	19.19	1.206	5.91%
Device 10	0.017	25	19.13	1.271	6.23%
Device 11	0.017	25	19.07	1.331	6.52%
Device 12	0.017	30	19.00	1.398	6.86%
Device 13	0.054	35	18.93	1.471	7.21%
Device 14	0.054	20	18.90	1.503	7.37%
Device 15	0.017	35	18.86	1.538	7.54%
Device 16	0.017	30	18.84	1.564	7.67%
Device 17	0.017	25	18.82	1.582	7.75%
Device 18	0.054	25	18.81	1.595	7.82%
Totals	0.602	515			

Notes:  
 Wire resistance is doubled in the calculations for two wires (Positive and Negative).  
 The voltage calculated to the last device must not be lower than the manufactures listed minimum operating voltage (IE: rated operating voltage 16-33 VDC (24 VDC nominal)).

#### Point to Point NAC Voltage Drop Calculation

9/13/2017

Project Name: 30-32 STATE STREET  
 Circuit Number: NAC-4

Nominal System Voltage	20.4 volts	Wire Gauge	16	Resistance Per 1000	4.89
Minimum Device Voltage	16.0 volts		16		4.89
Distance from source to 1st device	80 feet		16		4.89
Wire Gauge for balance of circuit			16		4.89
Max Output Current	1.50 amps				
Total Circuit Current	0.284 amps				
End of Line Voltage	19.95 volts				

**Circuit is within limits**

Device	Current	Distance previous device	Voltage at Device	Drop from source	Percent Drop
Device 1	0.054	80	20.18	0.222	1.09%
Device 2	0.017	20	20.13	0.267	1.31%
Device 3	0.017	35	20.06	0.340	1.67%
Device 4	0.054	15	20.03	0.369	1.81%
Device 5	0.054	25	20.00	0.404	1.98%
Device 6	0.017	15	19.98	0.416	2.04%
Device 7	0.017	35	19.96	0.441	2.16%
Device 8	0.054	20	19.95	0.451	2.21%
Totals	0.284	245			

Notes:  
 Wire resistance is doubled in the calculations for two wires (Positive and Negative).  
 The voltage calculated to the last device must not be lower than the manufactures listed minimum operating voltage (IE: rated operating voltage 16-33 VDC (24 VDC nominal)).

#30 - APT.#8

#32 - APT.#7

**FOURTH FLOOR FIRE ALARM PLAN**  
 SCALE: 1/4"=1'-0"  
 FIELD VERIFY DIMENSIONS

RESERVED FOR CITY STAMP

REVISION	DESCRIPTION	DATE
0	ISSUED FOR REVIEW & APPROVAL	9/14/2017

**SEACOAST SECURITY**

4 Summer Street • Freeport, Maine 04032  
 Office: (207) 706-3369 • Fax: (207) 865-0852

**30-32 STATE STREET**  
**PORTLAND, MAINE**  
**FOURTH FLOOR FIRE ALARM PLAN**

DRAWN	JPB UNICAD JOB #17617
CHECKED	BRADY B. HAWES NICET III 138751
DATE	9/14/2017
REVISION	0
SCALE	1/4"=1'-0"

shop drawings created by  
 5794 W. 4900 St.  
 Hasler, UT 84013  
 Office: 801.985.0410

**UNICAD** Inc.  
 Fire Alarm Design & Drafting Services

www.unicad.net

**FA-6**