Honeywell Security
Battery & Power Budget Calculator
2003 Honeywell International Inc. All Rights Reserved

Facility Information	
Location:	108 SHERMAN STREET
Account #:	
Model:	Vista-128FBP
Engineer:	
Date:	10/18/2013

Standby and Alarm Times		Battery Contingency \Factor
Battery Standby (hours):	24	10%
Alarm Duration (minutes):	5	
Recommended Battery (AH)	14.3	

Recommended Battery Capacity OK for 48-Hr Recharge

SELECTED PANEL MAXIMUM OUTPUT RATINGS

PANEL:	Polling\ \Loop (mA)	Standby Auxiliary Power (mA)	Alarm Auxiliary Power (mA)	Panel Standby (mA)	Panel Alarm (mA)	Bell #1 Output (mA)	Bell #2 Output (If Used: mA)	Maximum Panel Standby Output	Maximum Panel Alarm Output	Max. Battery Supported By Panel
Vista-128FBP	128	1000	1700	300	470	1700	1700	1300	2800	34.4
								Total Standby	Total Alarm	
Calculated Current Draw	60.4	150	310	Calculated Bell Draw		0	0	210	370	
								Standby Budget	Alarm Budget	
Power Budget	67.6	850.0	1390.0	Bell Power Budget		1700.0	1700.0	1089.6	2429.6	
	Current OK	Current OK	Current OK			Current OK		Current OK	Current OK	
				External Bell Power Req'd (mA):		0.0		Ext. UL Power Req'd (mA):		0.0

KEYPADS	Enter Quantity	How many powered by 4297?	Standby (aux pwr)	Alarm Current (aux)	Polling Loop	Total Polling Loop	Total Standby Current	Total Alarm Current	Total External Current Required
6160CR (PANEL INTERFACE)	1	0	45	150			45	150	
6160CR2 (REMOTE ANNUNCIATOR	1	0	45	160			45	160	

AUXILIARY POWERED DEVICES	Enter Quantity	How many powered by 4297?	Standby (aux pwr)	Alarm Current (aux)	Polling Loop	Total Polling Loop	Total Standby Current	Total Alarm Current	Total External Current Required
5881EN RECEIVER	1	0	60	0			60	0	

POLLING LOOP DEVICES	Enter Quantity	How many powered by 4297?	Standby (aux pwr)	Alarm Current (aux)	Polling Loop	Total Polling Loop	Total Standby Current	Total Alarm Current	Total External Current Required
4193SN TWO ZONE SIM	16	0			1.5	24			
5192SD SMOKE DETECTOR	13	0			2.8	36.4			

FPS1 Battery Calculation

10/18/2013

PROJECT NAME: 108 SHERMAN STREET
Required Standby Time: 24 Hours
Required Alarm Time: 5 Minutes

Regulated Load in Standby

Device Type	Number of Devices		Current (Amps)		Total Current (Amps)
Altronix AL802ULADA	1	X	0.09000	=	0.09000
TOTAL STANDBY LOAD					0.09000

Regulated Load in ALARM

Device Type	Number of Devices		Current (Amps)		Total Current (Amps)
Altronix AL802ULADA	1	X	0.17500	=	0.17500
FPS1-1 (See voltage drop calcs for device quantity)	1	X	0.67900	=	0.67900
FPS1-2	1	X	0.81300	=	0.81300
FPS1-3	1	X	0.44600	=	0.44600
FPS1-4	1	X	0.37800	=	0.37800
TOTAL ALARM LOAD					2.49100

Battery Requirements

Standby Load			Required Standby Time in Hours		
Current (Amps)	0.09000	X	24.00000	=	2.16000
Alarm Load			Required Alarm Time in Hours		
Current (Amps)	2.49100	X	0.08333	=	0.20758
Total Ampere Hours (before derating factor)					2.36758
Derating Factor				X	1.2
TOTAL AMPERE HOURS REQUIRED				=	2.84110
BATTERIES TO BE PROVIDED (2 – 12v)					7 AH

GENERAL NOTES:

1. THESE DRAWINGS ARE DIAGRAMMATIC. REFER TO THE ARCHITECTURAL DRAWINGS FOR EXACT DIMENSIONS.
2. INSTALLATION SHALL COMPLY WITH NEC, NFPA 72 AND ALL OTHER APPLICABLE CODES AS REQUIRED BY THE LOCAL AUTHORITY HAVING JURISDICTION.
3. WIRING DEPICTED ON THESE PLANS IS SCHEMATIC – ACTUAL WIRE LOCATIONS MAY DIFFER FROM THESE PLANS. WIRING SHALL BE PERFORMED AS ACTUAL BUILDING CONSTRUCTION CONDITIONS ALLOW AND TO MINIMIZE PENETRATIONS THROUGH AREA SEPARATION WALLS AND FIRE WALLS. THE USE OF A RACEWAY IS PERMITTED AS LONG AS NO 110V OR HIGHER VOLTAGE CABLES ARE IN THE SAME RACEWAY.
4. FIRE RATINGS SHALL BE MAINTAINED FOR ALL PENETRATIONS THROUGH FIRE–RATED CONSTRUCTION.
5. POWER FOR ALL FIRE ALARM PANELS AND FIRE ALARM POWER SUPPLIES MUST BE PROVIDED BY A DEDICATED AC BRANCH CIRCUIT.
6. POWER–LIMITED AND NONPOWER–LIMITED CIRCUIT WIRING MUST REMAIN SEPARATED IN CABINET. ALL POWER–LIMITED CIRCUIT WIRING MUST REMAIN AT LEAST 0.25" AWAY FROM ANY NONPOWER–LIMITED CIRCUIT WIRING. FURTHERMORE, ALL POWER–LIMITED AND NONPOWER–LIMITED CIRCUIT WIRING MUST ENTER AND EXIT THE CABINET THROUGH DIFFERENT KNOCK OUTS AND/OR SEPARATE CONDUITS.
7. WHEN UTILIZING CLASS "A" CIRCUITS, SEPARATE OUTGOING AND RETURN CONDUCTORS OF CLASS "A" CIRCUITS BY A MINIMUM OF 12" WHERE RUN VERTICALLY AND 48" WHERE RUN HORIZONTALLY.
8. WHEN UTILIZING SHIELDED CABLE TIE SHIELDS THROUGH AND INSULATE AT EACH JUNCTION BOX. INSULATE AND TAPE BACK AT END.
9. ALL FIRE ALARM CABLING SHALL BE ACCEPTABLE TO THE FIRE ALARM EQUIPMENT MANUFACTURER FOR THE INTENDED PURPOSE.
10. SMOKE DETECTORS SHALL NOT BE INSTALLED UNTIL AFTER CONSTRUCTION CLEAN–UP IS COMPLETED AND FINAL.
11. LOCATE SMOKE DETECTORS A MINIMUM OF THREE (3) FEET FROM MECHANICAL DIFFUSERS. WALL–MOUNTED SMOKE DETECTORS SHALL BE LOCATED A MINIMUM OF 4" AND A MAXIMUM OF 12" FROM CEILING. CEILING–MOUNTED SMOKE DETECTORS SHALL BE MOUNTED ON CEILINGS AND NOT ON THE BOTTOMS OF BEAMS OR JOISTS.
12. PROVIDE SYNCHRONIZATION OF ALL VISUAL NOTIFICATION APPLIANCE CIRCUITS. PROVIDE ALL REQUIRED SYNC MODULES. PROVIDE A MULTI–SYNC MODE SLAVE CONNECTION BETWEEN ALL SYNC MODULES.
13. VERIFY ALL FIELD SELECTABLE AUDIBILITY SETTINGS OF NOTIFICATION APPLIANCES WITH FIRE ALARM CONTRACTOR.
14. UPON COMPLETION OF THE FIRE ALARM SYSTEM INSTALLATION AND PROGRAMMING, THE INSTALLING CONTRACTOR SHALL PERFORM FINAL TESTING OF THE ENTIRE SYSTEM, PER ALL APPLICABLE CODES, AND SHALL COORDINATE AND PERFORM A FINAL FIRE ALARM SYSTEM INSPECTION.
15. PROVIDE OFF–SITE MONITORING AS REQUIRED BY THE INTERNATIONAL FIRE CODE, SECTION 907.15 AND THE LOCAL AUTHORITY HAVING JURISDICTION.
16. INSTALLING CONTRACTOR SHALL, PHYSICALLY, LABEL ALL INITIATING DEVICES AND NOTIFICATION APPLIANCE CIRCUIT END OF LINE (WHEN WIRING CLASS "B"). THESE LABELS SHALL BE IN PLACE PRIOR TO START–UP AND TESTING.

APPLICABLE CODES:

MAINE UNIFORM ENERGY & BUILDING CODE
PORTLAND CITY CODE, CHAPTER10, FIRE PREVENTION & PROTECTION
NFPA 1, FIRE CODE, & NFPA 101, LIFE SAFETY CODE

FIRE ALARM SYMBOL LEGEND

NOTE: ALL SYMBOLS MAY NOT BE USED ON THIS PROJECT

SYMBOL	DESCRIPTION	MOUNTING
FCP	FIRE ALARM CONTROL PANEL	WALL–TOP @ 66"
FPS	FIRE ALARM POWER SUPPLY	FIELD VERIFY
FSA	FIRE SYSTEM ANNUNCIATOR	WALL–TOP @ 66"
FSD	FIRE/SMOKE DAMPER	BY OTHERS
	SMOKE DETECTOR	CEILING
	DUCT SMOKE DETECTOR	BY OTHERS
	HEAT DETECTOR	CEILING
CM	ADDRESSABLE CONTROL MODULE	FIELD VERIFY
MM	ADDRESSABLE MONITOR MODULE	FIELD VERIFY
P	MANUAL PULL STATION	WALL @ 48"
R	CONTROL RELAY (MULTI–VOLTAGE)	FIELD VERIFY
RM	ADDRESSABLE RELAY MODULE	FIELD VERIFY
KB	KNOX BOX	FIELD VERIFY
	MAGNETIC DOOR HOLDER	FIELD VERIFY
	WATER FLOW SWITCH	BY OTHERS
	VALVE TAMPER SWITCH	BY OTHERS
	BELL	BY OTHERS
	CEILING MOUNT STROBE	FIELD VERIFY
	CEILING MOUNT HORN / STROBE	FIELD VERIFY
	CEILING MOUNT SPEAKER / STROBE	FIELD VERIFY
	HORN	WALL @ 10'–0
	HORN / STROBE	WALL 80"–96"
	SPEAKER / STROBE	WALL 80"–96"
SP	SPEAKER	WALL @ 90"
	STROBE	WALL 80"–96"

ABBREVIATION	DESCRIPTION
E	EXISTING
G	WITH GUARD
P	PENDENT MOUNT
R	RESIDENTIAL (110V)
S	SOUNDER BASE
WP	WEATHER PROOF
EOL	END OF LINE RESISTOR
EOLR	END OF LINE RELAY
AWG	AMERICAN WIRE GAUGE
TWP	TWISTED PAIR
TWSP	TWISTED SHIELDED PAIR
FPLP	FIRE POWER LIMITED PLENUM
FPLR	FIRE POWER LIMITED RISER

SPEAKER WATTAGE (2W) 75 STROBE CANDELA 30

DEVICE ADDRESS
L1D001 OR D01
(L – DENOTES LOOP #)
(D or M – DENOTES DETECTOR OR MODULE #)

1–#16/2 TWP
WIRE TYPE ABBREVIATED
CONDUCTOR COUNT
WIRE SIZE
OF CABLES (IF OMITTED ONLY 1 CABLE NEEDED)

RESERVED FOR CITY STAMP

OPERATIONS MATRIX

FIRE ALARM INPUT \ FIRE ALARM OUTPUT	ACTIVATE ALARM INDICATOR	ACTIVATE AUDIBLE ALARM	ACTIVATE TROUBLE INDICATOR	ACTIVATE AUDIBLE TROUBLE INDICATOR	TRANSMIT ALARM SIGNAL	TRANSMIT TROUBLE SIGNAL
SMOKE DETECTORS	●	●			●	
HEAT DETECTORS	●	●			●	
PULL STATIONS	●	●			●	
FIRE ALARM AC POWER FAIL			●	●		●
FIRE ALARM LOW BATTERY			●	●		●
OPEN CIRCUIT			●	●		●
GROUND FAULT			●	●		●
NAC SHORT CIRCUIT			●	●		●
LOSS OF AC TO BUILDING			●	●		●

WIRE NOTE:
VERIFY EXACT WIRE TYPE WITH FIRE ALARM CONTRACTOR BEFORE ORDERING.

FIRE ALARM RISER DIAGRAM

SCHEMATIC: NO SCALE

REVISION	DESCRIPTION	DATE
0	ISSUED FOR REVIEW & APPROVAL	10/19/2013

CUNNINGHAM
Security Systems
10 Princes Point Road, Yarmouth, Maine 04096
Office: 207.846.3350 • Fax: 207.846.6080

108 SHERMAN STREET
PORTLAND, MAINE 04101

CALCS, LEGEND, MATRIX, NOTES, RISER DIAGRAM

DRAWN	JPB UNICAD JOB #13608
CHECKED	WAYNE B. HAWS NICET IV 90496
DATE	10/18/2013
REVISION	
SCALE	

shop drawings created by: 5794 W. 4600 So., Hooper, UT 84315 Office: 801.985.0410
UNICAD Inc.
www.unicad.net Fire Alarm Design & Drafting Services

Date: 10/28/13
Reviewed for Code Compliance
Inspectors Division
Approved with Conditions
CITY OF PORTLAND RESIGNAL MAINE