

**EST Addressable Fire Alarm System
 UNE - Ludcke Auditorium
 Portland, Maine**

[Click Here to Return to
 Bill of Material/Index](#)

BATTERY STANDBY CALCULATIONS - Fire Alarm Control Panel

QTY	Model #	Description	Quiescent Current	Alarm Current	Total Quiescent	Total Alarm	
1	iO64R	Base Panel	0.155000	0.204000	0.155000	0.204000	Amp
1	SA-232	RS-232 Communications Card	0.013000	0.013000	0.013000	0.013000	Amp
8	SIGA-278	Addressable Manual Pull Station	0.000250	0.000400	0.002000	0.003200	Amp
16	SIGA2-PS	Addressable Smoke Detector	0.000045	0.018000	0.000720	0.288000	Amp
5	SIGA2-HFS	Addressable Heat Detector	0.000045	0.018000	0.000225	0.090000	Amp
2	SIGA-CR/MCR	Addressable Control Module	0.000100	0.000100	0.000200	0.000200	Amp
1	EC-50CR	Beam Detector	0.004000	0.014000	0.004000	0.014000	Amp
5	G4RF-S7VM	Speaker/Strobe Unit (15 Candela)	0.000000	0.088000	0.000000	0.440000	Amp
5	G4RF-S7VM	Speaker/Strobe Unit (30 Candela)	0.000000	0.193000	0.000000	0.965000	Amp
2	G4RF-S7VM	Speaker/Strobe Unit (110 Candela)	0.000000	0.248000	0.000000	0.496000	Amp
5	G1RF-VM	Strobe Unit (15 Candela)	0.000000	0.071000	0.000000	0.355000	Amp
1	495S1280R	Exterior Beacon	0.000000	0.350000	0.000000	0.350000	Amp
					Total	0.175145	3.2184 Amp

Total Quiescent x Time Required (60 Hours): **10.5087** Ah
 Total Alarm x Time Required (15 Minutes): **0.8046** Ah
Total Battery Required: 11.3133 Ah
Total Battery Required (+) 20% Spare Capacity: 13.57596 Ah
Battery Supplied: 18 Ah