



D1256RB Fire Keypad



- ▶ **Compatible with Bosch GV3 control panels and GV2 control panels (firmware version 7.04 and higher)**
- ▶ **Provides system control with easy to use function keys**
- ▶ **Built-in multi-tone sounder**
- ▶ **Easy to read vacuum-fluorescent display (VFD) shows complete system status in English**
- ▶ **Programmable custom text for each point**
- ▶ **Local system test display**
- ▶ **Molded red ABS plastic construction**

The D1256RB Fire Keypad is a full-function system controller and annunciator. This SDI bus compatible device works with the Bosch Security Systems, Inc. GV3 control panels and GV2 control panels (firmware version 7.04 and higher). Four one-touch function keys provide user-friendly control over the system. The function keys allow the user to silence the audible alarm output, silence the trouble sounder, reset the annunciator display, and reset the system detectors. Four additional navigational keys allow access to other programmed system functions. The D1256RB can be mounted in secure areas.

Certifications and Approvals

Region	Certification
USA	UL UOXX: Control Unit Accessories, System (ANSI/UL 864)
	FM
	CSFM 7165-1615:0119 FIRE ALARM CONTROL UNIT (COMMERCIAL)
	FDNY-CoA 6059

Functions

Display

The display uses words, numbers, and symbols to show the status of the fire system. When several events occur, each event is shown in order of priority followed by the time of occurrence. In conjunction with the 16-character vacuum-fluorescent display (VFD), four LEDs provide the following system status indications:

- Fire
- Silenced
- Supervisory
- Trouble

Installation/Configuration Notes

Compatible Control Panels

The D1256RB Fire Keypad is compatible with GV3 control panels¹ and GV2 control panels¹ with firmware version 7.04 or higher. The keypad will work with G Series Control Panels prior to GV2 v7.04; however the LEDs will not operate.

¹ The D7212GV3 and D7212GV2 are not listed for commercial fire applications.

Mounting Considerations

The keypad is a low profile, surface-mounted unit molded in durable red plastic with three mounting holes in the base that allow secure, correct positioning during installation. Protect the surface-mounted keypad by mounting it to a D56 or D56R Conduit Back Box. For desktop applications, the keypad can be mounted to a D55 Desk Stand.

Note Do not install the keypad in direct sunlight. This damages the module components and makes the display less visible. Do not mount in wet or moist locations.

Wiring Considerations

The keypad connects to the control panel for data and power through a standard four-wire flying lead cable. For field wiring use 0.8 mm (22 AWG) or 1.2 mm (18 AWG) wires. Resistance cannot exceed 25 Ω. The field wiring connects to a four-wire harness supplied with the unit.

Note Use shielded cable where excessive electromagnetic interference is a problem.

Parts Included

Quant.	Component
1	Keypad
1	Hardware pack
1	Literature pack

Technical Specifications

Environmental Considerations

Relative Humidity: 5% to 85% non-condensing at +30°C (+86°F)

Temperature (operating): 0°C to +50°C (+32°F to +122°F)

Mechanical Properties

Color: Red

Dimensions: 11.7 cm x 21 cm x 2 cm
(4.6 in. x 8.2 in. x 0.8 in.)

Material: CHI MEI POLYLAC PA757 ABS with UV Stabilizer. UL94-HB Fire Rated

Power Requirements

Current: 104 mA minimum, 225 mA maximum

Voltage: 12 VDC nominal supplied by the control panel

Trademarks

Due to the nature of this material, this document refers to hardware and software products by their trade names. In most, if not all cases, these designations are claimed as trademarks or registered trademarks by their respective companies in one or more countries. It is not Bosch's intent to use any of these names generically. The reader is therefore cautioned to investigate all claimed trademark rights before using any of these names other than to refer to the product described.

POLYLAC is a registered trademark of CHI MEI Industrial Corporation, LTD.

Plexiglas is a registered trademark of Arkema.

Ordering Information

D1256RB Fire Keypad	D1256RB
----------------------------	----------------

The D1256RB Fire Keypad provides our one-touch function keys for user-friendly control over the system

Accessories

D55 Keypad Desk Stand	D55
------------------------------	------------

Portable desk stand in smoke colored Plexiglas.

D56 Surface Mount Conduit Box	D56
--------------------------------------	------------

White surface mount box.

D56R Red Surface Mount Conduit Box	D56R
---	-------------

Red surface mount box.

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by