

**Gamewell Fire Alarm System Addition
1 City Center - 1st Floor
Portland, Maine**

SEQUENCE OF OPERATION MATRIX

	<p><i>Alarm Signal to Portland FD via Masterbox</i></p> <p><i>Annunciate at FCC and Remote Annunciators</i></p> <p><i>Activate Evacuation Sequence</i></p> <p><i>Activate Elevator Recall Sequence (Elevator Lobby & Machine Rooms Only)</i></p> <p><i>Release / Unlock required doors and exitways</i></p> <p><i>Interface w/ HVAC, Sound & Mechanical Equipment as Required</i></p> <p><i>Supervisory Signal to 24 Hour Attendant Desk</i></p> <p><i>Trouble Signal to 24 Hour Attendant Desk</i></p>								
System Inputs	A	B	C	D	E	G	J	H	System Inputs
System Waterflow	x	x	x		x	x			System Waterflow
System Tamper Switch		x					x		System Tamper Switch
Water Level/ Pressure Switch		x					x		Water Level/ Pressure Switch
Manual Pull Stations	x	x	x		x				Manual Pull Stations
Area Smoke Detector	x	x	x	x	x	x			Area Smoke Detector
Area Heat Detectors	x	x	x	x	x	x			Area Heat Detectors
Duct Smoke Detector		x					x		Duct Smoke Detector
Fire Alarm - AC Failure		x						x	Fire Alarm - AC Failure
Fire Alarm - Low Battery		x						x	Fire Alarm - Low Battery
Signal Line Open Circuit		x						x	Signal Line Open Circuit
Signal Line Ground Fault		x						x	Signal Line Ground Fault
Strobe Circuit Open		x						x	Strobe Circuit Open
Strobe Circuit Ground		x						x	Strobe Circuit Ground
Audio Circuit Open		x						x	Audio Circuit Open
Audio Circuit Ground		x						x	Audio Circuit Ground
System Ground Fault		x						x	System Ground Fault
	A	C	D	D	E	F	G	H	