



1. WIRE AND CONNECT ALL NEW 120/208V DEVICES AND EQUIPMENT ON THIS FLOOR TO PANEL PH-8B.
2. WIRE AND CONNECT ALL 277/480V EQUIPMENT ON THIS FLOOR TO PANEL PH-8-1 OR PH-8-2.

B9 DRAWING NOTES

- 1 WIRE AND CONNECT TO 20A 1P CB 277V CIRCUIT WITH (2)#12, (1)#12G. PROVIDE 20A 1P CBs AS NEEDED.
- 2 WIRE AND CONNECT TO EXISTING 277V PANEL USING (2)#8, (1)#10G. PROVIDE 50A 1P CIRCUIT BREAKER IN EXISTING PANEL.
- 3 WIRE AND CONNECT TO EXISTING 480V PANEL USING (3)#10, (1)#10G. PROVIDE 30A 3P CIRCUIT BREAKER IN EXISTING PANEL.
- 4 WIRE AND CONNECT TO LOCAL 120V RECEPTACLE CIRCUIT.
- 5 WIRE AND CONNECT TO 30A 1P CB 277V CIRCUIT WITH (2)#10, (1)#10G. PROVIDE 30A 1P CBs AS NEEDED.
- 6 MOUNT DEVICES AT BENCH 3'-0" AFF.

A9 KEYNOTES