NOTIFIER by Honeywell

System Power Requirements

Notifier NFS2-640 Fire Alarm Control Panel

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 07/29/13

Protected Premises: USM - Luther Bonney Building
Address:
City: Portland State: Maine Zip:

Prepared By: BK Systems, Inc. Phone: 603-647-8775
Address: 4 Cote Avenue Email:
City: Goffstown State: New Hampshire Zip: 03045

AC Branch Current Requirements

5.00 AMPS @ 120 VAC

Current required by source to power the fire alarm system.

Primary Standby Load

1.19 Amps

Current load on the primary power supply during non-alarm conditions.

Primary Alarm Load

1.55 Amps

Current load on the primary power supply during alarm conditions.

Secondary Load Requirements

35.83 Amp Hours

Total Secondary Load from the calculation table below.

Current Draw		Time (hours)	Total (AH)
Secondary Standby Load 1.233 A	x	Required Standby Time 24 hours	29.59
Secondary Alarm Load 1.590 A	x	Required Alarm Time 0.167 hours	0.27
		Total Secondary Load	29.86
		Derating factor	x 1.2
		Secondary Load Requirements (Amp Hours)	**35.83** AH

Battery Selection

55 Amp Hours

Select batteries from the list below.

55 AH BAT-12550 Battery (12 volt)

● Two ● Four (two 12VDC sets in parallel)

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 07/29/13

Battery Distribution Chart

Shows amp-hour distribution of your selections.

Comments

1. Battery size exceeds FACP capacity. BB-55 or other external battery box
2. Selected battery size meets secondary load requirements.
3. The selected batteries (55AH) are within the charger range of this power supply (18-200AH).

Spare Battery Capacity	19.17	Battery Selection (AH) - Secondary Load Requirements (AH)
Secondary Standby Load	35.51	Secondary Standby Load (AH) * Derating Factor
Secondary Alarm Load	0.32	Secondary Alarm Load (AH) * Derating Factor

NOTIFIER by Honeywell

Device Current Draw

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 07/29/13

NFS2-640 Fire Alarm Control Panel

Quantity x [device current draw] = total current draw per device (in amps)

Part Number	Qty	Primary Non-Alarm	Primary Alarm	Sec
CPU2-640	1	x [0.25000] = 0.25000	x [0.25000] = 0.25000	x [0.25000] = 0.25000
CPS-24	1	x [0.00000] = 0.00000	x [0.00000] = 0.00000	x [0.04000] = 0.04000
NCA2 - Backlight On	1	x [0.40000] = 0.40000	x [0.40000] = 0.40000	x [0.40000] = 0.40000
HPFF8 Power Supplies	2	x [0.00000] = 0.00000	x [0.00000] = 0.00000	x [0.00000] = 0.00000
DAA Series	3	x [0.00000] = 0.00000	x [0.00000] = 0.00000	x [0.00000] =
DVC-EM	1	x [0.44000] = 0.44000	x [0.44000] = 0.44000	x [0.44000] = 0.44000
DVC-KD	1	x [0.06000] = 0.06000	x [0.06000] = 0.06000	x [0.06000] = 0.06000
NBG-12LX	19	x [0.00038] = 0.00713	x [0.00000] = 0.00000	x [0.00038] = 0.00713
FSP-851	74	x [0.00030] = 0.02220	x [0.00000] = 0.00000	x [0.00030] = 0.02220
FST-851	20	x [0.00030] = 0.00600	x [0.00000] = 0.00000	x [0.00030] = 0.00600
DNR	7	x [0.00000] = 0.00000	x [0.00000] = 0.00000	x [0.00000] = 0.00000
FSP-851R	7	x [0.00030] = 0.00210	x [0.00000] = 0.00000	x [0.00030] = 0.00210
RTS151	7	x [0.00000] = 0.00000	x [0.00000] = 0.00000	x [0.00000] = 0.00000
FMM-1	4	x [0.00035] = 0.00140	x [0.00000] = 0.00000	x [0.00035] = 0.00140
FMM-101	2	x [0.00035] = 0.00070	x [0.00000] = 0.00000	x [0.00035] = 0.00070
FRM-1	14	x [0.00026] = 0.00357	x [0.00000] = 0.00000	x [0.00026] = 0.00357
SLC Loop Device Activation Current	1	x [0.00000] = 0.00000	x [0.40000] = 0.40000	x [0.00000] = 0.00000
Total (Amperes):		1.1931 A	1.5500 A	1.2331 A

Part Number	Qty	Secondary Alarm
Total Primary Alarm Load - C2	1	x [1.55000] = 1.55000
CPS-24	1	x [0.04000] = 0.04000
Total (Amperes):		1.5900 A