NOTIFIER by Honeywell

System Power Requirements

DAA-7525 Digital Audio Amplifier

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 05/19/15

Protected Premises: Maine Medical Center - Wound Care Addition Date
Address: 335 Brighton Avenue
City: Portland State: ME Zip: 04103

Prepared By: Norris Inc. Phone: 207-883-3473
Address: 2257 Broadway Email:
City: South Portland State: ME Zip: 04106

AC Branch Current Requirements

4.50 AMPS @ 120 VAC

Current required by source to power the fire alarm system.

Secondary Load Requirements

10.38 Amp Hours

Total Secondary Load from the calculation table below.

Current Draw		Time (hours)	Total (AH)
Secondary Standby Load 0.350 A	x	Required Standby Time 24 hours	8.40
Secondary Alarm Load 0.984 A	x	Required Alarm Time (hours) 0.250 hours	0.25
		Total Secondary Load	8.65
		Derating factor	x 1.2
		Secondary Load Requirements	**10.38** AH

Battery Selection

12 Amp Hours

Select batteries from the list below.

12 AH BAT-12120 Battery (12 volt)

(•) Two ( ) Four (two 12VDC sets in parallel)

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 05/19/15

Battery Distribution Chart

Shows amp-hour distribution of your selections.

Comments

1. Batteries will fit in the FACP cabinet.
2. Selected battery size meets secondary load requirements.
3. The selected batteries (12AH) are within the charger range of this power supply (12-55AH).

Spare Battery Capacity	1.62	Battery Selection (AH) - Secondary Load Requirements (AH)
Secondary Standby Load	10.08	Secondary Standby Load (AH) * Derating Factor
Secondary Alarm Load	0.30	Secondary Alarm Load (AH) * Derating Factor