NAC Circuit Voltage Drop Calculation **Project Name CMP- Portland Service Center** Date 2/6/2017 Circuit Number Nac#5 Area Covered NAC Source Alarm Voltage 19.1 Wire Resistance Minimum Device Voltage 16 Gauge Per KFt Cable Distance to first appliance 150 14 3.14 2.497 **Total Circuit Current** 14 Wire Gauge for balance of circuit 3.14 Distance Circuit is within limits from Device previous Voltage at Drop from Percent Current device Device source Drop 0.397 17.92 1.18 6.2% Appliance 1 Appliance 2 0.397 35 17.69 1.41 7.4% Appliance 3 0.179 25 17.56 1.54 8.1% 35 0.346 Appliance 4 17.39 1.71 8.9% Appliance 5 0.176 45 17.23 1.87 9.8% 0.417 75 16.99 2.11 Appliance 6 11.0% Appliance 7 0.125 45 16.91 2.19 11.5% Appliance 8 0.230 75 16.80 2.30 12.0% Appliance 9 0.230 25 16.78 2.32 12.1% **END** 16.78 2.32 12.1% END 16.78 2.32 12.1% **END** 16.78 2.32 12.1% 2.32 **END** 16.78 12.1% **END** 16.78 2.32 12.1% **END** 16.78 2.32 12.1% 2.497 Totals 510

Appliance circuit voltage drop calculations start at "end of battery life" as NAC Source Alarm Voltage and use 20% below nameplate rating for Minimum Appliance Voltage.

Note. Wire resistance is based on the 2014 NEC Table 8 Uncoated DC resistance. All resistance is based on solid conductors