P300
Battery & Voltage Drop Calculations

Project Name:		**Standby**	
		Alarm	
Installed By:		**Batt Effi**	
Designed By:		**SL**	
Date:		**NAC Source V**	

Model #: P300
Panel ID:
Location:

Max Panel Current (

User assumes all responsibility current draw values in this wo submittal.

Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 03/29/16

Qty	FACP Part #	Description	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
1	P300	Analog Addressable FACP	0.130	0.130	0.220	0.220
			Panel Standby:	**0.130**	**Panel Alarm:**	**0.220**

	P-LINK (RS-485)		Standby		Alarm	
1	UD-1000	DACT	0.016	0.016	0.023	0.023
	RA-6075	LCD Annunciator	0.020		0.025	
	RA-6500	LCD Annunciator	0.020		0.050	
	LED-16	LED Annunciator	0.025		0.025	
	LED-16	LED Annunciator LED Power*	0.015		0.210	
1	CA-6075	Class A Module	0.012	0.012	0.044	0.044
	PSN-1000(E)	Power Expander	0.015		0.015	
1	SLCE-127	SLC Expander (2 Max)	0.060	0.060	0.060	0.060
	RLY-5	Relay Expander	0.025		0.035	
	RLY-5	Relay Expander Power*	0.010		0.135	
	DRV-50	LED Driver Module	0.025		0.025	
	DRV-50	LED Driver Module LED Power*	0.010		0.215	
	FCB-1000	Fire Communications Bridge	0.025		0.025	
	FIB-1000	Fiber Interface Board	0.030		0.030	
	SPG-1000	Serial Parallel Gateway	0.040		0.040	
		(Maximum current draw on P-Link limited to 1 Amp)	**P-LINK Standby:**	**0.088**	**P-LINK Alarm:**	**0.127**

Only enter quantity if PLINK power is being used to power devices

	SLC Devices		Standby		Alarm	
100	PSA	Analog Photo Smoke	0.000325	0.032500	0.000325	0.032500
	PSHA	Analog Photo Smoke/Heat	0.000325		0.000325	
5	RHA	Analog Rate of Rise Heat	0.000325	0.001625	0.000325	0.001625
	FHA	Analog Fixed Temp Heat	0.000325		0.000325	
13	APS-SA/APS-DA	Addressable Pull Station Single/Dual Action	0.000325	0.004225	0.000325	0.004225
7	MCM	Mini Contact Input Module	0.000325	0.002275	0.000325	0.002275
	SCM-4	Single Contact Input Module	0.000325		0.001000	
9	DCM-4	Dual Contact Input Module	0.000325	0.002925	0.001000	0.009000
7	TRM-4	Twin Relay Output Module	0.000325	0.002275	0.001000	0.007000
	CIZM-4 *	Conventional Zone Input Mod	0.000325		0.001000	
10	MOM-4 *	Monitored Output Module	0.000325	0.003250	0.001000	0.010000
	ARB *	Detector Base w/Relay	0.000325		0.000325	
73	ASB *	Detector Base w/Sounder	0.000325	0.023725	0.000325	0.023725
	SCI **	Short Circuit Isolator (Class A)	0.000325		0.002340	
	AIB **	Detector Base w/Isolator (Class A)	0.000325		0.002340	
	SCI/AIB Class B **	Current Draw from Install Manual				
2		SLC Loop Alarm LED Current	0.000000	0.000000	0.027000	0.054000
*	Requires Aux Power (Configure Below)		**SLC Standby:**	**0.072800**	**SLC Alarm:**	**0.144350**
**	See the installation manual for special considerations when installing AIB, SCI devices on Class B loops.					

NAC Circuits (See NAC Configuration below)			Standby (amps)	
Ckt	Use	Description	Total	
1			0.00000	
2			0.00000	
		NAC Standby:	0.00000	NAC

I/O Circuits (See I/O Configuration below)			Standby (amps)	
Ckt	Use	Description	Total	
1			0.00000	
2			0.00000	
		I/O Standby:	0.00000	I/O

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 03/29/16

Battery Calculation Summary

	Standby (amps)		Alarm (amps)
Panel Current:	0.13000		0.22000
P-Link Current:	0.08800		0.12700
SLC Device Current:	0.07280		0.14435
NAC Circuit Current:	0.00000		5.00000
I/O Circuit Current:	0.00000		0.00000
Total Standby:	**0.290800**	Total Alarm:	**5.49135**
Standby Hours:	24	Alarm Mins:	5
AH Required:	**6.98**	AH Required:	**0.46**

SLC Loop Type:	Class B
Point Capacity Needed:	233
Point Capacity Actual:	254

Total Combined Standby & Alarm AmpHours Required:	7.44
Efficiency Factor:	80%
Required Battery AmpHours:	**9.30**
Battery AmpHours Provided:	

Note: The cabinet will house two 8 AH or 18 AH batteries. The charging circuit is rated for up to two 55 AH batteries.

POTTER
The Symbol of Protection

NAC Circuit Configuration & Voltage Drop

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 03/29/16

NAC 1

MAX Circuit Current (amps): 3 Source Voltage Used

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @
#14 Solid	2.5		0.000	3.000	20.4

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
1	Horn/strobes	Total	0.000000	0.000000	3.000000	3.000000
			Total Standby:	0.00000	Total Alarm:	3.00000

NAC 2

MAX Circuit Current (amps): 3 Source Voltage Used (VDC): 20.4

Usage: Description:

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	2.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
1	Horn/strobes	Total	0.000000	0.000000	2.000000	2.000000
			Total Standby:	0.00000	Total Alarm:	2.00000

POTTER
The Symbol of Protection

I/O Circuit Configuration & Voltage Drop

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 03/29/16

I/O 1

MAX Circuit Current (amps): 1 Source Voltage Used

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @
#14 Solid	2.5		0.000	0.000	20.4

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**0.00000**

I/O 2

MAX Circuit Current (amps): 1 Source Voltage Used (VDC): 20.4

Usage: **Description:**

Wire Type	Ohms/1000ft	Length 1-Way	Actual Ohms	Max Load (amps	Volts @ EOL	Min Volts Req'd
#14 Solid	2.5		0.000	0.000	20.40	16

Qty	Lookup Type	Circuit Devices Desc	Standby (amps) Each	Standby (amps) Total	Alarm (amps) Each	Alarm (amps) Total
		User can add devices on the fly				
		to these bottom 5 rows				
		(No lookup function)				
			Total Standby:	**0.00000**	**Total Alarm:**	**0.00000**

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 03/29/16

User Defined Parts		
Description	**Standby**	**Alarm**
User Defined 1		
User Defined 2		
User Defined 3		
User Defined 4		
User Defined 5		
User Defined 6		
User Defined 7		
User Defined 8		
User Defined 9		
User Defined 10		
User Defined 11		
User Defined 12		
User Defined 13		
User Defined 14		
User Defined 15		
User Defined 16		
User Defined 17		
User Defined 18		
User Defined 19		
User Defined 20		
User Defined 21		
User Defined 22		
User Defined 23		
User Defined 24		
User Defined 25		
User Defined 26		
User Defined 27		
User Defined 28		
User Defined 29		
User Defined 30		
User Defined 31		
User Defined 32		
User Defined 33		
User Defined 34		
User Defined 35		
User Defined 36		
User Defined 37		
User Defined 38		
User Defined 39		
User Defined 40		
User Defined 41		
User Defined 42		
User Defined 43		
User Defined 44		
User Defined 45		
User Defined 46		
User Defined 47		
User Defined 48		
User Defined 49		
User Defined 50		
User Defined 51		
User Defined 52		
User Defined 53		
User Defined 54		
User Defined 55		

User Defined 56		
User Defined 57		
User Defined 58		
User Defined 59		
User Defined 60		
User Defined 61		
User Defined 62		
User Defined 63		
User Defined 64		
User Defined 65		
User Defined 66		
User Defined 67		
User Defined 68		
User Defined 69		
User Defined 70		
User Defined 71		
User Defined 72		
User Defined 73		
User Defined 74		
User Defined 75		
User Defined 76		
User Defined 77		
User Defined 78		
User Defined 79		
User Defined 80		
User Defined 81		
User Defined 82		
User Defined 83		
User Defined 84		
User Defined 85		
User Defined 86		
User Defined 87		
User Defined 88		
User Defined 89		
User Defined 90		
User Defined 91		
User Defined 92		
User Defined 93		
User Defined 94		
User Defined 95		
User Defined 96		
User Defined 97		
User Defined 98		
User Defined 99		
User Defined 100		

RESURGAM CITY OF PORTLAND, MAINE

Reviewed for Code Compliance
Inspections Division
Approved with Conditions

Date: 03/29/16