ELECTRICAL WORK RESPONSIBILITY:

ELECTRICAL CONTRACTOR TO REFER TO THE WORK RESPONSIBILITY SCHEDULE ON SHEET C104 FOR ADDITIONAL ELECTRIC WORK RESPONSIBILITIES.

SPECIAL NOTES:

S1. COORDINATE WORK WITH THE GENERAL CONTRACTOR TO LEAST INTERFERE WITH THE LANDLORD'S USE OF THE FACILITY. GENERAL CONTRACTOR MAY REQUIRE WORK INTERRUPTIONS DURING THE DAY AND MAY REQUIRE CERTAIN WORK TO BE PERFORMED ON PREMIUM TIME AT NIGHT OR ON WEEKENDS.

S2. UNLESS NOTED OTHERWISE MOUNTING HEIGHTS OF ELECTRICAL EQUIPMENT SHALL BE AS FOLLOWS:
SWITCHES: 4'-0" A.F.F. TO CENTER OF BOX
RECEPTACLES: 18" A.F.F. TO CENTER OF BOX
TELEPHONE: 18" TO CENTER OF BOX (DESK TYPE ONLY)

S3. REFER TO ARCHITECTURAL DRAWINGS FOR ALL FIRE RATED AND SMOKE RATED WALLS. SEAL ALL CONDUIT PENETRATIONS THROUGH SUCH WALLS IN ACCORDANCE WITH SPECIFICATIONS.

S4. ELECTRICAL DRAWINGS ARE DIAGRAMMATICAL ONLY. FOR EXACT LOCATION OF ALL LIGHTING FIXTURES, RECEPTACLES, ETC., REFER TO ARCHITECTURAL DRAWINGS AND ELEVATIONS.

S5. REFER TO MECHANICAL DRAWINGS FOR EXACT SIZE, LOCATION, AND ELECTRICAL REQUIREMENTS FOR ALL MOTORS AND MECHANICAL EQUIPMENT. COORDINATE WITH MECHANICAL CONTRACTOR AND PROVIDE ELECTRICAL CONNECTIONS AS REQUIRED FOR A COMPLETE AND OPERABLE SYSTEM.

S6. VISIT AND EXAMINE CAREFULLY THE BUILDING SO AS TO BECOME FAMILIAR WITH EXISTING CONDITIONS AND DIFFICULTIES THAT WILL ATTEND THE EXECUTION OF THE WORK. BEFORE SUBMITTING PROPOSALS. SUBMISSION OF A PROPOSAL WILL BE EVIDENCE THAT SUCH EXAMINATION HAS BEEN MADE AND LATER CLAIMS FOR LABOR, EQUIPMENT OR MATERIALS BECAUSE OF DIFFICULTIES ENCOUNTERED, WILL NOT BE RECOGNIZED.

S7. THE EXISTING CEILING CAVITIES ARE PLENUMS/NON PLENUM.

S8. ALL OUTLETS MOUNTED ABOVE COUNTER SHALL BE INSTALLED HORIZONTALLY AND NOT VERTICALLY. IN AREAS WHERE COUNTERS ARE PROVIDED, COORDINATE EXACT LOCATION OF OUTLETS AND WIRING WITH CASEWORK

S9. CONTRACTOR SHALL COORDINATE WITH ALL "VENDOR" TRADES FURNISHING EQUIPMENT REQUIRING ELECTRICAL CONNECTIONS. CHECK CAREFULLY ALL CONSTRUCTION DRAWINGS AND SPECIFICATIONS THAT ARE PART OF THIS PROJECT TO INSURE COMPLIANCE WITH VENDOR REQUIREMENTS. NO EXTRA CHARGES SHALL BE ACCEPTED BY OWNER, AFTER BIDDING FOR SUCH EQUIPMENT AND LABOR.

S10. EQUIPMENT LABELS AND INSTRUCTIONS REGARDING THE APPLICATION AND INSTALLATION OF THE LISTED EQUIPMENT SHALL BE FOLLOWED TO INSURE THAT THE EQUIPMENT IS BEING INSTALLED IN ACCORDANCE WITH THE MANUFACTURER'S LISTING INSTRUCTIONS. THE TEMPERATURE RATING OF THE EQUIPMENT TERMINATION MUST BE CORRELATED WITH THE CONDUCTOR AMPACITY TO PREVENT OVERHEATING AND PREMATURE FAILURE.

S11. COORDINATE WORK WITH FIELD CONDITIONS AND OTHER TRADES AND INSTALL CONDUIT AND BOXES TO CLEAR EMBEDDED DUCTS, OPENINGS AND OTHER STRUCTURAL FEATURES.

S12. ALL WORK IS TO BE DONE IN ACCORDANCE WITH THE LATEST REQUIREMENTS OF ALL APPLICABLE CODES AND REGULATIONS.

S13. ALL LIGHTING FIXTURES ARE TO BE LOCATED AS REQUIRED ON THE JOB TO CLEAR DUCTS, PIPING, EQUIPMENT, AND/OR MECHANICAL UNITS.

S14. ALL OF THE BOXES, CONDUITS, WIRES, CONTROL STATIONS, SLEEVES, INSERTS, FRAMES AND ANCHORS ARE NOT SHOWN ON THE DRAWINGS. ONLY MAJOR ITEMS ARE SHOWN. COORDINATE ALL WORK AS REQUIRED FOR PROPER DEMOLITION AND INSTALLATION.

S15. NO WIRING SHALL BE DONE PRIOR TO THE CONTRACTOR'S REVIEW OF THE PROJECT EQUIPMENT SHOP DRAWINGS. COORDINATE FIELD CONDITIONS WITH THE DESIGN DOCUMENTS. ANY DISCREPANCIES SHALL BE BROUGHT TO THE ARCHITECT/ENGINEER'S ATTENTION FOR FINAL RESOLUTION. WORK THAT HAS TO BE REPLACED DUE TO LACK OF PROPER SHOP DRAWINGS COORDINATION SHALL BE DONE AT CONTRACTOR'S EXPENSE.

S16. NEW PANELS SHALL NOT BE INSTALLED BELOW WATER PIPES OR VENTILATION DUCTS.

S17. FURNISH AND INSTALL EQUIPMENT DISCONNECT SWITCHES IN STRICT COMPLIANCE WITH CODE REQUIREMENTS. (NOT ALL LOCAL DISCONNECT SWITCHES ARE SHOWN).

S18. ALL OUTLETS BOXES SHALL BE PROVIDED WITH PROPER COVER PLATES.

S19. CIRCUITS ARE SIZED ASSUMING NO MORE THAN THREE CURRENT CARRYING CONDUCTORS IN A SINGLE CONDUIT. FOR CONDUITS CONTAINING MORE THAN THREE, PROVIDE APPROPRIATE DERATING OF CONDUCTORS PER APPLICABLE CODES.

S20. THE ACTIVATION OF A DUCT SMOKE DETECTOR SHALL CAUSE A VISUAL AND AUDIBLE SIGNAL IN A NORMALLY OCCUPIED LOCATION. EACH DUCT DETECTOR SHALL INDICATE A TROUBLE CONDITION VISUALLY OR AUDIBLY AND DEVICE SHALL BE LABELED "DUCT SMOKE DETECTOR TROUBLE". INSTALLATION SHALL COMPLY WITH NFPA 90A–4-4.4.3 WHERE IN-DUCT SMOKE DETECTORS ARE INSTALLED IN CONCEALED LOCATIONS, MORE THAN 10 FEET ABOVE THE FINISHED FLOOR, OR IN ARRANGEMENTS WHERE THE DETECTOR'S ALARM INDICATOR IS NOT READILY VISIBLE TO RESPONDING PERSONNEL, THE DETECTORS SHALL BE PROVIDED WITH REMOTE ALARM INDICATORS. REMOTE ALARM INDICATORS SHALL BE INSTALLED AT READILY ACCESSIBLE LOCATION AND SHALL BE CLEARLY LABELED TO INDICATE BOTH THEIR FUNCTION (E.G. IN-DUCT SMOKE DETECTOR ALARM") AND THE ROOF TOP UNIT ASSOCIATED WITH THE DETECTOR IN ACCORDANCE WITH NFPA 72.5-10.6.8.

SYMBOL LIST

SYMBOL	DESCRIPTION
	SINGLE POLE SWITCH
3W	THREE WAY SWITCH
T	THERMAL OVERLOAD SWITCH - "P" DENOTES PILOT LIGHT
D	DIMMER SWITCH LUTRON # NT-1000.
OS	OCCUPANCY SENSOR CEILING MOUNTED. WATTSTOPPER. SPECIFY ON DRAWINGS
OS	WALL MOUNTED OCCUPANCY SENSOR - WATTSTOPPER PW-100.
F.D.	120V., 15AMP DPST FUSED DISCONNECT SWITCH FOR ELEVATOR SIGNAL SUPPLY. COORDINATE EXACT LOCATION WITH ELEVATOR CONTRACTOR PRIOR TO ANY INSTALLATION.
C.L.	120V., 15AMP SPST FUSED DISCONNECT SWITCH FOR ELEVATOR CAB LIGHTING, COORDINATE EXACT LOCATION WITH ELEVATOR CONTRACTOR PRIOR TO ANY INSTALLATION.
	DUPLEX CONVENIENCE OUTLET (+ 18" ABOVE FINISHED FLOOR)
	SIMPLEX RECEPTACLE
	DOUBLE DUPLEX OUTLET (+ 18" ABOVE FINISHED FLOOR)
	DUPLEX CONVENIENCE OUTLET MOUNTED 6" ABOVE COUNTER TOP
	FLUSH FLOOR MOUNTED OUTLET BOX WITH DUPLEX RECEPTACLE
	FLUSH CEILING MOUNTED DUPLEX RECEPTACLE
	FLUSH CEILING MOUNTED OUTLET BOX WITH DOUBLE DUPLEX RECEPTACLE
	RECEPTACLE - RATING & VOLTAGE AS INDICATED ON DRAWINGS
	DATA OUTLET
	DATA OUTLET - CEILING MOUNTED
P W	TELEPHONE OUTLET (+ 18" ABOVE FINISHED FLOOR) "W" DENOTES WALL MOUNTED (+54" ABOVE FINISHED FLOOR) "P" DENOTES PUBLIC PAY PHONE (+54" ABOVE FINISHED FLOOR)
J, J	JUNCTION BOX - WALL OR CEILING MOUNTED
	NON - FUSED DISCONNECT SWITCH
	FUSED DISCONNECT SWITCH
	MAGNETIC MOTOR STARTER
	COMBINATION MAGNETIC MOTOR STARTER AND DISCONNECT SWITCH - DEVICE AS NOTED
	MOTOR CONNECTION - H.P. AS NOTED ON DRAWINGS
	CONDUIT RUN CONCEALED IN CEILING OR WALLS
	CONDUIT INSTALLED CONCEALED BELOW FLOOR SLAB OR UNDERGROUND.
	CONDUIT RUN EXPOSED
	HOMERUN TO PANEL INDICATING CIRCUIT NUMBERS - ALL WIRING SHALL BE #12 WITH GROUND WIRE UON (INCREASE TO #10 FOR CIRCUITS BETWEEN 100 AND 200 LF) CONSULT ENGINEER FOR RUNS OVER 200 LIN FEET IF WIRE SIZE IS NOT INDICATED - ALL HOMERUNS SHALL BE TO A 20 AMPERE, 1 POLE CIRCUIT BREAKER UON. WIRE FILL AS REQUIRED FOR APPLICATION INDICATED.
	"X" DENOTES GROUND WIRE, LONG SLASH ( ) DENOTES NEUTRAL AND SHORT SLASH ( ) DENOTES HOT CONDUCTOR
	RIGID CONDUIT WITH EXPLOSION PROOF SEAL-OFF.
	CONDUIT INSTALLED WITH ONE INTERCOM CABLE.
	CONDUIT INSTALLED WITH ONE MICROPHONE CABLE.
DC	DIRECT CURRENT WIRING, 2#12 IN 3/4" CONDUIT.
	CONDUIT UP OR DOWN AS MARKED.
	GROUND CONNECTION.
	JUNCTION BOX WITH FINAL EQUIPMENT CONNECTION
	FINAL EQUIPMENT CONNECTION
	CONDUIT STUBBED UP
	CONDUIT STUBBED DOWN

SYMBOL LIST

SYMBOL	DESCRIPTION
	CIRCUIT BREAKER
	SWITCH & FUSE
	PANELBOARD - 208Y/120V-3ph-4W
	PANELBOARD - 480/277V-3ph-4W
	PANELBOARD - 240/120V-1ph-3W
	DISTRIBUTION PANELBOARD - TOP OF PANELBOARD AT 6'-6" A.F.F.
CP	CONTROL PACKAGE - ALL CONTROLLING DEVICES, STARTERS, ASSOCIATED CONTROL STATIONS AND ASSOCIATED CONTROL WIRING SHALL BE FURNISHED, INSTALLED AND WIRED BY EQUIPMENT SUPPLIER. POWER WIRING AND DISCONNECTING DEVICES ONLY SHALL BE UNDER THIS DIVISION OF THE WORK UNLESS NOTED OTHERWISE.
	TELEPHONE TERMINAL CABINET
TR	CONTROL TRANSFORMER REFER TO DETAIL 7/E403
B	WALL MOUNTED BELL REFER TO DETAIL 7/E403
	DOORBELL PUSHBUTTON REFER TO DETAIL 7/E403
	SECURITY CAMERA.
T	THERMOSTAT (FURNISHED BY MECHANICAL CONTRACTOR, INSTALLED AND WIRED BY ELECTRICAL CONTRACTOR). INSTALL AT 5'-0" A.F.F.
TV	TELEVISION OUTLET
AMP	AMPLIFIER
S	SPEAKER
VC	SOUND SYSTEM VOLUME CONTROL.
VR	VIDEO RACK.
KP	SECURITY KEYPAD
C	DOOR CONTACT
E	EMERGENCY PUSH BUTTON CONNECTED TO ALARM SYSTEM
T	OFFICE TELEPHONE JUNCTION BOX
TC	OFFICE DATA/POS SYSTEM JUNCTION BOX
PIR	SECURITY SYSTEM PASSIVE INFRARED SENSOR
RX	AUDIBLE SECURITY ALARM
FACP	FIRE ALARM CONTROL PANEL, TOP OF PANEL AT +6'-0" A.F.F.
F	FIRE ALARM PULL STATION MOUNTED AT 48" AFF UON
F S	FIRE ALARM SPEAKER WITH STROBE LIGHT - WALL MOUNTED AT 80" AFF UON
F S	FIRE ALARM STROBE LIGHT - WALL MOUNTED AT 80" AFF UON
F S	FIRE ALARM STROBE LIGHT - RECESSED CEILING MOUNTED
F P	FIRE ALARM SMOKE DETECTOR - CEILING MOUNTED
F DS	FIRE ALARM DUCT SMOKE DETECTOR - WITH REMOTE TEST STATION - COORDINATE DUCT MOUNTING WITH THE MC
F D	MAGNETIC DOOR HOLD DEVICE
T/S F/S	SPRINKLER SYSTEM TAMPER SWITCH/FLOW SWITCH - FURNISHED AND INSTALLED BY MC, WIRED BY EC
	FIRE ALARM HEAT DETECTOR - CEILING MOUNTED
+3'-10"	HEIGHT ABOVE FLOOR TO CENTER LINE OF OUTLET BOX.
A.	DENOTES AMPERES
A.F.F.	DENOTES ABOVE FINISHED FLOOR
C.	DENOTES CONDUIT
CO	DENOTES CONDUIT ONLY
ETR	DENOTES EXISTING TO REMAIN
GFI	DENOTES GROUND FAULT INTERRUPTER
GRD.	DENOTES GROUND
IG	ISOLATED GROUND
NF	DENOTES NON FUSED
N.I.C.	DENOTES NOT IN CONTRACT
NL	DENOTES NIGHT LIGHT
UNO	DENOTES UNLESS NOTED OTHERWISE
UOI	UBRAN OUTFITTERS INCORPORATED
WP	DENOTES WEATHERPROOF

GENERAL LIGHTING FIXTURE SCHEDULE NOTES:

1. INSTALLATION OF FIXTURES SHALL BE ACCORDING TO MANUFACTURER'S RECOMMENDATIONS AND ACCORDING TO CODE REQUIREMENTS.
2. ALL LIGHTING FIXTURES SHALL BE SUPPLIED BY URBAN OUTFITTERS UNLESS NOTED OTHERWISE.
3. ELECTRICAL CONTRACTOR SHALL PROVIDE U-CHANNEL (UNI-STRUT OR EQUAL) TO SPAN STRUCTURAL MEMBERS AND PROVIDE SUPPORT FOR LIGHTING FIXTURES.
4. ALL FIXTURES SHALL BE RECEIVED, UNLOADED, INVENTORIED, HANDLED, STORED, PROTECTED, UNCRATED, ASSEMBLED, INSTALLED, WIRED, LAMPED ETC. BY THE ELECTRICAL CONTRACTOR (EC). EC SHALL CONFIRM CONDITION, QUANTITY, AND SPECIFICATION OF FIXTURES UPON RECEIPT. EC SHALL IMMEDIATELY REPORT ANY DAMAGE, MISSING ITEMS OR DEVIATIONS FROM SPEC.
5. EXIT AND EMERGENCY LIGHTING FIXTURES TYPES AND LOCATIONS ARE SUBJECT TO BUILDING DEPARTMENT AND FIRE DEPARTMENT APPROVAL.
6. ALL LIGHTING FIXTURES, WIRING METHODS, ETC. WITHIN A PLENUM CEILING MUST BE "PLENUM APPROVED" AS PER LOCAL ORDINANCES.
7. REFER TO ARCHITECTURAL REFLECTED CEILING PLAN FOR EXACT LOCATION OF LIGHT FIXTURES.
8. INSTALLATION OF LIGHTING FIXTURES SHALL BE CAREFULLY COORDINATED WITH ARCHITECTURAL, STRUCTURAL, MECHANICAL AND SPRINKLER DRAWINGS TO AVOID CONFLICTS . IF CONFLICTS SHOULD ARISE, EC SHALL CLARIFY WITH ARCHITECT PRIOR TO PROCEEDING WITH INSTALLATION.
9. LIGHTING FIXTURE QUANTITIES ARE SHOWN FOR A GUIDE ONLY AND TO CONFIRM ENERGY CODE COMPLIANCE. ELECTRICAL CONTRACTOR SHALL CONFIRM ALL LIGHTING FIXTURE QUANTITIES WITH PLAN DRAWINGS PRIOR TO SUBMISSION OF BID. ALL DISCREPENCIES SHALL BE BROUGHT TO THE ATTENTION OF THE ENGINEER AT LEAST ONE WEEK PRIOR TO SUBMISSION OF BID. CONTRACTOR SHALL BE RESPONSIBLE TO PROVIDE THE QUANTITIES OF FIXTURES NECESSARY TO COMPLETE THE PROJECT AS INDICATED ON THE ARCHITECTURAL AND ELECTRICAL DRAWINGS.
10. MOUNT EMERGENCY LIGHTS AS HIGH AS POSSIBLE AND ALLOWED BY AHJ.

LIGHT FIXTURE SCHEDULE

Lighting Fixture Information										Lamp Information					Site Conditions	
Qty.	Type	Image	Manufacturer	Description	Fixture Watts	Catalogue #	Beam Spread	Mounting	Flange & Aperture Finish	Lamp Image	Lamp Manu.	Lamp Watts	Lamp Catalogue # & Code	Base & Lamp Life	Location	Notes
4	A3F		Intense	4.5" dia. 39W T4 Metal Halide Adjustable Accent, Flood	44	Housing: IHMA4-T4-039-E-FL, wired for 120V Trim: IC40040-SD-SFW	45°	Recessed	White, semi diffuse		Philips	39	CDM-TC T4 Elite 35W/930 1CT 92818 91 05117	G8.5 15,000	Sales Perimeter	Optional mounting accessories available, Contractor to inform buyer
17	B4W-1		Lightolier	6.5" dia. 70W T6 Metal Halide Cylinder Downlight, Wide Flood	79	Fixture: C6CS70T6EU, wired for 120V Trim: C6T6VW-CCD Canopy: C4CSW	Wide Beam	Pendant, Canopy (Swivel Kit)	White, comfort clear diffuse		Philips	70	CDM-T ELITE 70W/930 T6 1CT 92818 53 05117	G12 15,000	Special Ceiling Areas, Sales	Electrician to supply stem on site of rigid conduit 5/8" dia. Length per
27	C21		Bartco	1 lamp Linear 21W T5 Fluorescent Strip (to match N21)	23	BFL281-21/UNV/RS, wired for 120V	-	Surface Mount	White		Philips	28	F21T5/830/ ALTO 23081-3	Mini Bi-Pin 35,000	Coves	
11	D3W		Intense	4.5" dia. 39W T4 Metal Halide Downlight, Wide Flood	44	Housing: IHM420-T4-039-E-WF, wired for 120V, fixed optics Trim: IC449-HZ-SFW	55°	Recessed	White, semi diffuse		Philips	39	CDM-TC T4 Elite 35W/930 1CT 92818 91 05117	G8.5 15,000	Sales	
6	D4W		Intense	4.5" dia. 70W T6 Metal Halide Downlight, Wide Flood	79	Housing: IHM420-T4-070-E-WF, wired for 120V, fixed optics Trim: IC449-HZ-SFW	55°	Recessed	White, semi diffuse		Philips	70	CDM-T ELITE 70W/930 T6 1CT 92818 53 05117	G12 15,000	Sales	
18	D6F		Contech Lighting	5" dia. 50W Halogen MR16 Downlight, Flood with cosmetic-peach di-chroic	50	Fixture: LYK316-CTR302-P-CLR, wired for 120V	36°	Recessed	White, clear		Ushio	50	EXN/FG/ ULTRA TITAN 109-3553	GU5.3 14,000	Fitting Rooms	
3	D42		Lightolier	7.2" dia. 1 lamp 42W Compact Fluorescent **Lensed** Downlight, 120V	46	Trim: 8097DWHW Housing: 57142BU, wired for 120V	-	Recessed	White, white		Philips	42	PL-T 42W/830/ 4P/ALTO 26873-0	GX 24q-4 16,000	BOH areas	
2	EHC		Evenlite Inc.	Aperion Retracted Recessed Emergency Light with 2 adjustable MR16 halogen lamps, 90 minute backup, 15 minute time delay for use in HID areas, 120V, Ceiling Recessed	50	APR-25-NC-UI-TD, wired for 120V	EM	Ceiling Recessed	White, white		-	25	MR16 Lamps supplied with fixture	-	Sales areas	Field paintable to match wall finish
10	EMC		Lightalarms	Thermoplastic Emergency Lighting unit with adjustable halogen heads, 120V, Ceiling/Pendant Mount	11	LCA-25Q, wired for 120V	EM	Ceiling / Pendant Mount	White	-	-	5.4	Halogen DC T5 Wedge base supplied with fixture	-	BOH areas	
3	EMW		Lightalarms	Thermoplastic Emergency Lighting unit with adjustable halogen heads, 120V, Wall Mount	11	LCA-25Q, wired for 120V	EM	Wall Surface Mount	White	-	-	5.4	Halogen DC T5 Wedge base supplied with fixture	-	BOH areas	
3	EXW		Lightalarms	Thermoplastic Exit sign, self powedered, 120V, Wall Mount, **White** finish	-	QLXN500-G-S, wired for 120V	EXIT	Wall Surface Mount	White	-	-	-	LED supplied with fixture	-	BOH areas	Replaceable knockout directional chevron's
3	EZC		Contech Lighting	Adjustable Recessed or Surface Mount LED Edge-Lit Exit Sign with Battery Back-Up, Green Letters,	3	Double Face: REXA-DF-G-EM-C-P, wired for 120V Single Face: REXA-SF-	EXIT	Ceiling Recessed	White, clear acrylic faceplate	-	-	-	LED supplied with fixture	-	Sales areas	Removable directional indicators
2	EZW		Contech Lighting	Adjustable Recessed or Surface Mount LED Edge-Lit Exit Sign with Battery Back-Up, Green Letters, 120V, Wall Mount, **White** finish	3	Double Face: REXA-DF-G-EM-C-P, wired for 120V Single Face: REXA-SF-G-EM-P, wired for 120V	EXIT	Wall Surface Mount	White, clear acrylic faceplate	-	-	-	LED supplied with fixture	-	Sales areas	Removable directional indicators
27	F32		Mercury Lighting	2 Lamp 4' T8 linear fluorescent Wrap around with Acrylic lens, 120V	65	M105-2-32-OCT-A-ELB-UNI, wired for 120V	-	Chain or Surface Mount, per plans	White, acrylic lens		Philips	32	F32T8/TL830/ PLUS/ALTO 36000-8	Med. Bi-Pin 36,000	BOH	
93	H4W		Janmar	Track Head, 70W T6 Metal Halide, Wide Flood	79	738E-70CMH-T6G12-CPAR30-II-WFL-WHT	36°	Track Mounted	White		Philips	70	CDM-T ELITE 70W/930 T6 1CT 92818 53 05117	G12 15,000	Sales with high ceiling	
84'	L2		WAC Lighting	LED flexible strip 2700°K, with connectors and power supply to fit behind mirror as a halo light, applied by peel and stick 3M adhesive, each length to be 7.5' longh on each side of the mirror, this spec lists all components for one mirror	23	**LED Fixture:** (2) LED-T24W/-5-WT **(5' long)** (6) LED-T24W-1-WT **(1' long)** **Power Supply:** (1) EN-2460-P-AR-T **Joiner Connectors:** (1) LED-TC-Y **(3-way " Y")** (2) LED-TC-IC12 **(12" long)** (2) LED-TC-IC6 **(6" long)**	apx. 160°	Surface Mount	-		WAC Light-ing	0.25	2700°K LED's	50,000	Internally Lit Mirror, Fitting Rooms	Fixture has plug in power supply, field cuttable every 2", Reference cutsheets for layout and installation
1	S25		Mercury Lighting	3' T8 Fluorescent Lensed Closet Light, 120V	27	MP1-1-25-OCT-A-WHT-ELB-UNI, wired for 120V	-	Wall Surface Mount	White, white		Philips	25	F25T8/TL830/ PLUS/ALTO 14556-5	Med. Bi-Pin 36,000	Closets	control by door jamb switch when applicable
310'	TS		Intense	Single Circuit Track and all necessary parts, White	-		-	Suspended	White	-	-	-	-	-	-	All Tread Rod for suspension, by Contractor, For Track TT-6 or TS-6 on the plan, 8'-0" length track to be field cut.
5	X1											60W with porcelain socket				

NewStudio Architecture
4431 Lake Avenue South
White Bear Lake, MN 55110
p: 651.207.5527 f : 651.207.8247

ANTHROPOLOGIE
60 Pearl Street
Portland, ME 04101

HALLBERG ENGINEERING
Mechanical/Electrical Consulting Engineers
1750 Commerce Court, White Bear Lake, MN 55110
(651) 748-1100 - Fax (651) 748-8370

Date: 09/22/14

DRAWN BY: DJQ CHECKED BY: KLS/PJF
NSA PROJECT NUMBER: 2013-99
PROJECT PHASE: CD
HEI PROJECT NUMBER: R14-1941.000

ISSUE / DATE:

100% CHECKSET	07-11-2014
BID/PERMIT	08-01-2014
REVISION 1 - CITY COMMENTS	09-19-2014

REVISION :

SHEET TITLE :
ELECTRICAL SYMBOL LEGEND AND SPECIAL NOTES

SHEET NO :
E400