

RESPONSIBILITY MATRIX LEGEND				
STOREFRONT EXTRUSION	O	GC	FACTORY FINISHED	COMMENTS
ITEM				
FURNISHED BY				
INSTALLED BY				
L = LANDLORD O = OWNER (GAP INC.) GC = GENERAL CONTRACTOR E = EXISTING				
RESPONSIBILITY MATRIX				
ITEM	FURNISHED BY	INSTALLED BY	COMMENTS	
MAIN OVERCURRENT DEVICE AT (IF NOT LANDLORD'S SERVICE POINT)	GC	GC		
METER AT LANDLORD'S SERVICE POINT	GC	GC		
C/T'S AT LANDLORD'S SERVICE POINT	GC	GC		
C/T CABINET AT LANDLORD'S SERVICE POINT	GC	GC		
DOOR BUZZER SYSTEM	GC	GC	14	
SERVICE ENTRANCE CONDUIT(S) LANDLORD'S TO LEASE SPACE WITH PULL WIRE	GC	GC		
208/120 VOLT PANEL(S)	GC	GC		
ELECTRICAL GEAR & LIGHTING CONTROLS (IF NOT FURNISHED BY LOEB ELECTRIC)	GC	GC	14	
LIGHTING FIXTURES AND LAMPS	O	GC	2,6	
MUSIC SYSTEM/SPEAKERS/CABINET	O	O	1,2,8,10	
MUSIC SYSTEM WIRING	O	O	1,2,3,8,10	
SECURITY CAMERA	O	O	-	
BURGLAR ALARM	O	GC	5	
REMARKS:				
1. ALL FINAL EQUIPMENT WIRING AND EQUIPMENT INSTALLATION BY OTHERS. 2. GENERAL CONTRACTOR TO COORDINATE SCHEDULE AND DELIVERY WITH SUPPLIER. STANDARD SHIPPING PROVIDED BY GAP INC. ANY EXPEDITED SHIPPING COSTS ARE RESPONSIBILITY OF THE GENERAL CONTRACTOR. 3. ROUGH-IN BY G.C. 4. G.C. TO COORDINATE SCHEDULE AND DELIVERY WITH SUPPLIER. STANDARD SHIPPING PROVIDED BY ATHLETA. ANY EXPEDITED SHIPPING COSTS ARE RESPONSIBILITY OF THE GENERAL CONTRACTOR. 5. ITEM DELIVERY SCHEDULED BY OWNER FOR LAST WEEK OF CONSTRUCTION. 6. G.C. TO SCRIBE TO FIT. 7. ALL FINAL EQUIPMENT WIRING AND EQUIPMENT INSTALLATION BY OTHERS. 8. NOT USED. 9. NOT USED. 10. ROUGH-IN BY G.C. 11. SEE PROJECT MANUAL & INSTALLATION GUIDE FOR DETAILED SUBMITTAL REQUIREMENTS. 12. NOT USED. 13. NOT USED. 14. FOR LOEB ELECTRIC NATIONAL ACCOUNTS PRICING, SEE CONTACT INFO BELOW. 15. NOT USED. 16. FOR LOEB ELECTRIC NATIONAL ACCOUNTS PRICING, SEE CONTACT INFO BELOW.				
NOTE:				
THE RESPONSIBILITY MATRIX ONLY DELINEATES ITEMS SUPPLIED AND/OR INSTALLED BY OWNER AND/OR LANDLORD. ANY WORK BY CONSTRUCTION DOCUMENTS NOT DEFINED AS RESPONSIBILITY OF OWNER OR LANDLORD IS SUPPLIED AND INSTALLED BY GENERAL CONTRACTOR. SEE BID CLARIFICATION LETTER FOR ANY VARIATION BY SCOPE OF WORK RESPONSIBILITY.				
GENERAL CONTRACTOR IS RESPONSIBLE FOR THE UNLOADING OF ANY OWNER SUPPLIED CONSTRUCTION ITEMS.				
LOEB ELECTRIC CONTACT INFORMATION				
JOHN CALLICOAT 1800 E. 5TH AVENUE COLUMBUS, OHIO 43219 PHONE: 614-421-5058 FAX: 614-299-6268 EMAIL: TheGap@loebelectric.com				

ELECTRICAL SYMBOLS

- ▼ TELEPHONE OUTLET
- ▼ TELEPHONE OUTLET, FLOOR MOUNTED
- ▼ TELEPHONE OUTLET, CEILING MOUNTED
- ▼ DATA OUTLET
- ▼ DATA OUTLET, FLOOR MOUNTED
- ▼ DATA OUTLET, CEILING MOUNTED
- ▼ PHONE/DATA OUTLET, FLOOR MOUNTED
- ▼ PHONE/DATA OUTLET, CEILING MOUNTED
- ▼ PHONE/DATA OUTLET
- ▼ DUPLEX RECEPTACLE
- Ⓜ CEILING MOUNTED RECEPTACLE
- Ⓜ PS DUPLEX RECEPTACLE, FLOOR MOUNTED
- Ⓜ PS POWERSTRUT MOUNTED RECEPTACLE
- Ⓜ CEILING MOUNTED QUADRUPLEX RECEPTACLE
- Ⓜ QUADRUPLEX RECEPTACLE
- Ⓜ GFI DUPLEX RCPT WITH GND FAULT CIRCUIT INTERRUPTER
- Ⓜ W DUPLEX, WHITE RECEPTACLE AND COVERPLATE
- Ⓜ WS DUPLEX, WHITE RCPT AND STAINLESS STEEL COVERPLATE
- Ⓜ SF DUPLEX RECEPTACLE, STOREFRONT
- Ⓜ SINGLE RECEPTACLE
- Ⓜ QUADRUPLEX RECEPTACLE WITH ISOLATED GROUND
- Ⓜ DUPLEX RECEPTACLE WITH ISOLATED GROUND
- Ⓜ JUNCTION BOX
- Ⓜ SWITCH, 1-POLE, REFER TO ARCH FOR MOUNTING HEIGHT
- Ⓜ SWITCH, 3-WAY, REFER TO ARCH FOR MOUNTING HEIGHT
- Ⓜ MOTOR RATED SWITCH WITH THERMAL OVERLOAD PROTECTION
- Ⓜ DIMMER SWITCH
- Ⓜ MS MOTION SENSOR
- Ⓜ BB BYPASS BUTTON
- Ⓜ RB REMOTE BALLAST
- Ⓜ RELAY
- Ⓜ NON-FUSED DISCONNECT SWITCH
- Ⓜ FUSED DISCONNECT SWITCH
- Ⓜ MAGNETIC STARTER
- Ⓜ ELEC PANELBOARD (SHOWN TO SCALE ON PLANS)
- Ⓜ DRY TYPE TRANSFORMER
- Ⓜ PUSH BUTTON FOR BELL OR BUZZER
- Ⓜ DOOR BUZZER
- Ⓜ BUZZER OR BELL
- Ⓜ ADA PUSHBUTTON
- Ⓜ INTERCOM CALL BUTTON
- Ⓜ ADT CONTROL PANEL
- Ⓜ SPEAKER VOLUME CONTROL
- Ⓜ SPEAKER
- Ⓜ BASS MODULE MOUNTED ABOVE CEILING
- Ⓜ ACCESS PANEL. SEE ARCHITECTURAL DRAWINGS.
- Ⓜ HOMERUN CIRCUIT
- Ⓜ POWERSTRUT SUSPENDED FROM STRUCTURE
- Ⓜ UNISTRUT
- Ⓜ FACP FIRE ALARM CONTROL PANEL
- Ⓜ ANNUN FACP REMOTE ANNUNCIATOR
- Ⓜ PHOTO CELL
- Ⓜ MANUAL PULL STATION
- Ⓜ CEILING MOUNTED SMOKE DETECTOR
- Ⓜ DUCT MOUNTED SMOKE DETECTOR
- Ⓜ 120V POWER FROM RTU REC/LT CCT IF REQUIRED
- Ⓜ INTERNAL CONTACTOR
- Ⓜ CONTROL RELAY
- Ⓜ TAMPER SWITCH
- Ⓜ WATER FLOW SWITCH
- Ⓜ HORN WITH STROBE LIGHT WALL MOUNTED @ 80" AFF
- Ⓜ STROBE WALL MOUNTED @ 80" AFF
- Ⓜ HORN WALL MOUNTED @ 80" A.F.F.
- Ⓜ STROBE LIGHT CEILING MOUNTED.
- Ⓜ HORN WITH STROBE LIGHT CEILING MOUNTED
- Ⓜ HVAC TEMPERATURE SENSOR
- Ⓜ HVAC THERMOSTAT
- Ⓜ ELECTRICALLY POWERED EQUIPMENT
- Ⓜ AFF ABOVE FINISH FLOOR
- Ⓜ EAS ELECTRONIC ARTICLE SURVEILLANCE
- Ⓜ EBBH ELECTRIC BASEBOARD HEATER
- Ⓜ EC ELECTRICAL CONTRACTOR
- Ⓜ EM EMERGENCY
- Ⓜ EWC ELECTRIC WATER COOLER - COORDINATE RECEPTACLE LOCATION WITH PLUMBING CONTRACTOR
- Ⓜ IG ISOLATED GROUND
- Ⓜ NL NIGHT LIGHTING
- Ⓜ WP WEATHER PROOF
- Ⓜ (X) X = QUANTITY OF CONDUCTORS
- NOTE: NOT ALL SYMBOLS NECESSARILY USED ON PLAN.

ELECTRICAL GENERAL NOTES

1. THE ABBREVIATION G.C., WHEREVER IT APPEARS IN THESE ELECTRICAL DRAWING, SHALL REFER TO "GENERAL CONTRACTOR".
2. THE CONTRACTOR FOR THIS WORK IS REQUIRED TO READ THE SPECIFICATIONS AND REVIEW DRAWINGS OF ALL DIVISIONS OF WORK AND IS RESPONSIBLE FOR THE COORDINATION OF THIS WORK AND THE WORK OF ALL SUBCONTRACTORS WITH ALL DIVISIONS OF WORK. IT IS THE CONTRACTOR'S RESPONSIBILITY TO PROVIDE ALL SUBCONTRACTORS WITH A COMPLETE SET OF BID DOCUMENTS.
3. LIGHTING, RECEPTACLES AND EQUIPMENT SHALL BE CONNECTED TO EXACT PANEL AND BREAKER AS SHOWN ON PLANS.
4. ELECTRICAL HOME RUNS SHOWN ARE SCHEMATIC AND MAY ORIGINATE FROM DIFFERENT LOCATIONS UNLESS OTHERWISE NOTED. MULTIPLE CONNECTIONS TO A SINGLE LIGHT FIXTURE FOR VOLTAGE DROP CONDITIONS OR AS A RESULT OF A FIELD CONDITION ARE ACCEPTABLE. ANY RELATED COSTS FOR MULTIPLE CONNECTIONS SHALL BE INCLUDED IN BID.
5. SEE ARCHITECTURAL REFLECTED CEILING PLAN FOR EXACT LOCATION AND QUANTITY OF LIGHTING FIXTURES AND SIGNAGE ELEMENT LOCATIONS.
6. ALL LIGHTING AND RECEPTACLE CIRCUITS UP TO 60'-0" IN LENGTH SHALL UTILIZE #12 CONDUCTORS MINIMUM, CIRCUITS FROM 61'-0" THRU 100'-0" IN LENGTH SHALL UTILIZE #10 CONDUCTORS MINIMUM AND FROM 101'-0" THRU 150'-0" IN LENGTH SHALL UTILIZE #8 CONDUCTORS MINIMUM, UNLESS OTHERWISE NOTED.
7. IN DRYWALL CEILING AREAS, ARRANGE CIRCUITS TO AVOID THE USE OF JUNCTION BOXES IN INACCESSIBLE LOCATIONS. THE USE OF JUNCTION BOXES ABOVE DRYWALL CEILINGS SHALL BE LIMITED TO LOCATIONS NEAR ACCESS PANELS AS LOCATED ON PLANS. FIELD COORDINATE WITH G.C. PRIOR TO ROUGH-IN TO AVOID ANY CONFLICTS.
8. FIELD VERIFY EXACT LOCATION AND ELECTRICAL REQUIREMENTS OF ALL HVAC EQUIPMENT THROUGH G.C. PRIOR TO ORDERING RELATED ELECTRICAL EQUIPMENT.
9. PLACEMENT OF ALL RECEPTACLES IN THE "SALES" AREA SHALL BE INTENTIONAL (I.E. - CENTERED ON COLUMNS, WALL FEATURES OR TIGHT TO CORNERS AND FLUSH MOUNTED AT GYP BOARD WALL ONLY). FIELD VERIFY EXACT PLACEMENT OF RECEPTACLE WITH G.C. PRIOR TO ROUGH-IN.
10. CONTRACTOR TO VERIFY THAT ALL ITEMS ON CONTRACTOR CHECKLIST ARE COMPLETED PRIOR TO MEP COMMISSIONING. CONTRACTOR WILL RECEIVE CONTRACTOR CHECKLIST IN ELECTRONIC FORM WITH BID DOCUMENTS.

DRAWING SCHEDULE	
NUMBER	TITLE
E0-1	ELECTRICAL NOTES AND LEGENDS
E1-0	POWER PLAN
E1-0A	POWER PLAN - HVAC
E1-1	LIGHTING PLAN
E4-0	LIGHT FIXTURE SCHEDULE
E5-0	EAS DETAIL
E6-0	CASHWRAP DETAILS
E9-0	POWER RISERS AND SCHEDULES
E9-1	PANEL SCHEDULES
E9-4	LIGHT FIXTURE DETAILS
E9-5	ELECTRICAL DETAILS

NEW STORE



GAP INC.
CORPORATE ARCHITECTURE
1 HARRISON STREET
SAN FRANCISCO, CA 94105


STORE NO.: 7641

STORE NAME:
PORTLAND

STORE LOCATION:
152 MIDDLE STREET
PORTLAND, ME 04101

PROJ. I.D.: 0000053405

PROTOTYPE DATE: 09/4/15
PROTOTYPE VERSION 4.1



DICKERSON ENGINEERING, INC.
Professional Electrical Engineers
8101 NORTH MILWAUKEE AVENUE
NILES, ILLINOIS 60714
TEL (847) 966-0290

PROFESSIONAL STAMP:

ARCHITECT INFO:
ChipmanDesign
Architecture Group P.C.
2105 S. River Road, Suite 400
Des Plaines, Illinois 60018
7847-288-6900 F 847-288-6944

ISSUE TYPE:
100% CD CHECKSET 5/20/16
PERMIT / BID
LL APPROVAL

DRAWN BY: PR
A&E JOB NO.: 16-5433

SHEET TITLE:
ELECTRICAL NOTES
AND LEGENDS

SHEET NUMBER:

E0-1