Reviewed for Code Compliance
Inspections Division
Approved with Conditions
Date: 11/04/13

PROJECT NOTES:

1. INTERLOCK SHUNT TRIP CIRCUIT BREAKERS SERVING CIRCUITS TO ITEMS BELOW RANGE EXHAUST HOOD WITH HOOD FIRE SUPPRESSION SYSTEM TO DEACTIVATE CIRCUITS UPON DISCHARGE OF HOOD SUPPRESSION SYSTEM.
2. ALL RECEPTACLES IN KITCHEN SHALL BE GFI RATED PER THE NATIONAL ELECTRICAL CODE.
3. INSTALL SEAL–OFF FITTINGS ON CONDUIT PENETRATING THE WALK–IN COOLER.
4. PROVIDE CONTROL WIRING BETWEEN THE COOLER EVAPORATOR AND COOLER CONDENSER. COORDINATE WITH EQUIPMENT SUPPLIER.
5. MOUNT, WIRE, AND INTER–CONNECT VAPOR–PROOF LIGHTS IN WALK–IN COOLER AND FREEZER. LIGHTS PROVIDED BY THE EQUIPMENT SUPPLIER. CIRCUIT LIGHTS TO KITCHEN LIGHTING CIRCUIT.
6. ELECTRICAL CONTRACTOR TO PROVIDE LIGHTING SWITCH FOR KITCHEN HOOD LIGHTS. LOCATE LIGHTING SWITCH ADJACENT TO HOOD EXHAUST SWITCH. VERIFY EXACT LOCATION WITH MECHANICAL CONTRACTOR.
7. PROVIDE INSTALLATION AND WIRING OF KITCHEN HOOD COMPONENTS FURNISHED BY THE HOOD SUPPLIER, INCLUDING I/O PROCESSOR, KEYPAD, TEMPERATURE SENSOR, OPTIC SENSOR, VARIABLE FREQUENCY DRIVE, AND HOOD LIGHTS.
8. CONNECT KITCHEN HOOD SUPPRESSION SYSTEM WITH FIRE ALARM SYSTEM TO INDICATE AN ALARM CONDITION UPON SUPPRESSION DISCHARGE. CIRCUIT FIRE SUPPRESSION SYSTEM TO KP #16.
9. NOT USED.
10. EXTEND INCOMING SERVICE FROM UTILI COMPANY SERVICE METER WITH MAIN CIRCUIT BREAKER UNDER THE FLOOR SLAB. RISE TO PANEL KP LOCATED IN MECHANICAL MEZZANINE IN A 2–1/2" CDT.
11. VERIFY ALL ELECTRICAL CONNECTIONS AND CIRCUIT REQUIREMENTS WITH KITCHEN EQUIPMENT SUPPLIER PRIOR TO ROUGH–IN.
12. EXTEND EXISTING BUILDING FIRE ALARM SYSTEM AS REQUIRED TO ACCOMMODATE DEVICES SHOWN, NEW DEVICES SHALL MATCH EXISTING MANUFACTURER AND TYPE. PROVIDE A FIRE ALARM SYSTEM BOOSTER FOR NEW INDICATING DEVICES. CIRCUIT TO PANEL KP #18.

HERE POSSIBLE. WHERE NECESSARY, PROVIDE CEWAY PAINTED TO E TO WHICH IT IS SURFACE RACEWAY IN STRAIGHT LINES PARALLEL TO WALLS/BEAMS.

14. CONNECT EF–1 AND EF–2 (120V, 1PH, 50W) TO ROOM LIGHTING CIRCUIT. FAN TO HAVE INTEGRAL MOTION SENSOR.
15. UNLESS SPECIFICALLY NOTED OTHERWISE, 3–PHASE LOADS SHALL BE CIRCUITED WITH 3 #12, 1 #12 GND, IN A 3/4" CDT.

PANEL KP (MECHANICAL MEZZANINE):

120/208 VOLT, 3 PHASE, 4 WIRE, 225A, MLO, 72 CIRCUIT BREAKERS

PROVIDE THE FOLLOWING CIRCUIT BREAKERS:

(1) 60A/3P SHUNT TRIP – DISHWASHER
(4) 20A/1P SHUNT TRIP – GAS EQUIPMENT UNDER RANGE HOOD
(1) 45A/3P – CONDENSING UNIT CC–1
(4) 20A/3P – COOLER COMPRESSOR SF–1, MAU–1, AH–1
(3) 20A/1P – GAS FURNACE, GAS WATER HEATER, MOTOR OPERATED DAMPERS
(2) 20A/1P – COOLER, COOLER EVAPORATOR
(4) 20A/1P – KITCHEN EQUIPMENT, KITCHEN RECEPTACLES
(2) 20A/1P – FIRE SUPPRESSION SYSTEM, F/A BOOSTER
(2) 20A/1P – BAR EQUIPMENT
(5) 20A/1P – RECEPTACLES
(4) 20A/1P – LIGHTING
(22) 20A/1P – SPARES

POWER PLAN
1/4" = 1'–0"

WSA winton scott architects
5 Milk Street
Portland, Maine 04101
207 774 4811
www.wintonscott.com

STATE OF MAINE LAWRENCE E. BARTLETT No. 7928 LICENSED PROFESSIONAL ENGINEER

KING'S HEAD
Tenant Fit Up

Merrill's Wharf
Portland, Maine

REVISIONS

PERMIT DOCULMETS
June 07, 2013

Power Plan

Scale: As Noted

E 101