

ROOM 6 FLUORO BASEMENT POWER

PLAN

1/2" = 1'-0"

ITEM #	DEVICE REQUIREMENTS FOR FLUORO ROOMS 6 THE ELECTRICAL CONTRACTOR IS TO PROVIDE (UNLESS NOTED OTHERWISE)
CB1	480V, 3 PHASE, 100A CIRCUIT BREAKER WITH SHUNT TRIP IN A NEMA 1 ENCLOSURE.
CB2	480V, 3 PHASE, 30A CIRCUIT BREAKER WITH SHUNT TRIP IN A NEMA 1 ENCLOSURE.
ST	SHUNT TRIP/EMERGENCY OFF BUTTON. LARGE, RED, MUSHROOM HEAD BUTTON WITH CONTACTS TO OPERATE SHUNT TRIP FEATURE OF CB1 AND CB2 SIMULTANEOUSLY.
MB	INSTALL A 19 1/4"W x 67"H x 4"D FLANGED TERMINAL WALL BOX WITH REMOVABLE SCREW-TYPE COVER PLATE FURNISHED BY PHILIPS. SURFACE MOUNT 75"AFF TO TOP OF BOX. CUT TOP AND/OR BOTTOM OF BOX AS REQUIRED TO CONNECT TO "WR1".
ME	INSTALL A 19 1/4"W x 67"H x 4"D FLANGED TERMINAL WALL BOX WITH REMOVABLE SCREW-TYPE COVER PLATE FURNISHED BY PHILIPS. SURFACE MOUNT 75"AFF TO TOP OF BOX. CUT TOP AND/OR BOTTOM OF BOX AS REQUIRED TO CONNECT TO "WR1".
MR	INSTALL A 19 1/4"W x 67"H x 4"D FLANGED TERMINAL WALL BOX WITH REMOVABLE SCREW-TYPE COVER PLATE FURNISHED BY PHILIPS. SURFACE MOUNT 75"AFF TO TOP OF BOX. CUT TOP AND/OR BOTTOM OF BOX AS REQUIRED TO CONNECT TO "WR1".
MU	8"W x 8"L x 6"D CEILING BOX, FLUSH MOUNTED WITH REMOVABLE SCREW-TYPE COVER PLATE.
MS	GROMMET OPENING ON TOP OF "FR1". EXACT SIZE TO BE DETERMINED BY PHILIPS.
FR1	EXISTING FLOOR TRENCH. EXISTING RACEWAY TO BE MODIFIED TO ACCOMMODATE FLUSH MOUNTING OF ED ELEVA FLOORPLATE.
TV	8"W x 8"L x 4"D CEILING BOX, FLUSH MOUNTED WITH REMOVABLE SCREW-TYPE COVER PLATE.
IR I	6"W x 6"L x 4"D CEILING BOX, FLUSH MOUNTED WITH REMOVABLE SCREW-TYPE COVER PLATE. MOUNT IR BOX TO BOX COVER. LOCATION SHOWN IS RECOMMEND LOCATION AND MAY BE REVISED. VERIFY EXACT LOCATION WITH PHILIPS.
IB	4"W x 4"L x 4"D WALL BOX WITH REMOVABLE SCREW-TYPE COVER PLATE. FLUSH MOUNT 84" AFF TO BOTTOM OF BOX. LOCATION SHOWN IS RECOMMEND LOCATION AND MAY BE REVISED. VERIFY EXACT LOCATION WITH PHILIPS.
R1	EXISTING SURFACE MOUNTED RISER DUCT WITH REMOVABLE SCREW-TYPE COVER PLATE FROM FINISHED FLOOR TO "WR1".
QR QR	GROMMETTED CABLE OPENING ON "WR2". LOCATION SHOWN IS RECOMMEND LOCATION AND MAY BE REVISED. VERIFY EXACT LOCATION WITH PHILIPS.
EEC	GROMMETTED CABLE OPENING ON "WR2". LOCATION SHOWN IS RECOMMEND LOCATION AND MAY BE REVISED. VERIFY EXACT LOCATION WITH PHILIPS.
VF	GROMMETTED CABLE OPENING ON "WR2". LOCATION SHOWN IS RECOMMEND LOCATION AND MAY BE REVISED. VERIFY EXACT LOCATION WITH PHILIPS.
WR1	EXISTING WALL RACEWAY WITH REMOVAVBLE SCREW-TYPE COVERPLATE. SURFACE MOUNTED 30"+/- AFF.
WR2	10"W x 4"D WALL RACEWAY WITH 3 COMPARTMENTS AND REMOVAVBLE SCREW-TYPE COVERPLATE. SURFACE MOUNT BELOW COUNTER FOR ENTIRE LENGTH. CONNECT TO WR4 LOCATED IN THE EXAM ROOM. MOUNT AT SAME HEIGHT AS WR1.
WR4	10"Wx4"D WALL RACEWAY WITH 3 COMPARTMENTS AND REMOVABLE SCREW - TYPE COVERPLATE. CONNECT TO WR1 IN THE EXAM ROOM AND WR2 IN THE CONTROL ROOM.
WL	WARNING LIGHT. PROVIDE SURFACE MOUNTED X-RAY ON FIXTURE ABOVE DOOR X-RAY ON LIGHT SHALL BE SURE-LITES LPX6-G8 OR EQUAL.

		CABLE AND C	ONDUIT REQUIREMENTS - FI	LUORO ROOM 6
FROM ITEM #	TO ITEM #	CONDUIT QTY AND SIZE	CABLE	REMARKS
CB1	ST ST	(1) - 3/4"	2 #12 & #12 GND	CONDUIT & CABLE PROVIDED BY THE ELECTRICAL CONTRACTOR.
CB2	ST	(1) - 3/4"	2 #12 & #12 GND	CONDUIT & CABLE PROVIDED BY THE ELECTRICAL CONTRACTOR.
CB1	ME	(1) - 2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED BY PHILIPS, INSTALLED BY THE ELECTRICAL CONTRACTOR.
CB2	MR	(1) - 1 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED BY PHILIPS, INSTALLED BY THE ELECTRICAL CONTRACTOR.
MR	₩L	(1) - 1/2"	2 #12 & #12 GND	CONDUIT & CABLE PROVIDED BY THE ELECTRICAL CONTRACTOR.
MR	DS	(1) - 1/2"	2 #12 & #12 GND	CONDUIT & CABLE PROVIDED BY THE ELECTRICAL CONTRACTOR.
MR	ME	(1) - 2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MR	MB	(1) - 2 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MR	MB	(1) - 2 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MR	EEC	VIA WR4 & WR2	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MR	EEC	VIA WR4 & WR2	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MB	EEC	VIA WR1 & WR4 & WR2	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MR	VF	VIA WR4 & WR2	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MB	QR	VIA WR4 & WR2	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MB	TV	(1) - 1 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MB	TV	(1) - 1 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MB	IR I	(1) - 2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MR	IB	(1) - 2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MS	MR	VIA WR1 & WR4	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
MS	MR	VIA WR1 & WR4	BY PHILIPS	CABLES FURNISHED AND INSTALLED BY PHILIPS.
ME	MU	(1) - 2 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
ME	MU	(1) - 2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING.
MR	MU	(1) - 2 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING
MR	MU	(1) - 2 1/2"	BY PHILIPS	CONDUIT PROVIDED BY THE ELECTRICAL CONTRACTOR; CABLES FURNISHED AND INSTALLED BY PHILIPS. PROVIDE PULL STRING

NOT

- 1. SEE SHEET E-001 FOR LEGEND AND GENERAL NOTES.
- 2. SEE SHEET EP101 FOR LOCATION OF PANELBOARD P1.
- 3. REFER TO PHILIPS INSTALLATION DRAWING FOR EASY DIAGNOST ELEVA. N-EAS100611.

REFERS TO ITEM ON PHILIPS DRAWINGS

KEYED NOTES:

- 1) INSTALL RECEPTACLE BETWEEN "WR2" AND COUNTER.
- RELOCATED POSITION. SEE ED101 FOR EXISTING LOCATION.
- INSTALL RECEPTACLE @96" AFF FOR IMAGE PROJECTOR.

 PROVIDE CONNECTION AT CEILING TO PATIENT LIFT.
 COORDINATE EXACT LOCATION WITH EQUIPMENT. CIRCUIT #P1-21.

ARCHITECTURE	ENGINEERING	PLANNING	INTERIOR DESIGN	COMMISSIONING
ARC	ENG	PLA	INT	00
			F	
			Ē	
			C	R



CONTINUE CON	Ş
PROJECT	
NORTH	
MAG NORTH	

				H	/					
										H
					1401F01	AUC II ON				G
\D\C	(g)	NOIN			TOILO	ISSUED FOR CONSTRUCTION		08.24.10		
Bramball Radiolo	Bramhall Radiology FLUORO RENOVATIONS			PORTLAND, ME					CURRENT ISSUE STATUS:	E
								8.24.10	DATE	
								ISSUED FOR CONSTRUCTION	DESCRIPTION	D
								ISSUED FI	10	С
								0	REV	
	APHIC	0" 	LE:				1"			
-	ALE: OJECT	МДМ	JAGE	R·			As	indica	ated DJV	
_		N BY	_	1.					CDS	1

A/E OF RECORD: PROJECT NO:

SHEET TITLE:
ENLARGED POWER

EP 402

PLAN SHEET 2