LIGHTING

- 2x4 FLUORESCENT FIXTURE
- Ab — ASSOCIATED CONTROL DEVICE
- FIXTURE TYPE (SEE LIGHT FIXTURE SCHEDULE)
- 1x4 FLUORESCENT FIXTURE
- 2x2 FLUORESCENT FIXTURE
- FIXTURE WIRED TO UNSWITCHED NORMAL CIRCUIT
- FIXTURE WIRED TO UNSWITCHED EMERGENCY CIRCUIT
- FIXTURE WIRED TO SWITCHED EMERGENCY CIRCUIT
- DOWN LIGHT
- FLUORESCENT STRIP
- WALL MOUNTED FIXTURES
- TRACK LIGHTING
- WALL WASH LIGHT FIXTURE
- EXIT SIGN, CEILING MOUNTED ARROW INDICATES EGRESS DIRECTION SHADING INDICATES SIGN FACE
- EXIT SIGN, WALL MOUNTED SHADING INDICATES SIGN FACE
- TD — DUAL HEAD EMERGENCY LIGHT BATTERY PACK TD – TIME DELAY RESET
- REMOTE EMERGENCY LIGHTING HEAD
- S_3 — 3-WAY TOGGLE SWITCH
- S_a — SINGLE POLE TOGGLE SWITCH INDICATES CONTROLLED FIXTURE
- S_4 — 4-WAY TOGGLE SWITCH
- S_K — KEY SWITCH
- S_{II} — DUAL LEVEL SWITCHING
- S_D — DIMMER SWITCH. INCANDESCENT OR FLUORESCENT AS REQUIRED.
- S_P — TOGGLE SWITCH WITH PILOT LIGHT
- S_T — TIMER SWITCH, SPRING WOUND
- S_{DT} — SINGLE POLE DOUBLE THROW TOGGLE SWITCH, CENTER POSITION OFF
- S_{WP} — WEATHER PROOF
- S_{XP} — EXPLOSION PROOF
- UNSWITCHED CONTINUATION OF BRANCH CIRCUIT
- HOME RUN
- 1a — OCCUPANCY SENSOR
  - a. INDICATES CONTROLLED FIXTURE
  - 1. INDICATES TYPE
    - 1=WATTSTOPPER WALL SWITCH DW-100
    - 2=WATTSTOPPER WALL SWITCH DW-200
    - 3=WATTSTOPPER WALL SWITCH TS-400
    - 4=WATTSTOPPER CEILING SENSOR W-500A
    - 5=WATTSTOPPER CEILING SENSOR W-1000A
    - 6=WATTSTOPPER CEILING SENSOR W-2000A
    - 7=WATTSTOPPER CEILING SENSOR W-2000H
  - INDICATES AIMING DIRECTION

COMMUNICATION & DATA SYSTEMS

- TELEPHONE SYSTEM WALL JACK W–INDICATES WALL MOUNTED AT 48" AFF P–INDICATES PAYPHONE (2)–INDICATES 2 OUTLETS, SINGLE BOX
- DATA SYSTEM OUTLET
- COMBINATION VOICE/DATA SYSTEM OUTLET
- UNDERFLOOR TELEPHONE SYSTEM OUTLET
- UNDERFLOOR DATA SYSTEM OUTLET
- UNDERFLOOR VOICE & DATA OUTLET
- CATV — CABLE TELEVISION SYSTEM OUTLET. MOUNT 18"AFF UNLESS OTHERWISE NOTED
- CCTV — CLOSED CIRCUIT TELEVISION OUTLET. MOUNT 18" AFF UNLESS OTHERWISE NOTED
- PA — PAGING SYSTEM CONTROL PANEL AND PAGING AMPLIFIER
- S — PAGING SYSTEM SPEAKER. CEILING MOUNTED
- S — PAGING SYSTEM SPEAKER. WALL MOUNT AT 7'–6" AFF
  - 1. FLUSH, 2. SURFACE, 3. HORN, 4. DUAL HORN
- MIC — MICROPHONE OUTLET. WALL MOUNT 6'–0" AFF UNLESS OTHERWISE NOTED
- VC — VOLUME CONTROL
- HC — INTERCOM SYSTEM HAND KEY
- CS — CLOCK SPEAKER
- HS — INTERCOM SYSTEM HAND SET
- C — WALL MOUNTED CLOCK
- CEILING MOUNTED TELEPHONE SYSTEM OUTLET
- CEILING MOUNTED DATA SYSTEM OUTLET
- CEILING MOUNTED VOICE & DATA OUTLET

POWER

- (4) 30A — NON-FUSED SAFETY SWITCH AMPERE RATING; NEMA ENCLOSURE RATING
- F 60AS 40AF (4) — FUSED SAFETY SWITCH. TOP NUMBER INDICATES SWITCH AMPERE RATING. LOWER NUMBER INDICATES FUSE RATING; NEMA ENCLOSURE
- 1 (4) — MAGNETIC MOTOR STARTER. FVNR UNLESS INDICATED OTHERWISE; NEMA ENCLOSURE RATING; NEMA SIZE (TYPICAL)
- CB 20/1 — COMBINATION CIRCUIT BREAKER/MAGNETIC MOTOR STARTER FIRST NUMBER INDICATES CIRCUIT BREAKER AMPERE RATING SECOND NUMBER INDICATES NEMA STARTER SIZE
- F 60/40/1 — COMBINATION FUSED DISCONNECT/MAGNETIC MOTOR STARTER NUMBERS INDICATE DISCONNECT AMPERE RATING/FUSE RATING/NEMA STARTER SIZE
- 30/1 — NON-FUSED DISCONNECT/MAGNETIC MOTOR STARTER FIRST NUMBER INDICATES CIRCUIT BREAKER AMPERE RATING SECOND NUMBER INDICATES NEMA STARTER SIZE
- M OL — MANUAL MOTOR STARTER. TOGGLE OPERATED, 1,2 OR 3 POLE AS REQUIRED. OVERLOAD PROTECTION
- M — MANUAL MOTOR SWITCH, TOGGLE OPERATED, SINGLE PHASE. 1 OR 2 POLE AS REQUIRED (NO OVERLOAD PROTECTION)
- CB 100A — ENCLOSED CIRCUIT BREAKER AMPERE RATING
- 5 — ELECTRIC MOTOR, NUMBER INDICATES HORSEPOWER RATING
- 5 — EXPLOSION PROOF MOTOR
- VAV — VARIABLE AIR VOLUME CONTROL ACTUATORS
- HS H/O/A — LOCAL SELECTOR SWITCH H/O/A – HAND/OFF/AUTO
- EMO — EMERGENCY OFF BREAK GLASS STATION
- PB — PUSHBUTTON STATION
- J — JUNCTION BOX
- T — TRANSFORMER
- P — POWER POLE
- CONDUIT TURNING UP
- CONDUIT TURNING DOWN
- EY CONDUIT SEAL
- E — DUPLEX RECEPTACLE, NEMA 5–20R. INSTALLED ON EMERGENCY CIRCUIT (TYPICAL)
- GFI DUPLEX RECEPTACLE, NEMA 5–20R
- HOSPITAL GRADE DUPLEX RECEPTACLE, NEMA 5–20R
- HOSPITAL GRADE GFCI DUPLEX RECEPTACLE, NEMA 5–20R
- IG — HOSPITAL GRADE ISOLATED GROUND DUPLEX RECEPTACLE, NEMA 5–20R
- SINGLE RECEPTACLE, NEMA 5–20R
- DOUBLE DUPLEX (QUADRUPLEX) RECEPTACLE, NEMA 5–20R
- HOSPITAL GRADE DOUBLE DUPLEX RECEPTACLE NEMA 5–20R
- S — SWITCHED RECEPTACLE
- FLOOR OUTLET, DUPLEX RECEPTACLE, NEMA 5–20R
- CEILING MOUNTED DUPLEX RECEPTACLE, 5–20R
- POWER RECEPTACLE, 480 VOLT NEMA CONFIGURATION AS NOTED.
- POWER RECEPTACLE, 240 VOLT NEMA CONFIGURATION AS NOTED.
- PANELBOARD, NORMAL POWER
- PANELBOARD, EMERGENCY POWER
- MULTI OUTLET ASSEMBLY

NURSE CALL SYSTEM

- CL — NURSE CALL CALL LIGHT
- PATIENT CALL BUTTON
- NURSE CALL PULL CORD
- N M — NURSE CALL MASTER STATION

LINE TYPES

- EXISTING
- NEW
- DEMOLITION

FIRE ALARM

- FACP — FIRE ALARM CONTROL PANEL
- FAA — FIRE ALARM ANNUNCIATOR
- M — FIRE ALARM MASTER BOX
- F — FIRE ALARM MANUAL PULL STATION
- F — FIRE ALARM SPEAKER/STROBE UNIT
- F — FIRE ALARM AUDIBLE/VISIBLE NOTIFICATION APPLIANCE (GENERAL EVACUATION)
- FIRE ALARM AUDIBLE/VISIBLE NOTIFICATION APPLIANCE CLEAN ROOM NOTIFICATION (LOCAL)
- F (110) C — FIRE ALARM VISIBLE ONLY NOTIFICATION APPLIANCE CANDELA INTENSITY–15/75 UNLESS OTHERWISE NOTED; CEILING MOUNTED
- P A — PHOTOELECTRIC SMOKE DETECTOR. CEILING MOUNTED INDICATES AUXILIARY CONTACT.
- H <TPP–1> — FIXED TEMPERATURE HEAT DETECTOR. CEILING MOUNTED. INDICATES EQUIPMENT INTERLOCKED WITH THE DETECTOR
- P1 <RC–1> — CLEAN ROOM SMOKE DETECTOR; INDICATES EQUIPMENT INTERLOCKED WITH THE SMOKE DETECTOR
- H R — COMBINATION RATE–OF–RISE/FIXED TEMPERATURE HEAT DETECTOR. CEILING MOUNTED
- D — DUCT SMOKE DETECTOR, PHOTOELECTRIC WITH AUXILIARY CONTACT.
- FS — SPRINKLER SYSTEM FLOW SWITCH
- TS — SPRINKLER SYSTEM TAMPER SWITCH
- DH — FIRE ALARM SYSTEM MAGNETIC DOOR HOLDER
- INTERLOCK RELAY
- SD — SMOKE DAMPER
- RTI — DUCT SMOKE DETECTOR REMOTE TEST INDICATOR
- K — KNOX BOX

SECURITY SYSTEMS

- S 2–WAY — 2–WAY CEILING MOUNTED INTERCOM SPEAKER
- S — CEILING MOUNTED PAGING SPEAKER
- H — WALL MOUNTED PAGING HORN
- C — CEILING OR WALL MOUNTED FIXED CAMERA
- P — CEILING OR WALL MOUNTED PTZ CAMERA
- PAGE — PAGING CONTROL EQUIPMENT
- INT — INTERCOM MASTER STATION
- DOOR — DOOR CONTROL EQUIPMENT
- DC — MONITORED DOOR POSITION SWITCH AND CONTROLLED DOOR HARDWARE
- DPS — MONITORED DOOR POSITION SWITCH
- STANDARD INTERCOM STATION
- VISITATION TELEPHONE
- WALL MOUNTED DURESS BUTTON
- GP — GRAPHIC CONTROL PANEL
- TS — TOUCH SCREEN WORKSTATION
- TV — CCTV CONTROL OR DISPLAY EQUIPMENT
- ZONE — PERIMETER CONTROL EQUIPMENT
- DUR — DURESS CONTROL EQUIPMENT
- DURESS ALARM RECEIVER
- TEL — OFFICER CONTROLLED COLLECT–ONLY PUBLIC TELEPHONE
- DEL — OFFICER CONTROLLED FIRE SPRINKLER (DELUGE) HEAD
- MW+ — DUAL TECHNOLOGY VOLUMETRIC SENSOR
- DR — LOCAL DOOR RELEASE BUTTON
- WAT — OFFICER CONTROLLED SHOWER WATER SUPPLY
- L&E — OFFICER CONTROLLED LIGHTING AND ELECTRICAL OUTLETS
- D — DOOR CONTACT
- CR — CARD READER
- KP — KEY PAD
- CCTV — CLOSED CIRCUIT TELEVISION CAMERA
- ES — ELECTRIC STRIKE
- ML — MAG LOCK

ONE LINE DIAGRAM

- 52 — MEDIUM VOLTAGE DRAWOUT CIRCUIT BREAKER
- LOW VOLTAGE DRAWOUT CIRCUIT BREAKER
  - AF – AMP FRAME
  - AT – AMP TRIP
  - EO – ELECTRICALLY OPERATED
- MOLDED CASE CIRCUIT BREAKER
- ST — ST – SHUNT TRIP; GF – GROUND FAULT; EO – ELECTRICALLY OPERATED
- DISCONNECT, ISOLATION OR SAFETY SWITCH
- FUSED CUTOUT
- FUSED LOAD BREAK SWITCH
- MEDIUM VOLTAGE MOTOR STARTER
- 1 — MAGNETIC MOTOR STARTER. NUMERAL INDICATES NEMA SIZE. FVNR UNLESS OTHERWISE NOTED. FVR – FULL VOLTAGE REVERSING; RVAT – REDUCING VOLTAGE AUTO TRANSFORMER; 2S – TWO SPEED
- CAPACITOR
- VFD — VARIABLE FREQUENCY DRIVE
- 0A — POWER TRANSFORMER
  - 0A – LIQUID TYPE SELF COOLED
  - AA – DRY TYPE SELF COOLED
  - FA – FAN COOLED
  - CONNECTION
- SHIELDED ISOLATION TRANSFORMER
- 2 480/120 — POTENTIAL TRANSFORMER RATIO NUMBER REQUIRED
- 3 600/5 — CURRENT TRANSFORMER RATIO NUMBER REQUIRED
- GROUND FAULT CURRENT TRANSFORMER
- 5 — MOTOR, NUMBER INDICATES HORSEPOWER
- GENERATOR
- N F L ATS — ATS – AUTOMATIC TRANSFER SWITCH; MTS – MANUAL TRANSFER SWITCH
- A — METER
  - A – AMMETER
  - V – VOLTMETER
  - W – WATTMETER
  - WH – WATT HOURMETER
  - KWH – KILOWATT HOUR
  - KVAR – KILOVAR METER
  - VAR – VAR METER
  - HZ – FREQUENCY METER
  - PF – POWER FACTOR METER
- DPM — DIGITAL POWER METER
- AS — METER TRANSFER SWITCH
  - AS – AMMETER SWITCH
  - VS – VOLTMETER SWITCH
- TVSS — TRANSIENT VOLTAGE SURGE SUPPRESSOR
- LA — LIGHTNING ARRESTOR
- K — KEY INTERLOCK
- FUSE
- E F — ELECTRONIC POWER FUSE
- DRAWOUT DEVICE
- GROUND

ABBREVIATIONS

A,AMP	AMPERE
AFF	ABOVE FINISHED FLOOR
AFG	ABOVE FINISHED GRADE
AHJ	AUTHORITY HAVING JURISDICTION
AIC	AMPERE INTERRUPTING CAPACITY
AWG	AMERICAN WIRE GAUGE
BFG	BELOW FINISHED GRADE
BOS	BOTTOM OF STEEL
C	CONDUIT, CONDUCTOR
CATV	CABLE TELEVISION
CB	CIRCUIT BREAKER
CCTV	CLOSED CIRCUIT TELEVISION
CPT	CONTROL POWER TRANSFORMER
CT	CURRENT TRANSFORMER
CU	COPPER
DACT	DIGITAL ALARM COMMUNICATOR TRANSMITTER
DB	DIRECT BURIED
DISC	DISCONNECT
DN	DOWN
EMT	ELECTRICAL METALLIC TUBING
EWC	ELECTRIC WATER COOLER
FAA	FIRE ALARM ANNUNCIATOR
FACP	FIRE ALARM CONTROL PANEL
FBO	FURNISHED BY OTHERS
FU	FUSE
FWE	FURNISHED WITH EQUIPMENT
GEN	GENERATOR
GFCI	GROUND FAULT CIRCUIT BREAKER
GND	GROUND
HP	HORSEPOWER
HTR	HEATER
IG	ISOLATED GROUND
IMC	INTERMEDIATE METAL CONDUIT
K	KILO
KCMIL	THOUSAND CIRCULAR MILS
KV	KILOVOLT
KVA	KILOVOLT–AMPERE
KVAR	KILOVOLT–AMPERE REACTIVE
KW	KILOWATT
KWH	KILOWATT–HOUR
LA	LIGHTNING ARRESTER
LTG	LIGHTING
MC	METAL CLAD
MCB	MAIN CIRCUIT BREAKER
MFR	MANUFACTURER
MI	MINERAL INSULATED
MLO	MAIN LUG ONLY
MTD	MOUNTED
MV	MEDIUM VOLTAGE
NC	NORMALLY CLOSED
NEC	NATIONAL ELECTRICAL CODE
NEG	NEGATIVE
NEUT	NEUTRAL
NIC	NOT IN CONTRACT
NO	NORMALLY OPEN
NTS	NOT TO SCALE
PF	POWER FACTOR
PH	PHASE
PVC	POLYVINYL CHLORIDE
RGS	RIGID STEEL CONDUIT
RSC	RIGID STEEL CONDUIT
RTD	RESISTANCE TEMPERATURE DETECTOR
SN	SOLID NEUTRAL
STP	SHIELDED TWISTED PAIR
STT	SHIELDED TWISTED TRIPLET
SWBD	SWITCHBOARD
SWGR	SWITCHGEAR
TOS	TOP OF STEEL
TRANSF	TRANSFORMER
TVSS	TRANSIENT VOLTAGE SURGE SUPPRESSER
V	VOLT
VA	VOLT–AMPERE
VAR	VOLT–AMPERE REACTIVE
WM	WATT METER
WP	WEATHER PROOF
XFMR	TRANSFORMER
XP	EXPLOSION PROOF

GENERAL NOTES:

1. ALL WORK SHALL BE PERFORMED IN ACCORDANCE WITH NFPA–70, NATIONAL ELECTRICAL CODE (NEC).
2. ALL MOTOR SAFETY SWITCHES, DISCONNECTS AND MOTOR STARTERS ARE PROVIDED BY DIVISION 260000 UNLESS NOTED AS FURNISHED WITH EQUIPMENT (FWE).
3. UNLESS OTHERWISE NOTED CONVENIENCE RECEPTACLES SHALL BE MOUNTED 18–INCHES AFF, LIGHTING TOGGLE SWITCHES 48–INCHES AFF, DATA SYSTEM OUTLETS 18–INCHES AFF, FIRE ALARM NOTIFICATION DEVICES 80–INCHES AFF OR 6–INCHES BELOW CEILING, WHICHEVER IS LOWER, AND FIRE ALARM MANUAL PULL STATIONS 48–INCHES TO TOP OF DEVICE.
4. ALL PENETRATIONS THROUGH FLOORS, RATED WALLS AND PARTITIONS SHALL BE SEALED WITH UL APROVED FIRE SEALANT MATERIAL TO MAINTAIN THE RATING OF SEPARATION.
5. ALL ENCLOSURES, CONDUIT BODIES AND THEIR COVERS CONTAINING FIRE ALARM SYSTEM CONDUCTORS SHALL BE PAINTED RED.
6. AN EQUIPMENT GROUNDING CONDUCTOR SHALL BE INSTALLED WITH EVERY FEEDER AND BRANCH CIRCUIT.
7. UNLESS OTHERWISE NOTED, WIRING SHALL BE 2#12 AWG CONDUCTORS AND #12 GND. HOME RUNS FED FROM 20A–1P CIRCUITS IN EXCESS OF 100 FEET SHALL BE #10 AWG. FEEDERS AND MOTOR BRANCH CIRCUITS SHALL BE INSTALLED IN A 3/4" CONDUIT UNLESS OTHERWISE NOTED.
8. FLEXIBLE CONNECTIONS TO MOTORS SHALL BE LIQUID TIGHT FLEXIBLE METAL CONDUIT, UNLESS OTHERWISE NOTED.
9. LIGHTING TOGGLE SWITCHES SHALL BE COMMERCIAL SPECIFICATION GRADE 120 VOLT, SIDE WIRED AND PROVIDED WITH GROUNDING SCREW. HUBBELL, LEVITON, PASS AND SEYMOUR OR APPROVED EQUAL. DIMMER SWITCHES SHALL BE LEVITON SURE SLIDE 6667–31 OR APPROVED EQUAL. COORDINATE COLOR WITH ARCHITECT.
10. CONVENIENCE RECEPTACLES SHALL BE COMMERCIAL SPECIFICATION GRADE OR HOSPITAL GRADE AS SHOWN ON THE DRAWINGS, GROUNDING TYPE NEMA 5–20R, SIDE WIRED. HUBBELL, LEVITON, PASS AND SEYMOUR OR APPROVED EQUAL. RECEPTACLE WITH AN "E" SUBSCRIPT SHALL BE RED EVEN THOUGH THEY ARE NOT INSTALLED ON AN EMERGENCY CIRCUIT. COORDINATE COLORS OF OTHERS WITH ARCHITECT.
11. PROVIDE WALL PLATES FOR ALL WIRING DEVICES, NYLON SMOOTH TYPE. WALL PLATE COLOR SHALL MATCH DEVICE COLOR. ALL WALL PLATES SHALL BE PROVIDED WITH A CLEAR ADHESIVE LABEL STATING PANELBOARD AND CIRCUIT NUMBER.
12. WIRING AND DEVICES FOR VOICE/DATA JACKS, CATV JACKS, NURSE CALL SYSTEMS, CARD READERS, MICROPHONES, SPEAKERS, VOLUME CONTROL AND SECURITY EQUIPMENT ARE PROVIDED BY THE OWNER. PROVIDE RECESSED BOXES IN THE WALL OR CEILING WHERE INDICATED ON THE DRAWINGS AND 3/4" CONDUIT FROM WALL BOXES TO ABOVE AN ACCESSIBLE CEILING. IF DEVICES COME WITH THEIR OWN BACK BOX, A SEPARATE BOX IS NOT REQUIRED. COORDINATE WITH OWNER.

GENERAL NOTE

1. ALL GENERAL NOTES, SYMBOL LISTS, AND DETAILS ARE TO BE CONSIDERED AS APPLICABLE TO ALL ELECTRICAL DRAWINGS FOR THIS PROJECT. SYMBOLS AND ABBREVIATIONS SHOWN ON THIS SHEET ARE FOR REFERENCE ONLY AND DO NOT INDICATE THEIR INCORPORATION IN THE DESIGN.

144 Fore Street/P.O. Box 618
Portland, Maine 04104
tel. (207) 772–3846
fax. (207) 772–1070
www.smrtinc.com

ARCHITECTURE
ENGINEERING
PLANNING
INTERIOR DESIGN
COMMISSIONING

SMRT

STATE OF MAINE JOHN P. PERKINS No. 7107 LICENSED PROFESSIONAL ENGINEER

UNIVERSITY OF SOUTHERN MAINE
SIMULATION LABORATORY
PORTLAND, MAINE

ISSUED FOR BIDDING & CONSTRUCTION
4–15–11
CURRENT ISSUE STATUS:

REV	DESCRIPTION	DATE
0	ISSUED FOR BIDDING, PERMITTING & CONSTRUCTION	4–15–11

GRAPHIC SCALE: 0" 1"

SCALE:	NONE
PROJECT MANAGER:	SLB
JC/DRAWN BY:	CDS
A/E OF RECORD:	JPP
CAD FILE:	E–001–10150
PROJECT NO:	10150–00
DATE:	4–15–11

SHEET TITLE:

LEGEND AND GENERAL NOTES

SHEET No. E–001

© COPYRIGHT 2009 SMRT INC.