

FIRE ALARM LEGEND

- FCPS** INTELLIGENT ADDRESSABLE FIRE ALARM CONTROL PANEL (NOTIFIER #NFS2-640)
- BAT** BATTERY CABINET (NOTIFIER #NFS-LBBR)
- RMCP** REMOTE MICROPHONE CONTROL PANEL WITH SWITCHES (NOTIFIER #RM-1 W/ #LCD2-80)
- FPS** FIRE CONTROL POWER SUPPLY WITH BATTERY BACKUP (NOTIFIER #HPFFB)
- EX** EXISTING RADIO TRANSMITTER BOX (AES #778BF)
- EX** NETWORK COMMUNICATION MODULE (NOTIFIER #NION)
- EX** EXISTING DOCUMENT BOX
- EX** EXISTING KNOX BOX
- PT** ADDRESSABLE DUAL ACTION MANUAL PULL STATION (NOTIFIER #NBG-12LX)
- SD** ADDRESSABLE SMOKE DETECTOR (NOTIFIER #FSP-851 WITH #B210LP BASE)
- SD** ADDRESSABLE DUCT SMOKE DETECTOR (NOTIFIER #DNR WITH FST-851R AND #ST-3 SAMPLING TUBE)
- SD** ADDRESSABLE 135' F.T. HEAT DETECTOR (NOTIFIER #FST-851 WITH #B210LP BASE)
- MM** ADDRESSABLE MONITOR MODULE (NOTIFIER #FM-1)
- MM** ADDRESSABLE MINI MONITOR MODULE (NOTIFIER #FM-101)
- MM** ADDRESSABLE RELAY MODULE (NOTIFIER #FRM-1)
- RTS** REMOTE TEST STATION (NOTIFIER #RTS151)
- SPSW** 24VDC SYNC. MULT-CANDELA SPEAKER/STROBE (NOTIFIER #SPSW)
- SPSW** CEILING 24VDC SYNC. MULT-CANDELA SPEAKER/STROBE (NOTIFIER #SPSCW)
- SPSW** 24VDC SYNCHRONIZED MULTI-CANDELA STROBE (NOTIFIER #SW)
- FM** 24VDC WALL MOUNT MAGNETIC DOOR HOLDERS (NOTIFIER #FM-998)
- SW** SPRINKLER SYSTEM WATER FLOW SWITCH
- SW** SPRINKLER SYSTEM TAMPER SWITCH
- SW** SPRINKLER SYSTEM PRESSURE SWITCH
- RES** END-OF-LINE-RESISTOR
- TICKS** TICKS DENOTES NUMBER OF #14 FPLR FIRE ALARM RATED CONDUCTORS
- DEV** DEVICE TO BE FURNISHED AND INSTALLED BY OTHERS BUT WIRED BY THE E.C.

NOTE: THE SPECIFIED FIRE ALARM SYSTEM AND PERIPHERAL DEVICES SHALL BE NOTIFIER AS FURNISHED BY:
BK SYSTEMS, INC.
 4 COTE AVENUE
 GOFFSTOWN, NH 03045
 TELEPHONE: 603-647-8775
 FAX: 603-647-4806
 EMAIL: NIKWEBSTER@BKSYSTEMSINC.COM

FIRE ALARM NOTES:

1. SPEAKER CIRCUITS ARE INDICATED ON RISER DIAGRAM AND SYSTEM DESIGN DRAWINGS BY SUBSCRIPT S-1, 2, 3, ETC.; PLEASE REFER TO RISER AND SYSTEM LAYOUT DRAWINGS FOR LOCATION OF DEVICES.
2. 24VDC STROBE CIRCUITS ARE INDICATED ON RISER DIAGRAM AND SYSTEM DESIGN DRAWINGS BY SUB-SCRIPT V-1, 2, 3, ETC.; PLEASE REFER TO RISER AND SYSTEM LAYOUT DRAWINGS FOR LOCATION OF DEVICES.
3. ALL SPEAKERS ARE TO BE SET FOR 25 VOLT OPERATION AND SPEAKER WATTAGES ARE AS SHOWN ON THE SYSTEM DESIGN DRAWINGS.
4. ALL SPEAKERS ARE TO BE MOUNTED IN A FOUR (4) INCH SQUARE x 2-1/8 INCH DEEP BACKBOX WITH NO EXTENSION RING REQUIRED. THE SHIELD SHOULD BE TWISTED TOGETHER AND TAPED SECURELY IN EACH BACK BOX IN ORDER TO AVOID SHORTS AND GROUNDS WITHIN THE SYSTEM SPEAKER CIRCUITS.
5. THE SIGNAL CIRCUITS ARE TO BE WIRED AND INSTALLED WITH NO DEVIATION TO THE FIRE ALARM SYSTEM RISER DIAGRAM AND LAYOUT DRAWINGS DUE TO CIRCUIT AMPERAGE RESTRICTIONS WITHOUT FIRST DISCUSSING WITH AND OBTAINING APPROVAL FROM BK SYSTEMS, INC.
6. THE LOCATIONS OF INTERIOR AND EXTERIOR AUDIO/VISUAL DEVICES SHOWN ON THE DRAWINGS HAVE BEEN LOCATED IN ACCORDANCE WITH NFPA 72. UNDER NO CIRCUMSTANCES SHALL THE ELECTRICAL CONTRACTOR CHANGE THE LOCATIONS OF ANY OF THESE DEVICES WITHOUT FIRST DISCUSSING WITH AND OBTAINING APPROVAL FROM BK SYSTEMS, INC. IF THE ELECTRICAL CONTRACTOR INSTALLS ANY OF THESE DEVICES IN LOCATIONS OTHER THAN AS SHOWN ON THE CONTRACT DOCUMENTS, THE ELECTRICAL CONTRACTOR WILL BE RESPONSIBLE FOR ALL COSTS ASSOCIATED WITH RELOCATING, PATCHING AND PAINTING WHERE DEVICES HAD BEEN IMPROPERLY INSTALLED.
7. THE END-OF-LINE DEVICES MUST BE LOCATED IN A COMMON AREA ONLY.
8. NO "T" TAPPING ALLOWED ON ANY CIRCUITS.
9. NO WIRING OR CONDUITS TO ENTER OR EXIT FROM TOP LEFT CORNER OF THE FIRE ALARM CONTROL PANEL DUE TO LOCATIONS OF POWER SUPPLIES. NO WIRING OR CONDUITS TO ENTER OR EXIT THROUGH THE BOTTOM OF THE FIRE ALARM CONTROL PANEL EXCEPT FOR BATTERY BOX CONNECTIONS. ALL CONDUITS THAT ENTER THE CONTROL PANEL SHALL BE NO LARGER THAN ONE (1) INCH.
10. ALL SMOKE AND HEAT DETECTORS SHALL BE LOCATED A MINIMUM OF 3'-0" AWAY FROM ALL SUPPLY AIR DIFFUSERS.

WBRC
 ARCHITECTS + ENGINEERS

1. Reviewed, No Exception Taken
 2. Reviewed, Review as Noted
 3. Review and Re-submit
 4. Rejected
 5. Other, Held for Record, Not Reviewed

This review is a site to general compliance with the rules, codes and the information given in the Contract Documents. Conditions or comments made on the shop drawings during this review do not release the Contractor from compliance with the requirements of the Contract Documents and applicable laws, codes and regulations. Review of a specific item shall not constitute a review of the entire drawing set. The Contractor is responsible for dimensions to be coordinated and consistent with the project information that appears on the drawings, elevations, notes, sections, schedules, requirements and conditions of the contract documents. The work shall be in accordance with the drawings and specifications and shall be in accordance with the applicable laws, codes and regulations.

REVIEWER: **Stephanie J. Lapan, P.E.** DATE: **07.03.13**

SYSTEM INPUTS

	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O	P	Q	R	S	T	U	V	W	X	Y	Z	
1. MANUAL FIRE ALARM PULL STATIONS - GROUND																											
2. MANUAL FIRE ALARM PULL STATIONS - 1ST FLOOR																											
3. MANUAL FIRE ALARM PULL STATIONS - 2ND FLOOR																											
4. MANUAL FIRE ALARM PULL STATIONS - 3RD FLOOR																											
5. MANUAL FIRE ALARM PULL STATIONS - 4TH FLOOR																											
6. SMOKE DETECTORS - GROUND																											
7. SMOKE DETECTORS - GROUND-ELEVATOR RECALL																											
8. SMOKE DETECTORS - 1ST FLOOR																											
9. SMOKE DETECTORS - 1ST FLOOR-ELEVATOR RECALL																											
10. SMOKE DETECTORS - 2ND FLOOR																											
11. SMOKE DETECTORS - 2ND FLOOR-ELEVATOR RECALL																											
12. SMOKE DETECTORS - 3RD FLOOR																											
13. SMOKE DETECTORS - 3RD FLOOR-ELEVATOR RECALL																											
14. SMOKE DETECTOR - 4TH FLOOR																											
15. SMOKE DETECTORS - 4TH FLOOR-ELEVATOR RECALL																											
16. DUCT SMOKE DETECTORS - FOURTH FLOOR																											
17. HEAT DETECTORS - GROUND FLOOR																											
18. HEAT DETECTORS - 1ST FLOOR																											
19. HEAT DETECTORS - 2ND FLOOR																											
20. HEAT DETECTORS - 3RD FLOOR																											
21. HEAT DETECTORS - 4TH FLOOR																											
22. WATERFLOW - GROUND FLOOR																											
23. WATERFLOW - 1ST FLOOR																											
24. WATERFLOW - 2ND FLOOR																											
25. WATERFLOW - 3RD FLOOR																											
26. WATERFLOW - 4TH FLOOR																											
27. SPRINKLER CONTROL VALVE - BASEMENT FLOOR																											
28. SPRINKLER CONTROL VALVE - 1ST FLOOR																											
29. SPRINKLER CONTROL VALVE - 2ND FLOOR																											
30. SPRINKLER CONTROL VALVE - 3RD FLOOR																											
31. SPRINKLER CONTROL VALVE - 4TH FLOOR																											
32. ROOF HATCH DOOR CONTACT SUPERVISION																											
33. ELEV. SHUNT TRIP SUPERVISION																											
34. DISABLING OF ZONES OF INDIVIDUAL DEVICES																											
35. LOSS OF NETWORK COMMUNICATION																											
36. FIRE ALARM AC POWER FAILURE																											
37. FIRE ALARM ABNORMAL AC VOLTAGE																											
38. FIRE ALARM SYSTEM LOW BATTERY																											
39. BREAK IN BATTERY CIRCUIT																											
40. OPEN CIRCUIT																											
41. NOTIFICATION APPLIANCE CIRCUIT SHORT																											
42. SUPERVISORY																											
43. TROUBLE																											
44. ABNORMAL SWITCH POSITION AT FACP OR ANNUNCIATOR																											
45. VOICE AMPLIFIER FAILURE																											
46. LOSS OF COMMUNICATION WITH FACP CONNECTED DEVICES																											
47. OPENING/REMOVING/TAMPING WITH DEVICES																											
48.																											

FIRE ALARM SEQUENCE OF OPERATION MATRIX

CLASS A WIRING PER NFPA 72 2010 EDITION:

23.4.2.2* ALL STYLES OF CLASS A AND CLASS X CIRCUITS USING PHYSICAL CONDUCTORS (E.G., METALLIC, OPTICAL FIBER) SHALL BE INSTALLED SUCH THAT THE OUTGOING AND RETURN CONDUCTORS, EXITING FROM AND RETURNING TO THE CONTROL UNIT, RESPECTIVELY, ARE ROUTED SEPARATELY. THE OUTGOING AND RETURN (REDUNDANT) CIRCUIT CONDUCTORS SHALL NOT BE RUN IN THE SAME CABLE ASSEMBLY (I.E., MULTI-CONDUCTOR CABLE), ENCLOSURE, OR RACEWAY ONLY UNDER THE FOLLOWING CONDITIONS:
 (1) FOR A DISTANCE NOT TO EXCEED 3 M (10 FT) WHERE THE OUTGOING AND RETURN CONDUCTORS ENTER OR EXIT THE INITIATING DEVICE, NOTIFICATION APPLIANCE, OR CONTROL UNIT ENCLOSURES.
 (2) SINGLE CONDUIT/RACEWAY DROPS TO INDIVIDUAL DEVICES OR APPLIANCES.
 (3) SINGLE CONDUIT/RACEWAY DROPS TO MULTIPLE DEVICES OR APPLIANCES.
 INSTALLED WITHIN A SINGLE ROOM NOT EXCEEDING 92.9 M² (1000 FT²) IN AREA.

A.23.4.2.2
 A GOAL OF 23.4.2.2 IS TO PROVIDE ADEQUATE SEPARATION BETWEEN THE OUTGOING AND RETURN CABLES. THIS SEPARATION IS REQUIRED TO HELP ENSURE PROTECTION OF THE CABLES FROM PHYSICAL DAMAGE. THE RECOMMENDED MINIMUM SEPARATION TO PREVENT PHYSICAL DAMAGE IS 12 IN. (300MM) WHERE THE CABLE IS INSTALLED VERTICALLY AND 48 IN. (1.22M) WHERE THE CABLE IS INSTALLED HORIZONTALLY.

ANTICIPATED AMBIENT SOUND LEVELS	
BUSINESS OCCUPANCY	55DB
EDUCATIONAL OCCUPANCY	45DB
INSTITUTIONAL OCCUPANCY	50DB
MECHANICAL ROOMS	85DB
ASSEMBLY OCCUPANCY	55DB
RESIDENTIAL OCCUPANCY	35DB

This drawing and the information and design application herein contained is the property of BK Systems, Inc.; all information herein contained shall be treated as proprietary and confidential; no reproduction of this drawing or part thereof shall be made without the written consent of BK Systems, Inc.

BK SYSTEMS
 "BUILDING SYSTEMS SPECIALISTS"

BK SYSTEMS, INC.
 4 COTE AVENUE - GOFFSTOWN, NH 03045
 TEL.: (603) 647-8775 / FAX: (603) 647-4806
 www.bksystemsinc.com

REVISIONS	DATE
REV#1	07/01/13

USM - MASTERTON HALL
 PORTLAND, MAINE
 FIRE ALARM RISER DIAGRAM, NOTES, LEGEND
 PREPARED FOR:
 TRT ELECTRIC
 65 WASHINGTON STREET
 AUGUSTA, ME 04330

