



CIRCUITING NOTES
 ALL SITE LIGHTING SHALL BE CIRCUITED TO PANEL GN1. REFER TO PANEL SCHEDULES.

- OH--- OVERHEAD WIRING
- UG--- UNDERGROUND OR UNDERSLAB WIRING
- UTILITY POLE
- JUNCTION BOX, IN-GROUND
- Ⓜ 7'x12'x8" DEEP ELECTRICAL MANHOLE PER UTILITY SPECIFICATIONS, COORDINATE LOCATION WITH OTHER UNDERGROUND UTILITIES
- T PADMOUNT TRANSFORMER
- PB 4'x6' PULL BOX WITH 32" COVER PLATE IN ACCORDANCE WITH UTILITY STANDARDS
- P PEDESTAL LOCATION, PEDESTAL BY SERVICE PROVIDER, STUB UP (2) 2" CONDUITS WITH CONNECTORS AND BUSHINGS FROM HANDHOLE
- H HANDHOLE, MINIMUM 18"x36"x24", SIZE PER NEC FOR NUMBER OF CONDUITS INSTALLED
- M METER & CT CABINET, PEDESTAL MOUNTED
- SINGLE POLE MOUNTED LIGHT
- DOUBLE POLE MOUNTED LIGHT
- ← SINGLE POLE HOMERUN - (2)#12+(1)#12G UNO, CONNECT TO PANEL INDICATED
- ← SINGLE-PHASE HOMERUN OR MULTIPLE HOMERUN UTILIZING THE SAME CONDUIT, CONNECT TO PANEL INDICATED
- ← 3-PHASE HOMERUN OR MULTIPLE HOMERUN UTILIZING THE SAME CONDUIT, CONNECT TO PANEL INDICATED
- * BOLLARD LIGHT
- ⬇ GROUND MOUNTED LIGHT
- (E) EXISTING
- (R) REMOVE

F10 ELECTRICAL LEGEND
 NO SCALE

- ① MOUNT POLE HEAD ON 16" POLE.
- ② MOUNT POLE HEAD ON 16" POLE.
- ③ COORDINATE EXACT LOCATION OF ENTRANCE PEDESTAL WITH CIVIL.

E10 KEYED NOTES
 NO SCALE

- ① PRIMARY ELECTRIC - (3) 5"C
- ② TELEPHONE - (2) 4"C
 CATV - (1) 4"C
 SPARE - (1) 4"C
- ③ FEEDER TO 1999 ADDITION - (2) 4"C
 FEEDER TO EXISTING PANEL PPE - (1) 4"C
 FEEDER TO EXISTING PANEL PPE - (1) 4"C
 FEEDER TO EXISTING PANEL DPC - (2) 4"C
 FEEDER TO EXISTING PANEL LPB - (1) 3"C
 FEEDER TO EXISTING PANEL P24-25 - (1) 1-1/2"C
 FEEDER TO EXISTING PANEL HDA - (1) 4"C
 FEEDER TO EXISTING PANEL HDP - (1) 4"C
 FEEDER TO EXISTING PANEL DPA - (2) 3"C
 FEEDER TO EXISTING PANEL DPB - (2) 3"C
 FEEDER TO PANEL MN1 - (1) 3"C
 FEEDER TO PANEL MS1 - (1) 3"C
- ④ GENERATOR FEEDER - (3) 4"C
 GENERATOR ANNUNCIATOR - (1) 1"C
 GENERATOR SUPPORT BRANCH CIRCUITS - (2) 1"C
 GENERATOR CONTROL - (1) 1"C
- ⑤ TYPICAL SITE LIGHTING - (1) 1"C
- ⑥ ENTRANCE PEDESTAL POWER - (1) 3/4"C
 ENTRANCE PEDESTAL DATA - (1) 3/4"C
 SPARE - (1) 3/4"C
- ⑦ CCTV - (1) 1"C

D10 CONDUIT KEY
 NO SCALE

- ① TEMPORARY OVERHEAD PRIMARY BY UTILITY. COORDINATE WITH UTILITY.
- ② EXISTING PADMOUNT TRANSFORMER AND UNDERGROUND PRIMARY TO BE REMOVED. PROTECT AND MAINTAIN OPERATION UNTIL ALL EXISTING EQUIPMENT WITHIN EXISTING BUILDING HAS BEEN RE-FED.

C10 DRAWING NOTES
 NO SCALE

LAVALEE BRENSINGER ARCHITECTS
 155 Dow Street, Suite 400, Manchester, NH 03101
 92 Montvale Ave., Suite 2150, Stoneham, MA 02180
 NH: 603.622.5450 MA: 718.462.7263 www.LBPA.com

Allied Engineering
 Structural Mechanical Electrical Commissioning

160 Veranda Street
 Portland, Maine 04103
 T: 207.251.2368
 F: 207.251.2366
 Web: www.allied-eng.com

CATHERINE A. FAUCHER
 No. 7575
 PROFESSIONAL ENGINEER

Graphic Scale: 1" = 12' 0"

The Park Danforth

777 Stevens Ave, Portland, ME, 04103

NO.	DESCRIPTION	DATE
1	Addendum No 2	2015-06-25
2	Addendum No 4	2015-07-09



CONTENT:
 ELECTRICAL SITE PLAN

DRAWN BY: GMC

PROJECT NO: 12-056-00

DATE: 6/5/2015

REVISED:

SCALE: AS SHOWN

ES1.1

Project Phase
100% CONSTRUCTION DRAWINGS

COPYRIGHT © 2014 BY LAVALEE BRENSINGER PROFESSIONAL ASSOCIATION. ALL RIGHTS RESERVED. NO REPRODUCTION WITHOUT PERMISSION.

N:\Projects\2014\1418 - Park Danforth\00 Drawing Files - REVIT\2015\1418_EE.dwg - 04.09.2015 - 10:28am