		LIGHTIN ALL FIXTURES SHA LAMPS, HANGERS, FITTII		D COMPLE	TE WITH	ALL HARD		
7.05	MANUFACTURER	CATALOG NO.	1,550	VOLT			LAMPS	DEMARKS (DALLAST INFORMATION
TYPE			MTG.		NO.	WATT	TYPE	REMARKS/BALLAST INFORMATION
	HIGH BAY — ALUMINUM RE	FLECTOR			•			•
A	DAY-BRITE	HCF642CU-A24CF	P	120	6	42W	CFL	
	2' X 2' - PARABOLIC							
В	COLUMBIA	P422-317G-33-EU	R	120	3	17W	F17T8	
	TRACK HEAD							
С	HALO	L1701MB-L283MB	S	120	1	50W	PAR20	
	6" DOWNLIGHT CFL							
D	PRESCOLITE	LF6CFV42-6CFV-WT-B24	R	120	1	42W	CFL	
	DECORATIVE PENDANT — FISHER ISLAND							
E	FORECAST	F1852-68	P	120	4	26W	CFL	PROVIDE WITH SAFARI FABRIC SHADE AND ETCHED GLASS — MOUNT BOTTOM UP 8'AF
	DECORATIVE PENDANT — URBAN OASIS							
E1	FORECAST	F510-49	P	120	2	26W	CFL	PROVIDE WITH BEIGE ARTISAN PAPER SHADE AND ETCHED GLASS — MOUNT BOTTOM UP 8'AF
	DECORATIVE VANITY		<u> </u>				<u> </u>	
F	LITHONIA	11890 2' GEB 10IS	S	120	2	17W	F17T8	MOUNT ABOVE MIRROR
	4' STRIP							
G	COLUMBIA	K4-232-EU	S	120	2	32W	F32T8	
	MINI SCONCE - CFL						<u> </u>	
Н	GARDCO	111EMC-MT-26QF-120-BRP-PCB	S	120	1	26W	CFL	CENTER ABOVE DOOR

FIRE ALARM SYSTEM NOTE

THESE DOCUMENTS DO NOT FULLY COMPLY WITH THE REQUIREMENTS OF THE CITY OF PORTLAND FIRE DEPARTMENT. ADDITIONAL INFORMATION FOR FIRE ALARM SYSTEM EXTENSION THROUGHOUT THE PLAZA WILL BE REQUIRED TO FINALIZE SYSTEM DESIGN.

GENERAL NOTE

ELECTRICAL CIRCUITS INDICATED SHALL BE RUN TO OWNER PROVIDED PANEL IN ANYTIME FITNESS. COORDINATE EXACT PANEL LOCATION.

		<u>L E G E N D</u>
LP-	-1,3 ≪∰	HOMERUN TO PNLBRD - ARROWS INDICATE NUMBER OF CIRCUITS. CROSS LINES
A	٨	INDICATE NUMBER OF CONDUCTORS OTHER THEN TWO.
		CIRCUIT NUMBER(S)
		PANEL DESIGNATION
		WIRING CONCEALED IN WALL OR CEILING
		WIRING IN EXPOSED RACEWAY
	- UG -	WIRING IN RACEWAY CONCEALED UNDER FLOOR WIRING IN RACEWAY CONCEALED UNDERGROUND
	- UD -	WIRING IN UNDER FLOOR DUCT
		ITEMS SHOWN DASED ARE EXISTING
	- E -	EXISTING WIRING
		2' x 4' FLUORESCENT FIXTURE
		1' x 4' FLUORESCENT FIXTURE
		1' x 8' FLUORESCENT FIXTURE
		4' x 6" FLUORESCENT FIXTURE
		8' x 6" FLUORESCENT FIXTURE
		2' x 2' FLUORESCENT FIXTURE
	$\overline{\bullet}$	WALL MOUNTED FIXTURE
	0	CEILING MOUNTED FIXTURE
		RECESSED MOUNTED FIXTURE
	S	SINGLE POLE SWITCH - MTD CL UP 4'-0"
	Se	DOUBLE POLE SWITCH - MTD CL UP 4'-0"
	S3	THREE-WAY SWITCH - MTD CL UP 4'-0"
	So	DIMMER SWITCH - MTD CL UP 4'-0"
	S	SERVICE SWITCH
	0-	SIMPLEX RECEPTACLE - CL UP 15" OR AS NOTED
	÷	DUPLEX CONVENIENCE RECEPTACLE - MOUNTED - CL UP 18" OR AS NOTED
	•	DUPLEX CONVENIENCE RECEPTACLE - MOUNTED CL UP 48" OR AS NOTED
	-	GFCI DUPLEX CONVENIENCE RECEPTACLE - MOUNTED CL UP 48" OR AS NOTED
	€	DOUBLE DUPLEX RECEPTACLE IN TWO GANG WALL BOX — CL UP 18" OR AS NOTED
	M	TELEPHONE & DATA OUTLET IN SINGLE GANG WALL BOX— MOUNTED CL UP SAME AS ASSOCIATED RECEPTACLE
	K	TELEPHONE ONLY OUTLET — MOUNTED CL UP SAME AS ASSOCIATED DUPLEX RECEPTACLE, W= WALL CL UP 46"
	0	FLOOR MOUNTED DUPLEX RECEPTACLE — SEE PEDESTAL OR FLUSH FLOOR OUTLET DETAIL
	M	TELEPHONE/DATA OUTLET - MOUNTED UP SAME AS ASSOCIATED RECEPTACLE
	Mo	DATA OUTLET
	⋈ ≤	MODEM OUTLET
	IJ	JUNCTION BOX - SIZE AS REQUIRED OR AS INDICATED
		TELEPHONE (TEL) OR DATA (IDF) BACKBOARD — SIZE AS INDICATED
	_	LIGHTING/POWER PANELBOARD EXISTING PANELBOARD
	<u> </u>	POWER COMPANY METER
		FIRE ALARM DEVICES
	M	MASTER FIRE BOX — COORDINATE WITH LOCAL FIRE DEPARTMENT FOR
	[]	REQUIREMENTS
	ANN	FIRE ALARM ANNUNCIATOR PANEL
	E	FIREMANS KEY BOX
	FACP	FIRE ALARM CONTROL PANEL
	⊕ •• •• •• •• •• •• •• •• •• •• •• •• ••	SMOKE DETECTOR — MOUNTED ON CEILING
	₩1# ₩L	DUCT DETECTOR WITH SAMPLING TUBE - "S" = SUPPLY & "R" = RETURN FIRE ALARM HORN/LIGHT UNIT. CANDLE POWER (CD) PER NFPA 72 AND AS
	(F)E	NOTED - MOUNTED BOTTOM OF STROBE UP 80" ON WALL
		FIRE ALARM STROBE LIGHT UNIT. CANDLE POWER (CD) PER NFPA 72 AND AS NOTED — MOUNTED BOTTOM OF STROBE UP 80" ON WALL
	@	FIRE ALARM MINI-HORN/LIGHT UNIT. CANDLE POWER (CD) PER NFPA 72 AND AS NOTED - MOUNTED BOTTOM OF STROBE UP 80" ON WALL
	F	FIRE ALARM MANUAL PULL STATION - MOUNTED CL UP 4'-0" ON WALL
	FCPS	FIRE ALARM APPLIANCE/DEVICE POWER SUPPLY
	SFS	SPRINKLER FLOW SWITCH
	STS	SPRINKLER TAMPER SWITCH
	<u>- 1</u>	EMERGENCY LIGHTING DEVICES
	⊗ ‡	EXIT SIGN WITH ARROWS AS INDICATED — CEILING MOUNTED, EXCEPT AS NOTED
	₩	EXIT SIGN WITH ARROWS AS INDICATED — WALL MOUNTED TIGHT TO CEILING, EXCEPT AS NOTED
		EMERGENCY LIGHTING WITH BATTERY UNIT — WALL MOUNTED UP 7'-6". DUALLITE LZ-20-N
	9 2	EMERGENCY LIGHTING REMOTE HEAD WITH NUMBER OF HEADS AS INDICATED — MOUNTED UP 7'-6". NUMERAL INDICATES BATTERY UNIT CONNECTED TO.

Architects + Engineers

46 Harriman Drive

Authurn, ME 04210

207/784.5100 tel

129 Middle Street

Portland, ME 04101

207.775.0053 tel

One Perimeter Road

Manchester, NH 03103

603.626.1242 tel

www.harriman.com

© 2011

MISCELLANEOUS ---- ---- ----

TELEVISION COAXIAL OUTLET - MOUNTED UP SAME AS ASSOCIATED RECEPTACLE

EQUIPMENT LABEL - SEE EQUIPMENT SCHEDULE FOR WIRING REQUIREMENTS.

CONTROL PANEL

ELECTRIC DOOR HOLDER

WEATHER PROOF

KEYNOTE TAG

INTRUSION DETECTION SECURITY PANEL

MOTION DETECTOR - MOUNTED UP 7'-6" ON WALL

ACCESS KEY PAD - MOUNTED UP 4'-6" ON WALL

VERIFY EXACT LOCATION WITH ASSOCIATED PLAN.

C - INDICATES CEILING MOUNTED

RELAY OR CONTACTOR — SIZE AS REQUIRED OR AS INDICATED

DOOR SWITCH

DOOR LOCK

WESTGATE
SHOPPING CENTER
ANYTIME FITNESS
PORTLAND, MAINE

11110

Key Plan

HA Project No.

- 07-13-11 ISSUED FOR CONSTRUCTION
- 06-13-11 95% REVIEW

Mark Date Description

Issue Dates

Drawing Title

Drawing Status

ELECTRICAL SCHEDULES & LEGEND

Drawn By: **JWT**

Drawing Number

E00.1